EMC® Smarts®

Version 9.4.2

Installation Guide for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers

P/N 302-003-120
REV 01

EMC²

Copyright © 1996 - 2016 EMC Corporation. All rights reserved. Published in the USA.

Published September 2016

EMC believes the information in this publication is accurate as of its publication date. The information is subject to change without notice.

The information in this publication is provided as is. EMC Corporation makes no representations or warranties of any kind with respect to the information in this publication, and specifically disclaims implied warranties of merchantability or fitness for a particular purpose. Use, copying, and distribution of any EMC software described in this publication requires an applicable software license.

EMC^2, EMC, and the EMC logo are registered trademarks or trademarks of EMC Corporation in the United States and other countries. All other trademarks used herein are the property of their respective owners.

For the most up-to-date regulatory document for your product line, go to EMC Online Support (https://support.emc.com).

EMC Corporation
Hopkinton, Massachusetts 01748-9103
1-508-435-1000 In North America 1-866-464-7381
www.EMC.com

CONTENTS

Chapter 1 Overview

Product contents 10
Installation directory structure 13
Product and version compatibility 14
Installation tasks overview 14
Upgrade tasks overview 16
Migration tasks overview 17
Uninstallation tasks overview 19

Chapter 2 Performing an Installation

Installation overview 22
Installation prerequisites 23
Install the product 23
Install using Wizard mode 24
Install using CLI mode 28
Install using Unattended mode 30
Additional Service Assurance Manager installation tasks 32
Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both 32
Add additional features to a new installation 34
Support for FIPS 140-2 for 9.4.2 products 34
Enabling FIPS 140 mode on a new installation 35
Disabling FIPS 140 mode 38
Next steps 38

Chapter 3 NAS Installation and Startup

Overview 40
Installing and starting the HTTPS Adapter service 40
Running HTTPs adapter in FIPS mode 42

Chapter 4 Performing an Upgrade

Upgrade installation overview 46
Installer tasks 48
Installer-called utilities 48
Upgrade installation prerequisites 49
Upgrade the product 49
Add additional features to an upgrade installation 53
Upgrading 9.4.2 products in FIPS mode 54
Next steps 54

Chapter 5 Performing a Migration

Migration overview 56
Install and migrate on the same host 57
Migration procedure for the same host 58
Install and migrate on a different host 60
Migration procedure for a different host 61

Review license file migration 64
Migrate permanent license and set up FlexNet license server 65
Access to FlexNet license server using SM_LICENSE 67
Configuring license server behind the firewall 68
Post-migration tasks 68
Rename the repository file 69
Ensure that the Broker host:port is updated in the runcmd_env.sh files 69
Remove the old out-of-date service entries 70
Change the secret phrase to match rest of deployment 70
Uninstall the old software 70

Chapter 6 Migration Utilities

Customization migration utility overview 72
sm_migrate modes of operation 72
sm_migrate function 74
Customization migration procedures 76
Migrating customizations on the same host 76
Migrating customizations to a different host 78
Restoring customizations after an upgrade installation 81
Perform a rollback 82
Custom file migration use cases 83
Migration of security configuration files 85
Migration of dynamic model files 85
Three-way merge utility 86
Use cases for content block comparison 86
Configuration migration process logs 87
Automatically migrate topology for IP Manager using RPS utility 88
Functions of RPS migration utility 88
Running RPS migration utility 88
Deployment utility overview 89
Running the Deployment utility 90
sm_deploy modes of operation 90
To create a deployment package 91
Manage RPS file settings across multiple installations 91
To deploy the package 92
To Rollback 92

Chapter 7 Verifying the Installation

Check the version number 94
Obtain and install a temporary license file 95
Events and attributes for license expired alert 95
Start services 97
Starting services on UNIX 97
Starting services on Windows 97
Start programs 98
Service and program startup options 99
Start Smarts NOTIF 100
Verify the product status 102
Verify the FIPS 140 mode status 103
Collect system information 104
sm_getinfo files 104
sm_getinfo command-line syntax 105
sm_getinfo invocation examples 107

sm_getinfo data collection 107
Configuration Scanner Tool 108
Running the Configuration Scanner tool from the sm_getinfo utility 109

Chapter 8 Performing an Uninstallation

Before uninstallation 112
Remove manually installed services 112
Determine order for removing products (UNIX only) 112
Uninstall when same product software is installed twice (Windows only) 113
Detect and stop programs 113
Uninstall the FlexNet License Server 116
Uninstall EMC Smarts products 117
Uninstall using Wizard mode 117
Uninstall using CLI mode 118
Uninstall using Unattended mode 119

Appendix A The sm_edit utility

sm_edit 122
sm_edit example 122

Appendix B Manually Installing Services

Overview 124
Selection of bootstrap files when installing services 124
Broker services 124
Services for the IP Manager 125
IP Availability Manager-only server 125
IP Availability Manager-only server (interacting with EMC M&R) 126
IP Performance Manager-only Server 126
IP Performance Manager-only Server (interacting with EMC M&R) 127
IP Availability and Performance Manager Server 128
IP Availability and Performance Manager Server (interacting with EMC M&R) 128
IP Configuration Manager 129
IP Configuration Manager (interacting with EMC M&R) 130
Services for the Service Assurance Manager 131
EMC Smarts Broker 131
Service Assurance Manager (Presentation SAM server) 131
Service Assurance Manager (Global Manager) 132
Business Impact Manager server 132
Adapter Platform 133
Business Dashboard 133
Syslog Adapter 134
SNMP Trap Adapter 134
Notif trap Adapter 135
Notif syslog adapter 135
EMC Smarts Data Web Applications (Tomcat) 136
EMC Smarts Notification Exchange (Rabbit MQ) 136
EMC Smarts Notification Cache (ElasticSearch) 136
Services for the MPLS Manager 137
MPLS Topology Server 137
MPLS Monitoring Server 138
MPLS Analysis Server 138

MPLS VPN-Tagging Server 139
Services for the Server Manager 139
Server Manager 139
Services for the Network Protocol Manager installation 140
Network Protocol Manager for BGP 140
Network Protocol Manager for EIGRP 141
Network Protocol Manager for IS-IS 141
Network Protocol Manager for OSPF 142
Services for the Optical Transport Manager 143
EMC Smarts Optical Transport Manager for Next Generation WDM 143
EMC Smarts Optical Transport Manager for SDH (Topology) 144
EMC Smarts Optical Transport Manager for SDH (Analysis) 144
EMC Smarts Optical Transport Manager for PDH (Topology) 145
EMC Smarts Optical Transport Manager for PDH (Analysis) 145
EMC Smarts Optical Transport Manager for WDM (Topology) 146
EMC Smarts Optical Transport Manager for WDM (Analysis) 146
EMC Smarts Optical Transport Manager for IP Cross Domain Analysis 147
EMC Smarts TMF814 Cisco CTM Adapter for OTM 147
EMC Smarts TMF814 Ciena On-Center Adapter for OTM 148
Services for the VoIP Availability Manager 148
VoIP Availability Manager 148
VoIP Notification Trap Adapter 149

Appendix C Procedures for CD/DVD-ROMs

Mounting a CD/DVD-ROM on UNIX systems 152
Loading a CD/DVD-ROM on Windows 153

Appendix D Using the MPLS server_config Utility

Use the server_config.pl script to change domain names 156
Purpose 156
Run the script 156
Script options 157

Appendix E EMC Smart Optical Transport Manager Configuration

Prerequisites 162
Optical Transport Manager 162
SAM servers used with OTM 162
Global Manager 162
Configuring Optical Transport Manager 163
OTM settings 163
Configuring EMC M&R for the OTM Next Generation WDM Manager 163
Configure the RabbitMQ service for the OTM Next Generation WDM Domain Manager 165
OTM-Extensions 165
Configuration scenarios 166
Configuring the Service Assurance Manager 171
Configuring the presentation layer Global Manager 172

Appendix F Configuration Scanner tool Sample Output

Files created by Configuration Scanner tool 176
Sample outputs 176
Running Configuration Scanner tool with server name 176

Report when server is specified 177
Running Configuration Scanner tool without server name 182
Report when server is not specified 182

CHAPTER 1
Overview

This chapter describes the EMC Smarts Service Assurance Manager, EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, EMC Smarts Optical Transport Manager, and EMC Smarts VoIP Availability Manager, their compatibility with other EMC Smarts products, and installation tasks. It consists of the following topics:

- Product contents 10
- Product and version compatibility 14
- Installation tasks overview 14
- Upgrade tasks overview 16
- Migration tasks overview 17
- Uninstallation tasks overview 19

Product contents

This document provides installation, upgrade, migration, and uninstallation procedures for:

- EMC Smarts Service Assurance Manager
- EMC Smarts IP Manager
- EMC Smarts MPLS Manager
- EMC Smarts Server Manager
- EMC Smarts Network Protocol Manager
- EMC Smarts Optical Transport Manager
- EMC Smarts VoIP Availability Manager

The EMC Smarts Service Assurance Manager includes the following products:

- Service Assurance Manager

  The EMC Smarts Service Assurance Manager product includes the following components:

  - Global Manager
  - EMC Smarts Broker
  - EMC Smarts MBIM — Maintenance and Business Impact Manager Server
  - Generic notification adapters such as Log File, SNMP Trap, Script, and email
  - EMC Data Access API
    - Smarts Foundation EMC Data Access API (Smarts EDAA)
    - Alert EMC Data Access API (EDAA)
    - EMC Smarts Data Web Applications (Tomcat)
    - EMC Smarts Notification Exchange (Rabbit MQ)
    - EMC Smarts Notification Cache (ElasticSearch)

  NOTICE

  Some components, such as Business Impact Manager, require licensing.

- EMC M&R — EMC M&R is distributed with Service Assurance Suite. The *Service Assurance Suite Installation and Configuration Guide for EMC M&R* provides installation and configuration instructions. The *SolutionPack for EMC Smarts Summary Sheet* article provides instructions for installing the SolutionPack for EMC Smarts. The *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article provides instructions on configuring Service Assurance Manager to work with EMC M&R.

- Global Console

  The Global Console product is the graphical interface for all EMC Smarts products.

  Global Console functionality can also be deployed as a Web Console or a Business Dashboard.

- Adapter Platform

  The SAM Adapter Platform product provides functionality to import and normalize topology and events from outside the EMC Smarts domain.

- Syslog Adapter

  The Syslog Adapter product reads and processes system log (Syslog) messages. It requires the SAM Adapter Platform.

- Smarts Notification Module

  The Smarts Notification Module (NOTIF) augments EMC Smarts solutions with event management features that are configured through a graphical user interface (the Smarts NOTIF Editor). Smarts NOTIF enables the user to easily optimize the flow of events and notifications sent through any EMC Smarts system. Smarts NOTIF can be installed on either the SAM server or Adapter Platform server, or both. The internal event and notification processing features of the standard SAM Adapter Platform are replaced by Smarts NOTIF.

  NOTICE

  Smarts NOTIF functionality and architecture is discussed in the *EMC Smarts Notification Module User Guide*.

- Smarts Notification Module Cisco Syslog Processing Adapter

  The Smarts Notification Module Cisco Syslog Processing Adapter (referred to as the Smarts NOTIF Cisco Syslog Adapter) replaces the log file processing features of the standard Syslog Adapter. The Smarts NOTIF Cisco Syslog Adapter processes the log file information into useful notifications with or without the use of ASL scripts.

  NOTICE

  The *EMC Smarts Notification Module Cisco Syslog Processing Adapter Installation and User Guide* provides additional information on this adapter.

- SNMP Trap Adapter

  The SNMP Trap Adapter product reads SNMP traps and forwards traps to any EMC Smarts application. It requires the SAM Adapter Platform.

- XML Adapter

  The XML Adapter product imports and exports topology from any EMC Smarts application.

The EMC Smarts IP Manager includes the following products:

- IP Availability Manager
- IP Performance Manager

- IP Server Performance Manager
- IP Availability Manager Extension for NAS

The EMC Smarts MPLS Manager includes the following products:

- EMC Smarts MPLS Manager is composed of three servers:
  - MPLS Topology Server
  - MPLS Monitoring Server
  - MPLS Analysis Server
- MPLS VPN-Tagging Server

The EMC Smarts Network Protocol Manager includes the following products:

- EMC Smarts Network Protocol Manager for BGP
- EMC Smarts Network Protocol Manager for EIGRP
- EMC Smarts Network Protocol Manager for IS-IS
- EMC Smarts Network Protocol Manager for OSPF

The EMC Smarts Server Manager includes the Server Manager software.

The EMC Smarts Optical Transport Manager includes the following products:

- EMC Smarts Optical Transport Manager for Next Generation WDM
- EMC Smarts Optical Transport Manager for SDH (Topology and Analysis)
- EMC Smarts Optical Transport Manager for PDH (Topology and Analysis)
- EMC Smarts Optical Transport Manager for WDM (Topology and Analysis)
- EMC Smarts Optical Transport Manager for IP Cross Domain Analysis
- EMC Smarts TMF814 Cisco CTM Adapter for OTM
- EMC Smarts TMF814 Ciena On-Center Adapter for OTM

The VoIP Availability Manager includes the following products:

- EMC Smarts VoIP Availability Manager
- EMC Smarts VoIP Enablement Pack for Avaya
- EMC Smarts VoIP Enablement Pack for Cisco
- EMC Enablement Pack for ACME
- EMC Smarts VoIP Integration Pack for VoIP Performance Manager

Installation directory structure

The installation directory structure is shown in Figure 1 on page 14. All EMC Smarts products use the same basic installation directory structure.

In Figure 1 on page 14, notice that:

- BASEDIR, which is not an environment variable, is used in documentation to represent the top-level directory structure of an EMC Smarts product software installation.

  For UNIX, this location is /opt/InCharge/*‹product›*.

  For Windows, this location is C:\InCharge*‹product›*.

  BASEDIR represents:

  - For MPLS Manager —*‹installation_root_directory›/MPLS*
  - For IP Manager — *‹installation_root_directory›/IP*
  - For Service Assurance Manager — *‹installation_root_directory›/SAM*
  - For Server Manager — *‹installation_root_directory›/ESM*
  - For Network Protocol Manager — *‹installation_root_directory›/NPM*
  - For Optical Transport Manager — *‹installation_root_directory›/OTM*
  - For VoIP Availability Manager — *‹installation_root_directory›/VoIP*

  By default, EMC Smarts software is installed to BASEDIR/smarts.

  Optionally, you can specify the root of BASEDIR to be something different, but you cannot change the ‹product› location under the root directory.

- The EMC Smarts sm_edit utility ensures that modified files are always saved to the appropriate local area and that base (original) copies of the files remain unchanged. Appendix A, “The sm_edit utility,” provides additional information.

The *EMC Smarts System Administration Guide* provides detailed information about the directory structure for EMC Smarts software and the sm_edit utility.



Figure 1 Installation directory structure

Product and version compatibility

The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides information about the 9.4.2 products and the compatible versions of the EMC Smarts products.

Installation tasks overview

To install EMC Smarts Service Assurance Manager, IP Manager, MPLS Manager, Server Manager, Network Protocol Manager, Optical Transport Manager, or the VoIP Availability Manager, you need to meet the requirements or perform the tasks that are listed in Table 1 on page 14.

NOTICE

To install additional components to an existing installation, you can perform an installation or an upgrade.

Table 1 **Installation requirements and tasks (page 1 of 2)**

Before you install	
The Broker and FlexNet license host should be installed, configured, and operating.	*EMC Smarts System Administration Guide*

Table 1 Installation requirements and tasks (page 2 of 2)

The Global Console, Global Manager, and Service Assurance products should be installed, configured, and licensed.	*EMC Smarts Installation Guide for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*
EMC M&R product should be installed, configured, and licensed.	• *Service Assurance Suite Installation and Configuration Guide for EMC M&R* • *SolutionPack for EMC Smarts Summary Sheet* article • *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article
IP Manager should be installed, configured, and licensed. After IP Manager is installed, you can install or upgrade other Smarts products.	*EMC Smarts Installation Guide for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*
Review the important release issues for the product being installed.	*EMC Smarts Release Notes for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*
Obtain an evaluation or permanent license for the product.	"Obtain and install a temporary license file" on page 95
Determine if the products are supported on your platform.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*
Review the patch requirements for your operating system.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*
Determine if your system meets the hardware requirements.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*
Installation method	
Install the product.	Select one of the following installation methods: • "Install using Wizard mode" on page 24 • "Install using CLI mode" on page 28 • "Install using Unattended mode" on page 30
After you install	
Save your license in the proper location: • Evaluation license – Save ‹license_name›.lic to the BASEDIR/smarts/local/conf directory. • Permanent license – Use the procedures described in the *EMC Smarts System Administration Guide*.	"Obtain and install a temporary license file" on page 95
If your product is part of a deployment that requires the Federal Information Processing Standard (FIPS) Publication 140-2, a U.S. government computer security standard governing cryptographic modules, perform the procedure to enable products in FIPS mode.	"Support for FIPS 140-2 for 9.4.2 products" on page 34
If you installed the products as services, start them for the first time.	• "Starting services on UNIX" on page 97 • "Start programs" on page 98
Verify the current state of the products and the Broker.	"Verify the product status" on page 102
Optional task: After modifying your configuration files on one installation, you can use the deployment utility to create a deployment package of your configuration changes and deploy the package on other installations.	"Deployment utility overview" on page 89

Upgrade tasks overview

To upgrade, you need to meet the requirements or perform the tasks that are listed in Table 2 on page 16.

Table 2 Upgrade installation requirements and tasks (page 1 of 2)

Before you upgrade	
Review the release notes for important issues.	*EMC Smarts Release Notes for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*
Determine if the products are supported for your platform.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*
Determine if your system meets the hardware requirements.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*
Upgrade installation	
The order in which you upgrade products depends on whether the EMC M&R UI is included in your deployment. Upgrade the products in the following order: 1. Top-most SAM server If EMC M&R is included, this is the Presentation SAM server. If EMC M&R is not included, this is the top-most SAM server and related Service Assurance products and consoles in your deployment, either a SAM server or the top SAM server in a hierarchical SAM deployment. 2. If EMC M&R is included, update EMC M&R platform (core) components and the SolutionPack for EMC Smarts. Ensure that communication exists between the Presentation SAM server and the SolutionPack for EMC Smarts. 3. An Aggregation SAM server if it is a hierarchical SAM deployment. 4. IP Manager. 5. Any order: Server Manager, MPLS Manager, Network Protocol Manager, and VoIP Availability Manager. **Notice:** Presentation SAM server is the server that is configured in the SolutionPack for EMC Smarts for use with the EMC M&R UI. This does not mean that a hierarchical SAM is required.	• For EMC Smarts products: "Performing an Upgrade" on page 45 • For EMC M&R platform components: *Service Assurance Suite Installation and Configuration Guide for EMC M&R* • *SolutionPack for EMC Smarts Summary Sheet* article • *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article
After you install	
Evaluate your custom code and review the tools for restoring user customization.	"Custom file migration use cases" on page 83
(Optional) Update your license, if you installed additional products and they are not licensed features. Otherwise, existing licenses are supported for 9.4.2 products. No user action is required.	"Obtain and install a temporary license file" on page 95

Table 2 Upgrade installation requirements and tasks (page 2 of 2)

If your product is part of a deployment that requires the Federal Information Processing Standard (FIPS) Publication 140-2, a U.S. government computer security standard governing cryptographic modules, perform the procedure to upgrade products in FIPS mode.	"Upgrading 9.4.2 products in FIPS mode" on page 54
If you installed the products as services, start them for the first time.	• "Starting services on UNIX" on page 97 • "Start programs" on page 98
Verify the current state of the products and the Broker.	"Verify the product status" on page 102
(Optional) After performing an upgrade and modifying your configuration files on one installation, you can use the deployment utility to create a deployment package of your configuration changes and deploy the package on other installations. After deploying the package on other installations, you do not have to run the migrate utility to merge your customizations.	"Deployment utility overview" on page 89

Migration tasks overview

To migrate to Version 9.4.2, you need to meet the requirements or perform the tasks that are listed in Table 3 on page 17.

Table 3 Migration requirements and tasks (page 1 of 2)

Before you migrate	
Review the release notes for important issues.	*EMC Smarts Release Notes for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*
Determine if the products are supported for your platform.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*
Determine if your system meets the hardware requirements.	*EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*

Table 3 Migration requirements and tasks (page 2 of 2)

Installation and migration	
The order in which you migrate products depends on whether the EMC M&R UI is included in your deployment. Perform the migration in the following order: 1. Top-most SAM server If EMC M&R is included, this is the Presentation SAM server. If EMC M&R is not included, this is the top-most SAM server and related Service Assurance products and consoles in your deployment, either a SAM server or the top SAM server in a hierarchical SAM deployment. 2. If EMC M&R is included, migrate or update EMC M&R platform (core) components and the SolutionPack for EMC Smarts. Ensure that communication exists between the Presentation SAM server and the SolutionPack for EMC Smarts. 3. An Aggregation SAM server if it is a hierarchical SAM deployment. 4. IP Manager. 5. Any order: Server Manager, MPLS Manager, Network Protocol Manager, and VoIP Availability Manager. **Notice:** Presentation SAM server is the server that is configured in the SolutionPack for EMC Smarts for use with the EMC M&R UI. This does not mean that a hierarchical SAM is required.	• For EMC Smarts products: "Performing a Migration" on page 55. • For EMC M&R platform components: *Service Assurance Suite Installation and Configuration Guide for EMC M&R* • *SolutionPack for EMC Smarts Summary Sheet* article • *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article
After you install	
Evaluate your custom code and review the tools for restoring user customization.	"Custom file migration use cases" on page 83
If you installed the products as services, start them for the first time.	• "Starting services on UNIX" on page 97 • "Start programs" on page 98
Save your license in the proper location: • Evaluation license – Save ‹license_name›.lic to the BASEDIR/smarts/local/conf directory. • Permanent license – Use the procedures described in the *EMC Smarts System Administration Guide*. (Optional) Update your license, if you installed additional products and they are not licensed features. Otherwise, existing licenses are supported for 9.4.2 products. No user action is required.	"Obtain and install a temporary license file" on page 95
Verify the current state of the products and the Broker.	"Verify the product status" on page 102
(Optional) After performing a migration and modifying your configuration files on one installation, you can use the deployment utility to create a deployment package of your configuration changes and deploy the package on other installations. After deploying the package on other installations, you do not have to run the migrate utility to merge your customizations.	"Deployment utility overview" on page 89

Uninstallation tasks overview

To uninstall the product, you need to meet the requirements or perform the tasks that are listed in Table 4 on page 19.

Table 4 Uninstallation requirements and tasks

Before you uninstall	
Review uninstall prerequisites.	"Performing an Uninstallation" on page 111
Uninstallation	
Uninstall the product.	• "Uninstall using Wizard mode" on page 117 • UNIX only, "Uninstall using CLI mode" on page 118 • "Uninstall using Unattended mode" on page 119

CHAPTER 2
Performing an Installation

This chapter describes how to install a new installation of the EMC Smarts Service Assurance Manager, EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, EMC Smarts Optical Transport Manager, and EMC Smarts VoIP Availability Manager. It consists of the following topics:

- Installation overview 22
- Installation prerequisites 23
- Install the product 23
- Add additional features to a new installation 34
- Support for FIPS 140-2 for 9.4.2 products 34
- Next steps 38

Installation overview

The installation flow is shown in Figure 2 on page 22. A new installation installs a new version of a product on a host system that either has no software installed or has a previous version of the software installed. Chapter 4, "Performing an Upgrade," provides instructions to install an upgrade installation.



Figure 2 New installation flowchart

Installation prerequisites

Fulfill the following prerequisites before starting the installation:

- Ensure that you have superuser (User ID 0) or administrative privileges on the target host. The installation program will halt if you do not have the appropriate privileges.
- Ensure that the required operating system patches have been installed. Clicking **More Information** during the installation process will launch the System Information window and the Pass/Fail status of the operating system patches. The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides information on operating system patches.
- Determine the location of the EMC Smarts Broker.

  You must specify the location of the Broker during a new installation of EMC Smarts software. Typically, this location is chosen during the design of the EMC Smarts software deployment and before any installation begins. Consult with your deployment planner or check the build guide that documents your deployment to determine the name of the host where the Broker was installed and the port that the Broker uses.

  If the location is the same host where you are installing this product, the installation program will automatically install the Broker if it is not already on the host.
- (Service Assurance Manager only) Decide whether your operators will use the Service Assurance Manager Notification Console (classic SAM functionality) or the SolutionPack for EMC Smarts (in EMC M&R) to view and acknowledge notifications. If you plan to use the SolutionPack for EMC Smarts, you must install additional features and services when you install Service Assurance Manager.

Install the product

You acquire the software for the EMC Smarts Service Assurance Manager, EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, EMC Smarts Optical Transport Manager, and EMC Smarts VoIP Availability Manager in one of two ways:

- From the installation CD/DVD-ROM.

  Insert the CD/DVD-ROM into the optical drive of the host system. Appendix C, “Procedures for CD/DVD-ROMs,” describes how to access the optical drive for various operating systems.

  When you insert the installation CD/DVD, several minutes might pass between the InstallShield preparation screen and the EMC Smarts splash screen/installation dialog boxes. Be patient. Do not eject/reinsert the CD/DVD to start a second install process.
- From the EMC online support website.

  Go to the EMC online support website and download the installation file that is specific to your platform.

You install each product in one of three ways: Wizard mode, CLI mode, or Unattended mode.

Install using Wizard mode

Wizard mode provides a graphical user interface to the installation program for UNIX and Windows platforms.

On UNIX systems, Wizard mode uses the X Window System to display the installation wizard. The host on which you install the EMC Smarts software and the host where you log in must be configured to run the X Window System. Before starting the installation program using the Wizard mode, verify that the X Window System is running.

At the start of the installation, the installation program detects and stops all services, scheduled jobs, and processes that use programs or libraries that are running from the previous installation. It also stops the service daemon, sm_serviced, if it is running.

Be aware that In some cases, on Windows, services cannot be stopped by the installation program because multiple threads are locking the services. In those cases, use the Windows Control Panel to stop the services manually.

NOTICE

For instructions on installing the Service Assurance Manager Server in wizard mode, complete the steps in the following section. To install other Service Assurance Manager products after Server install, refer to "Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both" on page 32, and "Add additional features to a new installation" on page 34.

Running Wizard mode

1. Run the setup command that is appropriate for the operating system as shown in Table 5 on page 24.

Table 5 Server setup command syntax for Wizard mode (page 1 of 2)

Product	Operating system	Setup command
Service Assurance Manager Server **Notice:** For setup command syntax for other Service Assurance Manager products, refer to "Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both" on page 32.	Linux	./setup-SAM-9_4_2_0-linux64.bin
	Windows	setup-SAM-9_4_2_0-win64.exe
IP Manager	Linux	./setup-IP-9_4_2_0-linux64.bin
	Windows	setup-IP-9_4_2_0-win64.exe
MPLS Manager	Linux	./setup-MPLS-9_4_2_0-linux64.bin
	Windows	setup-MPLS-9_4_2_0-win64.exe
Server Manager	Linux	./setup-ESM-9_4_2_0-linux64.bin
	Windows	setup-ESM-9_4_2_0-win64.exe

Table 5 Server setup command syntax for Wizard mode (page 2 of 2)

Product	Operating system	Setup command
Network Protocol Manager	Linux	./setup-NPM-9_4_2_0-linux64.bin
	Windows	setup-NPM-9_4_2_0-win64.exe
Optical Transport Manager	Linux	./setup-OTM-9_4_2_0-linux64.bin
	Windows	setup-OTM-9_4_2_0-win64.exe
VoIP Availability Manager	Linux	./setup-VOIP-9_4_2_0-linux64.bin
	Windows	setup-VOIP-9_4_2_0-win64.exe

NOTICE

UNIX users: If the current directory is not set in your PATH variable, prepend the command with./ (a period followed by a forward slash).

The InstallShield wizard dialog box appears and closes. The **Shutdown Programs** dialog box and the **Welcome** screen appear.

2. Click **OK** in the **Warning** dialog box.

   If stopping services is necessary, you will be prompted with specific instructions later in the installation process.

3. Click **Next** in the **Welcome** screen.

   Next is disabled if you do not have administrative privileges and a message also appears. To install, you must restart the installation with the appropriate privileges.

4. Read and accept the EMC Corporation end user license agreement and click **Next**.

5. If the installation program detects an existing installation of the same product, the **Upgrade or Install** screen appears. In the **Upgrade or Install** screen, select **Install products to a new directory**.

6. Click **Next** to accept the default installation directory or type your preferred directory and click **Next**.

   The default installation directory is:

   If you specify a directory, the directory name cannot contain spaces. If the specified directory does not exist, it will be created. If you do not have write privileges, an error message appears.

7. In the **Installation Type** screen, select:
   - **Complete** to install all the products, including the EMC Data Access API (EDAA) feature. Click **Next**.
   - **Custom** to install a specific product. Click **Next**.
     a. In the **Choose Products** screen, clear the checkboxes for products that you do not want to install (by default, all products are selected).
     b. (Service Assurance Manager only)

        If you plan to use the EMC M&R UI and the Service Assurance Manager in this installation as the Presentation SAM server (interoperate with the SolutionPack for EMC Smarts), ensure you select **Service Assurance Manager** and **EMC Data Access API (EDAA)**.

        If you want to use the Service Assurance Manager and the EMC Data Access API (EDAA) feature without the EMC M&R UI, ensure you select **Service Assurance Manager** and **EMC Data Access API (EDAA)**.
     c. Click **Next.**
8. In the **Services Selection** screen, select the products that you want to install as services and click **Next**. If you do not install services at this point, you will need to install them manually later.

   For Service Assurance Manager services, you have two choices:
   - Select **EMC Smarts Service Assurance Manager Server** if you plan to run only the Service Assurance Manager.
   - Select **EMC Smarts Service Assurance Manager Server (notification cache publishing)** if you plan use the EMC M&R UI and the Service Assurance Manager.

   When installed as services, the products start automatically whenever the host starts up. EMC Corporation recommends that EMC Smarts products be installed as services whenever possible.

   If you are migrating from a previous version to 9.4.2 on the same host, you need to decide whether to install services during the 9.4.2 installation or to install them manually after the installation. Installing services during the installation will override the services for the previous version of installed products.

   For the same-host migration scenario, and assuming that you want to continue to run the previous version of installed products, you have two choices:
   - Install services during the 9.4.2 installation and then, after the installation, manually install services with unique names for the previous version of installed products.
   - Do not install services during the 9.4.2 installation and then, after the installation, manually install services with unique names for the 9.4.2 products.

   Appendix B, “Manually Installing Services,” describes how to install services manually.

9. (Service Assurance Manager only) If you selected the **EMC Smarts Service Assurance Manager Server (notification cache publishing)** service, select the EMC Data Access API services for:
   - **EMC Smarts Data Web Applications (Tomcat)**
   - **EMC Smarts Notification Exchange (Rabbit MQ)**
   - **EMC Smarts Notification Cache (ElasticSearch)**
10. (MPLS Manager only) The Domain Group Naming screen is displayed. Either accept the default (INCHARGE-MPLS) or enter a new name.

    The domain group name is the name given to the MPLS Manager that is made up of MPLS Topology Server, MPLS Monitoring Server, and MPLS Analysis Server. If you change the name of the MPLS Manager, the names of the three servers are changed accordingly.

    NOTICE

    You may want to define Domain Groups by geographical coverage. You could create a Domain Group for corporate headquarters and change INCHARGE-MPLS to HQ-MPLS, and later, a group for South America as SA-MPLS. The only requirement at this time is that you must install all services for any Domain Group on the same host. Even if you know that you are going to change the name of the Domain Group, you can perform the renaming step later, either through the Global Console or through a script from the command line. Appendix D, "Using the MPLS server_config Utility," provides more information.

11. In the **Broker Specification** screen, specify the EMC Smarts Broker.
    - If you are installing the Broker as a service, specify the port. The hostname defaults to localhost, where localhost is a literal name.
    - If the Broker is already running on this host, keep the default values.
    - If the Broker is running on another host, specify the hostname of that system and the port that the Broker uses.

    Click **Next** to continue.
12. The **Installation Criteria** screen appears. Review the list of products that will be installed and the target installation directory. At the bottom of the list, the total amount of disk space that is required for the selected products is provided so that you can verify that adequate disk space is available. To install the products, click **Next** and the **Installation Progress** screen appears.
13. Upon completion, the **Installation Summary** shows informational messages such as successful confirmations, error messages, and warnings. Investigate any errors or warnings.

    If **Next** appears, your system needs to be rebooted because one or both of the following tasks are pending on the system:
    - A system-protected file was replaced during the installation and requires a restart.
    - A pending restart was triggered by another application or by an operating system patch installation.

    Click **Next** and then reboot your system. Otherwise, click **Finish** to exit the installation.

The installation program writes an install log file to the BASEDIR/smarts/setup/logs directory, unless the installation fails at the very start, in which case the installation program writes the log file to the /tmp directory. The log file is a text file with the naming convention Install.‹product›.‹productversionNumber›.log.

14. If your product is part of a deployment that requires the Federal Information Processing Standard (FIPS) Publication 140-2, a U.S. government computer security standard governing cryptographic modules, follow the instructions in "Support for FIPS 140-2 for 9.4.2 products" on page 34.
15. "Next steps" on page 38 provides post-installation tasks.

NOTICE

For instructions on installing the Service Assurance Manager Server in CLI mode, complete the steps in the following section. To install other Service Assurance Manager products after Server install, refer to "Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both" on page 32.

Install using CLI mode

CLI mode provides a text-based method for invoking the installation program. This mode is intended for UNIX platforms with non-graphics consoles. The CLI mode follows the same process flow as the Wizard mode but uses text rather than graphics.

Running CLI mode

To start the CLI mode, invoke the setup command with the **-console** command-line option.

Table 6 Setup command syntax for CLI mode (page 1 of 2)

Product	Operating system	Executable
Service Assurance Manager Server	Linux	./setup-SAM-9_4_2_0-linux64.bin -console
	Windows	setup-SAM-9_4_2_0-win64.exe -console
Service Assurance Manager Console	Linux	./setup-CONSOLE-9_4_2_0-linux.bin -console
	Windows	setup-CONSOLE-9_4_2_0-win.exe -console
IP Manager	Linux	./setup-IP-9_4_2_0-linux64.bin -console
	Windows	setup-IP-9_4_2_0-win64.exe -console
MPLS Manager	Linux	./setup-MPLS-9_4_2_0-linux64.bin -console
	Windows	setup-MPLS-9_4_2_0-win64.exe -console
Server Manager	Linux	./setup-ESM-9_4_2_0-linux64.bin -console
	Windows	setup-ESM-9_4_2_0-win64.exe -console

Table 6 Setup command syntax for CLI mode (page 2 of 2)

Product	Operating system	Executable
Network Protocol Manager	Linux	./setup-NPM-9_4_2_0-linux64.bin -console
	Windows	setup-NPM-9_4_2_0-win64.exe -console
Optical Transport Manager	Linux	./setup-OTM-9_4_2_0-linux64.bin -console
	Windows	setup-OTM-9_4_2_0-win64.exe -console
VoIP Availability Manager	Linux	./setup-VOIP-9_4_2_0-linux64.bin -console
	Windows	setup-VOIP-9_4_2_0-win64.exe -console

User selections and navigation in CLI mode

During the installation and uninstallation processes, you are prompted with a series of steps and menus:

- For prompts, accept the default value or select another choice. The default values are indicated in brackets. To accept the default value, press **Enter**. To reply "yes," enter **y** or **Y**; to reply "no," enter **n** or **N**. Do not press **Delete** because doing so will cause the process to terminate with an error message.
- For selections in menus, accept the default selections or type the number of the item and press **Enter**. The default values are indicated in brackets or as pre-defined selections in menus. An **X** is used to indicate the selected item. When you are finished making selections, type zero (**0**) and press **Enter**.

If you incorrectly type an entry, press **5** to repeat the prompt and select the correct value. Arrow keys and the Backspace key are not supported.

To navigate between each step, use the keys described in Table 7 on page 29.

Table 7 Navigation keys

Key	Operation
1	Next, continue to the next step
2	Previous, go back to the previous step
3	Cancel, terminate the program
5	Redisplay, repeat the step
0	Accept the marked ([X]) menu choice

If your product is part of a deployment that requires the Federal Information Processing Standard (FIPS) Publication 140-2, a U.S. government computer security standard governing cryptographic modules, follow the instructions in "Support for FIPS 140-2 for 9.4.2 products" on page 34.

"Next steps" on page 38 provides post-installation tasks.

Install using Unattended mode

Unattended mode is supported for all operating systems, but separate response files are needed for UNIX and Windows systems. Unattended mode reads the selections and settings for the installation from a user-modifiable response file, which enables you to easily duplicate the installation on many computer systems. Manual intervention is not necessary after you execute the setup command.

The response file, named ‹product›-response.txt, is located on the CD/DVD-ROM in the /utils directory. The file provides instructions and examples of command line options that are passed to the installation program in Unattended mode. The command line options are organized by process flow, which is almost identical to that of Wizard mode or CLI mode.

NOTICE

For instructions on installing the Service Assurance Manager Server in Unattended mode, complete the steps in the following section. To install other Service Assurance Manager products after Server install, refer to "Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both" on page 32.

Modifying the response file

To modify the response file:

1. Copy the response file from the CD/DVD's /utils directory to a directory on your host, for example, to the /tmp directory.
2. Using a text editor, modify the values for the command line options in the response file:
   a. Specify the target directory.
   b. Select a directory for the process log file.
   c. Select the products to install. Ensure that the property value for the product is set to **true**.
   d. Select the products to start as services. Ensure that the property value for the product is set to **true**.
   e. Specify the location of the Broker. By default, the location is set to localhost at port 426.
3. Save the file.

Running Unattended mode

To start the Unattended mode, invoke the setup command with the -options command-line option, followed by the full path to the response file as described in Table 8 on page 31.

Table 8 Setup command syntax for Unattended mode

Product	Operating system	Executable
Service Assurance Manager Server	Linux	./setup-SAM-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-SAM-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
Service Assurance Manager Console	Linux	./setup-CONSOLE-9_4_2_0-linux.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-CONSOLE-9_4_2_0-win.exe -options ‹*path*›\‹*product*›-response.txt
IP Manager	Linux	./setup-IP-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-IP-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
MPLS Manager	Linux	./setup-MPLS-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-MPLS-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
Server Manager	Linux	./setup-ESM-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-ESM-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
Network Protocol Manager	Linux	./setup-NPM-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-NPM-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
Optical Transport Manager	Linux	./setup-OTM-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-OTM-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
VoIP Availability Manager	Linux	./setup-VOIP-9_4_2_0-linux64.bin -options ‹*path*›/‹*product*›-response.txt
	Windows	setup-VOIP-9_4_2_0-win64.exe -options ‹*path*›\‹*product*›-response.txt
where ‹*path*› is the fully qualified path to the response file and ‹*product*› is the product name, for example, IP_NETWORK_SUITE, MPLS_SUITE, or SAM_SUITE.		

For example for MPLS Manager, to start the Unattended mode of installation on Linux when the response file is located in /opt/home, enter:

```
./setup-MPLS-9_4_2_0-linux64.bin -options /opt/home/MPLS_SUITE-response.txt
```

If your product is part of a deployment that requires the Federal Information Processing Standard (FIPS) Publication 140-2, a U.S. government computer security standard governing cryptographic modules, follow the instructions in "Support for FIPS 140-2 for 9.4.2 products" on page 34.

"Next steps" on page 38 provides post-installation tasks.

Additional Service Assurance Manager installation tasks

If you are installing other Service Assurance Manager components such as the:

- Service Assurance Manager Console
- Smarts NOTIF Editor
- Both the Service Assurance Manager Console and the Smarts NOTIF Editor

follow one of the installation procedures for each component included in, "Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both" on page 32.

You can view and acknowledge notifications in the Notification Console in Service Assurance Manager or you can manage notifications from the EMC M&R user interface by installing the SolutionPack for EMC Smarts. The *SolutionPack for EMC Smarts Summary Sheet* article provides installation instructions. The *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article provides instructions on configuring Service Assurance Manager to work with EMC M&R.

Installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both

This section describes the steps for installing the Service Assurance Manager Console, or the Smarts NOTIF Editor, or both the Service Assurance Manager Console and the Smarts NOTIF Editor. Make sure you install the Service Assurance Manager Server first.

Install Service Assurance Manager Console, or the Smarts NOTIF Editor, or both using Wizard mode

To install the Service Assurance Manager Console:

1. Run the Setup command appropriate for the operating system listed in Table 9 on page 32.

Table 9 Console setup command syntax for Wizard mode

Operating system	Setup command
Linux	./setup-CONSOLE-9_4_2_0-linux.bin
Windows	setup-CONSOLE-9_4_2_0-win.exe

   The **InstallShield wizard** dialog box appears and closes. The **Shutdown EMC Smarts Programs** dialog box and the **Welcome** screen appear.

2. Click **OK** in the **Warning** dialog box.

   If stopping services is necessary, specific instructions prompts appear later in the installation process.

3. Click **Next** in the **Welcome** screen.

   Next is disabled if you do not have administrative privileges and a message also appears. To install, you must restart the installation with appropriate privileges.

4. Read and accept the EMC Corporation end user license agreement and click **Next**.

5. If the installation program detects an existing installation of the same product, the **Installation Type** screen appears.

   Select **Install the product to a new directory**.

   NOTICE

   This screen does not display if you are installing the product for the first time on the system.

6. Click **Next** to accept the default installation directory or type your preferred directory and click **Next**.

   If you specify a directory, the directory name cannot contain spaces. If the specified directory does not exist, it will be created. If you do not have write privileges, an error message appears.

7. In the **Setup** screen, select one of the following:

   - **Complete** to install all Service Assurance Manager Console components. Click **Next**.
   - **Custom** to install a specific product. Click **Next**.
     a. Clear products that you do not want to install (by default, all products are selected). From this screen, you may choose to install either the Global Console or the Smarts NOTIF Editor.
     b. Click **Next**.

8. In the **type of Global Console installation** screen, select:

   - **Global Console**, **Web Console**, and **Business Dashboard**. Click **Next**.
   - **Global Console**. Click **Next**.

9. The **Services Selection** screen appears. Select the products that you want to install as services and click **Next**. If you do not install services at this point, you must install them manually later.

   If you have an older version of a service running on the host, you must stop that service before installing a new version of the service.

   NOTICE

   When installed as services, EMC Smarts products start automatically when the system starts up. If the system is stopped and restarted, the EMC Smarts products restart automatically. EMC Corporation recommends that EMC Smarts products be installed as services whenever possible. If any of the products that are being installed can be started as services, these products are displayed in the services selection screen.

10. Specify the EMC Smarts Broker:

    - If the Broker is already running on this host, keep the hostname default value and change the Broker port accordingly if it is not running on port 426.
    - If the Broker is running on another host, specify the hostname of that system and the port the Broker uses.

    Click **Next** to continue.

11. Review the list of products that will be installed and the target installation directory. At the bottom of the list, the total amount of disk space required for the selected products is provided so that you can verify that adequate disk space is available. To install the products, click **Next** and the **Installation Progress** screen appears.
12. Upon completion, the **Installation Summary** displays informational messages such as successful confirmations, error messages, and warnings. Click **Finish** to exit the installation. It is not necessary to restart the system after installation.

    Investigate any errors or warnings. The log file is a text file with the naming convention Install.*<product>*.*<productversionNumber>*.log. It is located in the BASEDIR/smarts/setup/logs directory. If the installation process fails, the log files are located in the /tmp directory.
13. "Next steps" on page 38 provides information on post-installation tasks.

Install Service Assurance Manager Console, or the Smarts NOTIF Editor, or both using CLI mode

"Install using CLI mode" on page 28 provides information on installing Service Assurance Manager Console, or the Smarts NOTIF Editor, or both using CLI mode.

Install Service Assurance Manager Console, or the Smarts NOTIF Editor, or both using unattended mode

"Install using Unattended mode" on page 30 provides information on installing Service Assurance Manager Console, or the Smarts NOTIF Editor, or both using unattended mode.

Add additional features to a new installation

If after installing a new installation you want to add products to the new installation, run the installation again, select the **Add additional features** option in the **Upgrade or install** screen, and select all products that are already installed plus any other products that you would like to install in the new installation. Then proceed to "Next steps" on page 38.

Support for FIPS 140-2 for 9.4.2 products

The Federal Information Processing Standard (FIPS) Publication 140-2 is a U.S. government computer security standard governing cryptographic modules. FIPS 140 is required for any software purchased by the U.S government and U.S military. This release specifically addresses U.S Government accounts which require FIPS 140 compliance.

A configuration parameter, *SM_FIPS140*, has been introduced for FIPS 140 in the runcmd_env.sh file. The SAM or EMC Smarts administrator can enable or disable this parameter as required. The default value of this parameter is *FALSE*.

FIPS 140 mode allows you to use SNMP V1, SNMPV2C, SNMP V3, with SHA and AES 128 protocols. FIPS 140 does not support the DES privacy protocol or the MD5 authentication protocol. When you discover an SNMPv3 device, you need to select the option “V3” in the “Add Agent” window. The “Authentication Protocol” option lists only SHA and not MD5, and the “Privacy Protocol” option lists only AES and not DES. This is because MD5 and DES are not supported in FIPS 140 mode. When you discover SNMPv3 devices with MD5 and DES protocol as seed, the devices go to the Pending List and display as “Invalid” or “Unsupported SNMP V3 protocol.”

NOTICE

FIPS 140 mode cannot be enabled or disabled after a server is started. FIPS 140-enabled Domain Managers such as MPLS Manager, IP Manager, Service Assurance Manager, and Server Manager can work only with the SAM Global Console 9.x or later for FIPS 140-2 mode.

A non-FIPS 140 mode Broker will not be able to communicate with a FIPS 140-enabled Manager (IP server, SAM server, or Domain Manager). Trying to establish such a connection will result in the enabled Manager going into a DEAD state after couple of minutes. Communication should always happen between FIPS 140-enabled Brokers and Managers.

Inter-domain and FIPS 140 Broker communication happens only when the Broker, Managers, and the SAM Console are all in FIPS 140 mode, else the application will not be operational.

This section covers the following scenarios for FIPS 140:

- “Enabling FIPS 140 mode on a new installation” on page 35
- “Disabling FIPS 140 mode” on page 38
- “Verify the FIPS 140 mode status” on page 103

Enabling FIPS 140 mode on a new installation

When you install a 9.4.2 product, FIPS 140 is not enabled by default. You must enable FIPS 140 on a clean installation or an upgrade, before the servers are started, using the following procedure:

1. Back up the *imk.dat*, *brokerConnect.conf*, *serverConnect.conf* and *clientConnect.conf* files from the existing installation. These files are located in the *BASEDIR/local/conf* folder.

   NOTICE

   The backup is necessary in case you need to disable FIPS 140 mode and remove FIPS 140-2 encryption.

2. Run the following command at the command line prompt:

   sm_rebond --upgrade --basedir=<*BASEDIR*>/smarts

   For example for Service Assurance Manager, run the command:

   UNIX

   sm_rebond --upgrade --basedir=/opt/InCharge/SAM/smarts

   Windows

   sm_rebond --upgrade --basedir=C:\InCharge\SAM\smarts

   NOTICE

   The path must be set to the default install path. Regardless of the FIPS 140 state, the sm_rebond command must be invoked from the BASEDIR where the software is installed, not from any other product installation area which also has the sm_rebond utility.

3. When prompted, type a password to regenerate the *imk.dat* file. The default password is *Not a secret*.

4. Set the value for the parameter **SM_FIPS140** to **TRUE** in the *runcmd_env.sh* file. The file is located under the *BASEDIR/smarts/local/conf* directory.

Enabling FIPS 140 mode on SAM Web Console

1. Perform steps 1 - 3 as described in the section, "Enabling FIPS 140 mode on a new installation" on page 35.

2. Go to the ‹BASEDIR›/smarts/jre/lib/security folder, and in the java.security file, change:

   "sun.security.rsa.SunRsaSign" to "com.rsa.jsafe.provider.JsafeJCE" and "com.sun.net.ssl.internal.ssl.Provider" to "com.rsa.jsse.JsseProvider."

3. Set the value for the parameter SM_FIPS140 to TRUE in the runcmd_env.sh file. This file is located under the ‹BASEDIR›/CONSOLE/smarts/local/conf folder of your Global Console installation.
   or
   Use "-Dcom.smarts.fips_mode=true" as a command line parameter for the sm_gui command.

Enabling FIPS 140 mode on SAM Dashboard

1. Perform steps 1 - 3 as described in the section, "Enabling FIPS 140 mode on a new installation" on page 35.
2. Set the value for the com.smarts.fips_mode to TRUE in the corresponding webconsole.properties file (located under ‹BASEDIR›/InCharge/CONSOLE/smarts/tomcat/webapps/webconsole folder)
   or
   dashboard.properties file (located under ‹BASEDIR›/InCharge/CONSOLE/smarts/tomcat/webapps/templates).
3. Set the value for the parameter SM_FIPS140 to TRUE in the runcmd_env.sh file. This file is located under the ‹BASEDIR›/CONSOLE/smarts/local/conf folder of your Global Console installation.
   or
   Use "-Dcom.smarts.fips_mode=true" as a command line parameter for the sm_gui command.

Enabling FIPS 140 mode on SAM NOTIF

1. Perform steps 1 - 3 as described in the section, "Enabling FIPS 140 mode on a new installation" on page 35.
2. Go to the ‹BASEDIR›/CONSOLE/smarts/notif/editor/ or the ‹BASEDIR›/SAM/smarts/notif/editor folder, and edit the NotifGui.bat/NotifGui.sh file to replace the string, "com.netmg.notif.gui.NotifApplication" with "-Dcom.smarts.fips_mode=true com.netmg.notif.gui.NotifApplication."
3. Set the value for the parameter SM_FIPS140 to TRUE in the runcmd_env.sh file. This file is located under the ‹BASEDIR›/CONSOLE/smarts/local/conf folder of your Global Console installation.
   or
   Use "-Dcom.smarts.fips_mode=true" as a command line parameter for the sm_gui command.

NOTICE

If you install the servers as a service on Linux platforms, the services will start automatically after you issue the sm_rebond command. First stop the services, modify SM_FIPS140=TRUE in the runcmd_env.sh file, and then manually start the services.

After enabling FIPS 140 mode, when you start the broker and the SAM server, you may see the following message in the server log:

```
"CI-W-NOCGSS-No certificate loaded for INCHARGE-AM, generating
   self-signed certificate."
```

This message is generated because FIPS 140 requires secure communication, which can be achieved using SSL. If this certificate is not available, the SAM Manager generates a self-signed certificate. This message is benign in nature and does not impact functionality.

Disabling FIPS 140 mode

To disable FIPS 140:

1. Replace the *imk.dat*, *brokerConnect.conf*, *serverConnect.conf* and *clientConnect.conf* files in the *BASEDIR/local/conf* folder, with the copies saved from prior to """Enabling FIPS 140 mode on a new installation" on page 35". If you do not have a copy of these files saved, contact Technical Support.
2. Set the value for the **SM_FIPS140** parameter to **FALSE** in the *runcmd_env.sh* file. This file is located under *BASEDIR/smarts/local/conf/runcmd_env.sh.*
3. Restart all processes, such as the Broker, Domain Managers, SAM Global Manager, and Global Console.

NOTICE

RPS files started under FIPS mode cannot be re-used in non-FIPS mode. Domains will need to be started either from scratch or pre-FIPS RPS files can be used in cases where topologies have not changed. Restoring from older RPS files may not be productive as it will not contain any recent topology.

Next steps

Perform the following tasks:

- "Obtain and install a temporary license file" on page 95 describes tasks for obtaining and saving a new license file.
- Chapter 5, "Performing a Migration," describes additional tasks if you are migrating from a previous version of the product.
- Chapter 7, "Verifying the Installation," describes tasks for verifying the proper installation of the software and starting services.
- For EMC Smarts Optical Transport Manager (OTM), complete the post-installation configuration tasks as described in Appendix E, "EMC Smart Optical Transport Manager Configuration."

CHAPTER 3
NAS Installation and Startup

This chapter covers installation and startup issues for the EMC Smarts IP Availability Manager Extension for NAS. Topics in this chapter are:

- Overview 40
- Installing and starting the HTTPS Adapter service 40

Overview

The NAS Extension is installed with the IP Availability Manager. After installation, the IP Availability Manager can discover NAS devices, and perform root cause and impact analysis on these devices.

Configuring the NAS Extension involves the tasks summarized in Table 10 on page 40.

Table 10 Steps for configuring the NAS Extension

Procedure	Reference
If necessary, configure the HTTPS Adapter to support access to the managed Celerra devices.	For information about this requirement, refer to the "Configuring Control Station usernames and passwords" chapter in the *EMC Smarts IP Manager User Guide*.
If necessary, configure external Control Station and Data Mover IP addresses.	For information about this requirement, refer to the "Configuring Control Station and Data Mover IP addresses" chapter in the *EMC Smarts IP Manager User Guide,* which also refers you to the appropriate EMC documentation, if needed.
Install the HTTPS Adapter as a service and start the service.	"Installing and starting the HTTPS Adapter service" on page 40.
Start the IP Availability Manager.	*EMC Smarts Installation Guide for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*
Start the Global Manager.	*EMC Smarts Installation Guide for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*. For configuration information, refer to the *EMC Smarts Service Assurance Manager Configuration Guide*.
Start the Global Console.	*EMC Smarts Installation Guide for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*.

Installing and starting the HTTPS Adapter service

The NAS Extension software includes an adapter process (the HTTPS Adapter), which probes the Celerra devices using the HTTPS/XML probe to obtain internal topology information. While the installation of this adapter is automatic, you must install the service and start it manually. Install the HTTPS Adapter as a service and start the service manually, as described next for UNIX and Windows.

Once started, the HTTPS Adapter registers with the Broker. The *EMC Smarts System Administration Guide* provides more information about starting services.

UNIX:

To install the HTTPS Adapter as a service on UNIX, issue the following command:

```
# sm_service install --force --unmanaged --startmode=manual \
'--name=<service_name>' \
'--description=<Smarts description>' \
'BASEDIR/smarts/bin/sm_adapter_java'
'--name=<HTTPS_Adapter_Name>' \
'--output=<HTTPS_Adapter_Name>.log' \
'-J' \
'nas_probe.jar'
```

Where:

<*service_name*> is the name registered to the service daemon. You may choose any name you wish for this name; for example, **ic-remote-nas**. When you issue the ***sm_service show*** command, this name appears.

<*Smarts description*> is the description of the service. You may create any description you wish; for example, **Smarts remote NAS adapter**.

<*HTTPS_Adapter_Name*> is the name of the HTTPS Adapter, as registered with the Broker; for example, the default name is `remote-nas`.

You can also specify the Broker and Port, if the IP Availability Manager with NAS Extension is registered with a Broker and Port other than the default, **localhost:426**. To do this, add the following arguments to the end of the command:

```
--broker=<IP Address or Hostname>:<Port Number>
```

where <*IP Address or Hostname*> identifies the host on which the Broker is running, and <*Port Number*> identifies which port is used by the Broker. Please note that a colon separates the hostname from the port.

To start the service, type the following command:

```
# BASEDIR/smarts/bin/sm_service start <service_name>
```

To stop the service, issue the following command:

```
# BASEDIR/smarts/bin/sm_service stop <service_name>
```

Windows:

To install the HTTPS Adapter as a service on Windows, type the following command on one line:

```
▼ sm_service install --force --name=<service_name>
   --description=<Smarts description>
   --startmode=manual BASEDIR\smarts\bin\sm_adapter_java.exe
   "--name=<HTTPS_Adapter_Name>"
   "--output=<HTTPS_Adapter_Name>.log" "--jar=nas_probe.jar" ▲
```

Where:

<*service_name*> is the name registered to the service registry; this name must be unique to the registry. You may choose any name you wish for this name so long as the name has no white spaces. The following is an example, **ic-remote-nas**. When you issue the `sm_service show` command, this name appears.

<*Smarts description*> is the description of the service. You may create any description you wish but it is easier to find the service if all EMC Smarts services are grouped together. An example service description is **Smarts remote NAS adapter**. Service names display alphabetically in the Name column of the Services window located at Control Panel/Administrative Tools, so the example description will follow Smarts Performance Manager and precede Smarts Service Assurance Manager.

<*HTTPS_Adapter_Name*> is the name of the HTTPS Adapter, as registered with the Broker; for example, the default name is `remote-nas`.

You can also specify the Broker and Port, if the IP Availability Manager with NAS Extension is registered with a Broker and Port other than the default, **`localhost:426`**. To do this, add the following arguments to the end of the command:

```
--broker=<IP Address or Hostname>:<Port Number>
```

Where *<IP Address or Hostname>* identifies the host on which the Broker is running, and *<Port Number>* identifies which port is used by the Broker. Please note that a colon separates the hostname from the port.

To start the service, go to the Services window and select the service name, or issue the following command at a command prompt:

```
# BASEDIR\smarts\bin\sm_service start <service_name>
```

To stop the service, go to the Services window and select the service name, or issue the following command:

```
# BASEDIR\smarts\bin\sm_service stop <service_name>
```

Running HTTPs adapter in FIPS mode

The NAS subsystem was changed to provide FIPS 140 support. Hence you need to download additional JAR (Java Archive) files, else errors are seen in the NAS log when you run NAS discovery.

Example

```
NAS Log Error Snippet:

MAIN_MSG-*-STDFD_OUT-stdout: javax.net.ssl.SSLException:
   java.security.InvalidKeyException: Illegal key size

[June 17, 2011 6:37:49 PM GMT+05:30 +227ms] t@1084229984 platform
MAIN_MSG-*-STDFD_OUT-stdout:
   at com.rsa.sslj.x.aJ.b(Unknown Source)
   at com.rsa.sslj.x.aJ.a(Unknown Source)
   at com.rsa.sslj.x.aJ.b(Unknown Source)
   at com.rsa.sslj.x.aU.d(Unknown Source)
   at com.rsa.sslj.x.aU.a(Unknown Source)
   at com.rsa.sslj.x.aU.h(Unknown Source)
   at com.rsa.sslj.x.cI.startHandshake(Unknown Source)
   at
   com.smarts.nas_probe.ControlStationInterface.getSSLSocket(ControlSt
   ationInterface.java:314)
   at
   com.smarts.nas_probe.ControlStationInterface.post(ControlStationInt
   erface.java:75)
   at
   com.smarts.nas_probe.ControlStationInterface.getReply(ControlStatio
   nInterface.java:58)
   at com.smarts.nas_probe.XMP.NasXML(XMP.java:25)
Caused by: com.rsa.sslj.x.ax: java.security.InvalidKeyException:
   Illegal key size
   at com.rsa.sslj.x.aJ.b(Unknown Source)
   at com.rsa.sslj.x.cR.k(Unknown Source)
   at com.rsa.sslj.x.t.f(Unknown Source)
   at com.rsa.sslj.x.t$a.run(Unknown Source)
   at com.rsa.sslj.x.aJ$a$a.run(Unknown Source)
   at java.security.AccessController.doPrivileged(Native Method)
   at com.rsa.sslj.x.aJ$a.run(Unknown Source)
   ... 7 more

[June 17, 2011 6:37:49 PM GMT+05:30 +229ms] t@1084229984 platform
```

```
MAIN_MSG-*-STDFD_OUT-stdout: e
Caused by: java.security.InvalidKeyException: Illegal key size
   at javax.crypto.Cipher.a(DashoA13*..)
   at javax.crypto.Cipher.init(DashoA13*..)
   at javax.crypto.Cipher.init(DashoA13*..)
   at com.rsa.sslj.x.Y.<init>(Unknown Source)
   ......
```

With BSAFE SSL-J, some of the FIPS 140 cryptographic algorithms require Unlimited Strength Jurisdiction Policy Files.

Unlimited Strength Jurisdiction Policy JAR Files for NAS discovery

Download and install the Unlimited Strength Jurisdiction Policy Files to run the NAS adapter in FIPS mode using the following steps:

1. Download the Java Cryptography Extension (JCE) Unlimited Strength Jurisdiction Policy Files 8 from the Oracle website.
2. Extract the local_policy.jar and US_export_policy.jar files from the downloaded zip file.
3. Go to the smarts/jre/lib/security directory and then back up the existing policy files in this path.
4. Overwrite the local_policy.jar and US_export_policy.jar files to the smarts/jre/lib/security directory.

NOTICE

If you want to switch back from FIPS mode to non-FIPS mode, reset SM_FIPS140 to FALSE. You do not need to remove the Unlimited Strength Jurisdiction Policy Files.

CHAPTER 4
Performing an Upgrade

This chapter describes how to install an in-place upgrade installation for the EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, and EMC Smarts VoIP Availability Manager. Upgrade topics include:

- Upgrade installation overview 46
- Upgrade installation prerequisites 49
- Upgrade the product 49
- Add additional features to an upgrade installation 53
- Upgrading 9.4.2 products in FIPS mode 54
- Next steps 54

Upgrade installation overview

This chapter describes how to perform an upgrade installation for the IP Manager, Service Assurance Manager, MPLS Manager, Server Manager, Network Protocol Manager, and VoIP Availability Manager. An upgrade installation applies a new version of software to an existing version in the same directory on the same host. An “upgrade installation” is also known as an “in-place upgrade.” During an upgrade installation, new product services are not available to install, unless you select additional products during the upgrade procedure.

You can upgrade the versions of software listed in the *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* to Version 9.4.2 using the in-place upgrade instructions provided in this chapter.

The upgrade installation flow is shown in Figure 3 on page 47.

The order in which you upgrade products depends on whether the EMC M&R UI is included in your deployment. When deciding which Global Manager or underlying Domain Manager to upgrade first, perform the upgrade in the following order:

1. Start with the top-most SAM server.
   - If EMC M&R is included, this is the Presentation SAM server.
   - If EMC M&R is not included, this is the top-most SAM server and related Service Assurance products and consoles in your deployment, either a SAM server or the top SAM server in a hierarchical SAM deployment.
2. If EMC M&R is included, update EMC M&R platform (core) components and the SolutionPack for EMC Smarts.

   Ensure that communication exists between the Presentation SAM server and the SolutionPack for EMC Smarts.

   For information, consult the *Service Assurance Suite Installation and Configuration Guide for EMC M&R*, the *SolutionPack for EMC Smarts Summary Sheet* article, and the *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article.
3. An Aggregation SAM server if it is a hierarchical SAM deployment.
4. IP Manager.
5. Any order: Server Manager, MPLS Manager, Network Protocol Manager, and VoIP Availability Manager.

NOTICE

Presentation SAM server is the server that is configured in the SolutionPack for EMC Smarts for use with the EMC M&R UI. This does not mean that a hierarchical SAM is required.



Figure 3 Upgrade installation flowchart

Installer tasks

During an upgrade installation, the installation program performs the following tasks:

1. Detects and stops all services, scheduled jobs, and processes that use programs or libraries that are running from the existing installation. It also stops the service daemon, sm_serviced, if it is running.

   NOTICE

   Be aware that in some cases, on Windows, services cannot be stopped by the installation program because multiple threads are locking the services. In those cases, use the Windows Control Panel to stop the services manually.

   NOTICE

   If the broker is running on the host with a IP Manager, then it will have to be stopped during an upgrade. The broker has to be stopped to prevent the impact on all the other applications running on the system.

2. Creates a backup copy of your customizations in the ‹BASEDIR›/smarts/.migrate.bkp.‹version› directory.
3. Removes the patch, if any, from the existing installation.
4. Installs the software.
5. Prompts you to merge your customizations files in the BASEDIR›/smarts/.migrate.bkp.‹version› directory to the BASEDIR/smarts/local directory.

Installer-called utilities

The installation program invokes the sm_migrate utility to backup the existing user-customized files and base files. It also presents the sm_migrate command to be run after the 9.4.2 installation to complete a three-way merge of the following sets of files:

- Existing user-customized files in the ‹BASEDIR›/smarts/.migrate.bkp.‹version› directory.
- Existing base files in the ‹BASEDIR›/smarts/.migrate.bkp.‹version› directory.
- 9.4.2 base files in the BASEDIR/smarts directory

The sm_migrate utility invokes another utility, the sm_merge utility, for each of the files that requires a three-way merge. Chapter 6, “Migration Utilities,” explains how the sm_migrate and sm_merge utilities work.

Upgrade installation prerequisites

Fulfill the following prerequisites before starting the upgrade installation:

- Ensure that you have superuser (User ID 0) or administrative privileges on the target host. The installation program will halt if you do not have the appropriate privileges.
- Ensure that the required operating system patches have been installed. Clicking **More Information** during the installation process will launch the System Information window and the Pass/Fail status of the operating system patches. The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides information on operating system patches.
- Remove all the unused files in the /local directory. The unused files will also include RPS files and custom files created by you. The upgrade process uses the sm_migrate utility that creates a backup of all the files in the local directory and copies them back to local directory after the upgrade. RPS and custom files can be large, and may slow down the process.
- Disk space requirement—During an upgrade installation, the installer creates a backup of files in actions, conf, model, repos, rules, script directories. Ensure that you have disk space of twice the size of these directories available on the system. After the upgrade and verifying the installation, you can archive or remove the backup directories. This requirement is in addition to the minimum disc requirement outlined for each product in the *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*.

Upgrade the product

You upgrade each product in one of three ways: Wizard mode, CLI mode, or Unattended mode.

Perform the following tasks:

1. Review the important release issues found in your product-specific release notes.
2. On the host where the target existing installation resides, log in as superuser (User ID 0) or administrator.
3. Mount the CD/DVD-ROM. Appendix C, “Procedures for CD/DVD-ROMs,” provides more information.
4. Choose Wizard mode, CLI mode (UNIX only), or Unattended mode. The **setup** commands for invoking Wizard mode, CLI mode, and Unattended mode are listed in Table 5 on page 24, Table 6 on page 28, and Table 8 on page 31.
   - In Wizard mode or CLI mode, make the following additional selections:
     - In the **Upgrade or Install** screen, select **Upgrade existing suite** and click **Next** or enter [**1**].
     - In the **Target Installation Selection** screen (in which an existing product is selected unless the product was previously installed to more than one directory, in which case you will see multiple choices), select a target installation directory and click **Next** or enter [**1**].

- In the **Choose Products** screen, all of the existing products are selected to be upgraded. You can select additional products to add to the installation.

  For Service Assurance Manager only, add **EMC Data Access API (EDAA)** if the Service Assurance Manager in this upgrade is going to be configured in the SolutionPack for EMC Smarts and will be used as the Presentation SAM server for the EMC M&R UI.

- Specify any additional local directories created using SM_SITEMOD. Click **Next** or enter [**1**].

- In Unattended mode, specify the following additional options in the response file (‹product›-response.txt). All previously installed products must have their product options set to “true” in the response file.

  - Uncomment the **-W INSTALL_TYPE.INSTALL_CHOICE=UPGRADE** option.
  - Uncomment the **-W SITEMOD_BEAN.SITEMODS_VAR** option, and provide one or more directory locations to perform an upgrade. You can provide the name of the directories, or the directory name with absolute path.

    For example, on Linux:

    -W SITEMOD_BEAN.SITEMODS_VAR=local-1:/opt/InCharge/SAM/smarts/Local-2:local-3

    on Windows:

    -W SITEMOD_BEAN.SITEMODS_VAR=C:\InCharge\smarts\SAM\local3;C:\InCharge\SAM\smarts\local2

    NOTICE

    For specifying directory separators, use : on Linux and ; on Windows.

  - Uncomment the **-W MERGE_OPTION_UPGRADE.MERGE_CHOICE=MERGE** option to perform the merge.
  - Uncomment the **-W MERGE_OPTION_UPGRADE.MERGE_CHOICE=NOMERGE** option to not perform the merge.
  - Uncomment the **-P ‹*product*›.installLocation** option and set its property value to the installation directory of the target installation. The installation directory must end with **/‹*product*›**.
  - Ensure the property value is set to “true” for each product that is already installed plus any other product that you would like to add to the installation.

5. The installation program displays the **Directories created using SM_SITEMOD** screen which allows you to back up local directories that were created with SM_SITEMOD. If you used SM_SITEMOD to create local directories, enter a list of local directories. Click **Next** or enter [**1**].

   The installation program then runs the sm_migrate utility to create a backup file of the user-customized files and base files in the existing installation. The backup file, named .migrate.bkp.‹version›, is saved to the BASEDIR/smarts directory.

NOTICE

On a Windows-based host, extracting the sm_migrate utility and performing a migration takes a considerable amount of time. Be patient. Do not stop the migration process.

6. The installation program removes the patch, if any, from the existing installation and installs the 9.4.2 software.

7. After the installation, the installation program shows the **Restore User Configurations Instructions** screen, which presents the sm_migrate command for restoring the old user-customizations in the .migrate.bkp.‹version› backup file to the BASEDIR/smarts/local directory. The screen provides two options:

   a. **Yes, merge the files** - Select this option if you want the utility to automatically merge the files modified by you.

   b. **No, I will merge them later** - Select this option if you want to manually merge the files modified by you.

   Click **Next** or enter [**1**] to view the **Installation Summary**.

   NOTICE

   For Service Assurance Manager, the upgrade process inserts the _edaa user entry into the security configuration file serverConnect.conf and the runcmd_env.sh file. The upgrade process does not modify the clientConnect.conf, brokerConnect.conf, and imk.dat files. The upgrade process does not insert the _edaa user entry into the files of Domain Managers.

   NOTICE

   For Domain Managers, copying the security configuration files clientConnect.conf, serverConnect.conf, brokerConnect.conf, runcmd_env.sh, and imk.dat is not supported in an upgrade installation. You can manually copy the security configuration files using sm_migrate utility as described in "Restoring customizations after an upgrade installation" on page 81.

8. The **Installation Summary** shows informational messages such as successful confirmations, error messages, and warnings. Investigate any errors or warnings.

   If **Next** appears, your system needs to be rebooted because one or both of the following tasks are pending on the system:

   - A system-protected file was replaced during the installation and requires a restart.
   - A pending restart was triggered by another application or by an operating system patch installation.

   Click **Next** or enter [**1**] and then reboot your system. Otherwise, click **Finish** or enter [**1**] to exit the installation.

   The installation program writes an install log file to the BASEDIR/smarts/setup/logs directory, unless the installation fails at the very start, in which case the installation program writes the log file to the /tmp directory. The log file is a text file with the naming convention Install.‹product›.‹productversionNumber›.log.

9. Evaluate your custom code. Review the "Custom file migration use cases" on page 83. The sm_migrate utility migrated all user-customized files from the existing installation to the BASEDIR/smarts/local directory in the 9.4.2 installation. Review the output of the sm_migrate utility and evaluate if you would like to keep the user-customized files in the new installation.

   "Configuration migration process logs" on page 87 provides more information on the log files that are created after the migration of user-customized files.

10. Depending on your deployment, ensure that the *BASEDIR/smarts/local/conf/runcmd_env.sh* file includes the environment variables, SM_TLS_PROTOCOLS and SM_ALLOW_LEGACY_CRYPTO.

    Use SM_TLS_PROTOCOLS set to the +TLSv1.1 value only if you need to interoperate with EMC Smarts products based on Foundation 9.0.0.0 Build 1345 through 9.2.x.

    Use SM_ALLOW_LEGACY_CRYPTO set to TRUE only if you need to interoperate with EMC Smarts products based on Foundation versions prior to 9.0.0.0 Build 1345.

    "Check the version number" on page 94 provides the sm_server --version command to determine the Foundation (DMT) version.

    To ensure that the runcmd_env.sh file includes the environment variables:

    a. Go to the *BASEDIR/smarts/bin* directory and enter this command to open the runcmd_env.sh file:

       ```
       sm_edit conf/runcmd_env.sh
       ```

    b. Search for the environment variables. If they do not exist, add one or both depending on your deployment:

       ```
       SM_TLS_PROTOCOLS=+TLSv1.1
       SM_ALLOW_LEGACY_CRYPTO=TRUE
       ```

    c. Save and close the file.

11. If you plan to use the EMC M&R UI and the Service Assurance Manager in this upgrade is the Presentation SAM server for the EMC M&R UI, you need to use the sm_service command to install the ic-sam-server-pres service, and then remove the existing ic-sam-server service.

    NOTICE

    Presentation SAM server is the server that is configured in the SolutionPack for EMC Smarts for use with the EMC M&R UI. This does not mean that a hierarchical SAM is required.

    In addition to the ic-sam-server-pres service, ensure that you have installed the smarts-elasticsearch service, the smarts-rabbitmq service, and the smarts-tomcat service if you did not select them during the upgrade installation.

    Appendix B, "Manually Installing Services," provides the sm_service syntax for the Presentation SAM server, Tomcat, Rabbit MQ, and ElasticSearch.

    To remove the ic_sam_service service, type this command from the ‹BASEDIR›/smarts/bin directory:

    ```
    sm_service remove --name=ic-sam-server
    ```

The *EMC Smarts System Administration Guide* provides more information about how to use the sm_service command.

12. In this upgrade, if you plan use the EMC M&R UI and the Configuration Manager to configure IP Manager settings, you need to register the Configuration Manager and the IP Managers with the service command that includes the EMC Data Access API service option (--edaa). The *Service Assurance Suite How to Maintain IP Manager Settings* article explains how to use the Configuration Manager to configure IP Manager settings.
13. Optional for IP Manager, run the repository file migration utility (sm_migraterps) to make the repository file compatible with the newer 9.4.2 version of the software as described in "Automatically migrate topology for IP Manager using RPS utility" on page 88.
14. If you installed additional products and they are not licensed features, obtain and save a new license file as outlined in "Obtain and install a temporary license file" on page 95.

    Otherwise, existing permanent licenses are supported for 9.4.2 products. No user action is required.
15. If your product is part of a deployment that requires the Federal Information Processing Standard (FIPS) Publication 140-2, a U.S. government computer security standard governing cryptographic modules, follow the instructions in "Upgrading 9.4.2 products in FIPS mode" on page 54.
16. If you installed the products as services, start the services. "Starting services on UNIX" on page 97 or "Starting services on Windows" on page 97 provides more information.
17. Verify the current state of the products and Broker. "Verify the product status" on page 102 provides more information.
18. Initiate a discovery. Consult the discovery guide or user guide for your product for more information on this procedure.
19. For Server Manager,

    a. In the Domain Manager Administration Console, right-click on the ESM server (INCHARGE-ESM, by default) in the left pane and select the **Load All ESM Host monitoring data from Backup** option.

    b. Perform a discovery (**Topology › Discover All**) from the ESM server.

       All of the applications that were configured prior to the upgrade are restored and Server Manager starts to monitor those applications.

Add additional features to an upgrade installation

If after installing an upgrade installation you want to add products to the upgrade installation, run the installation again, select the **Add additional features** option in the **Upgrade or install** screen, and select all products that are already installed plus any other products that you would like to install in the upgraded installation.

Upgrading 9.4.2 products in FIPS mode

NOTICE

Upgrading in FIPS mode is not available for Server Manager.

9.4.2 products do not use a Federal Information Processing Standard (FIPS 140-2) approved encryption algorithm to protect the imk.dat file. By default, the 9.4.2 imk.dat file uses MD5, which is not a FIPS-approved algorithm. Hence, while upgrading from previous versions of products to Version 9.4.2, the imk.dat file needs to be regenerated in order to run in the FIPS mode.

In order to convert an existing installation to FIPS, use the sm_rebond (in non-FIPS mode) first to get everything re-encoded in a FIPS compatible way. The steps are as follows:

1. Run the following command at the command line prompt:

   ```
   sm_rebond --upgrade --basedir=<BASEDIR>/smarts
   ```

   The path must be set to the default install path. Regardless of the FIPS 140 state, you must run the sm_rebond command from the BASEDIR where the software is installed, not from any other product installation area which also has the sm_rebond utility.

   For example for Service Assurance Manager, run the command:

   Linux

   ```
   sm_rebond --upgrade --basedir=/opt/InCharge/SAM/smarts
   ```

   Windows

   ```
   sm_rebond --upgrade --basedir=C:\InCharge\SAM\smarts
   ```

2. When prompted, type a password to regenerate the imk.dat file. The default password is *Not a secret*.
3. Set the value for the parameter **SM_FIPS140** to **TRUE** in the *runcmd_env.sh* file. The file is located under the *BASEDIR/smarts/local/conf* directory.

Next steps

Chapter 7, "Verifying the Installation," describes tasks for verifying the proper installation of the software and starting services.

CHAPTER 5
Performing a Migration

This chapter provides instructions for migrating previous versions of the EMC Smarts Service Assurance Manager, EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, EMC Smarts Optical Transport Manager, and EMC Smarts VoIP Availability Manager to a new version. It consists of the following topics:

- Migration overview 56
- Install and migrate on the same host 57
- Install and migrate on a different host 60
- Review license file migration 64
- Post-migration tasks 68

Migration overview

Consult the *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* for software versions that require a manual migration to Version 9.4.2.

Two methods are available:

- Install and migrate on the same host
- Install and migrate on a different host

After the installation, run the sm_migrate utility to backup the user-customized files in the previous version and migrate the files to the new version. Chapter 6, "Migration Utilities," explains how the sm_migrate utility works.

Disk space requirement—During a migration, the sm_migrate creates a backup of files in actions, conf, model, repos, rules, script directories. Ensure that you have disk space of four times the size of these directories available on the system. After the migration and verifying the installation, you can archive or remove the backup directories. This requirement is in addition to the minimum disk requirement outlined for each product in the *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix*.

Server name requirement for migration—To preserve notification history and the original Source attributes of notifications in the Service Assurance Manager, the server names of underlying Domain Managers should remain the same. This way at the end of the migration of all EMC Smarts Domain Managers, the SAM server can correctly associate the pre-existing topology and notifications with the topology and events coming from migrated Domain Managers. For example, if the 9.4 Server Manager has a server name INCHARGE-ESM, do not change it to a different name for the 9.4.2 release.

Make sure that you read "Install and migrate on the same host" on page 57 and "Install and migrate on a different host" on page 60 in their *entirety before proceeding*.

NOTICE

Remove all the unused files in the /local directory. The unused files will also include RPS files and custom files created by you. The sm_migrate utility creates a backup of all the files in the local directory and copies them back to local directory. RPS and custom files can be large, and may slow down the process.

Install and migrate on the same host

To migrate from a previous version of a product to the new, current 9.4.2 version on the same host, you must:

1. Install the 9.4.2 product and specify an installation directory that is different from the one that is used for the previous installation.
2. Stop the old services for the previous version, if necessary.

   For UNIX, keep the service daemon (the sm_serviced component) running. If sm_serviced is stopped, all EMC Smarts products will stop and will need to be restarted.

   In some cases, on Windows, the installation program cannot stop the services, because multiple threads are locking the services. In those cases, use the Windows Control Panel to stop the services manually.

   For most cases, the installation program detects and stops all services, scheduled jobs, and processes that use programs or libraries that are running from the existing installation.

   It also stops the service daemon, sm_serviced, if it is running.
3. Migrate user-customized files from the previous installation to the new installation.
4. Reuse the customized Polling and Thresholds settings from the old repository.

Detailed instructions are described in "Migration procedure for the same host" on page 58.

For a test lab environment, since the two installations are on the same host, you can run both installations in parallel. For parallel installations, both installations connect to the same Broker and Global Manager, as long as the old and new product service and sm_server names are unique. In this case, you will need to rename the service and sm_server for the previous product version. Managers registered with the same Broker must have unique names.

For a production environment, EMC Corporation recommends that you decommission the previous version of product.

The order in which you upgrade products depends on whether the EMC M&R UI is included in your deployment. When deciding which Global Manager or underlying Domain Manager to migrate first, perform the migration in the following order:

1. Start with the top-most SAM server.
   - If EMC M&R is included, this is the Presentation SAM server.
   - If EMC M&R is not included, this is the top-most SAM server and related Service Assurance products and consoles in your deployment, either a SAM server or the top SAM server in a hierarchical SAM deployment.
2. If EMC M&R is included, migrate or update EMC M&R platform (core) components and the SolutionPack for EMC Smarts.

   Ensure that communication exists between the Presentation SAM server and the SolutionPack for EMC Smarts.

For information, consult the *Service Assurance Suite Installation and Configuration Guide for EMC M&R*, the *SolutionPack for EMC Smarts Summary Sheet* article, and the *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article.

3. An Aggregation SAM server if it is a hierarchical SAM deployment.
4. IP Manager.
5. Any order: Server Manager, MPLS Manager, Network Protocol Manager, and VoIP Availability Manager.

NOTICE

Presentation SAM server is the server that is configured in the SolutionPack for EMC Smarts for use with the EMC M&R UI. This does not mean that a hierarchical SAM is required.

Migration procedure for the same host

To migrate the previous version of the product to the new version on the same host, perform the following tasks:

1. Review the important release issues for the 9.4.2 product, as described in the *EMC Smarts Release Notes for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*.
2. Determine that the products that you are installing are supported for your platform. The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides more information.
3. Determine if the host has enough disk space and memory to accommodate so both versions of the product can co-exist. The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides more information.
4. Mount the CD/DVD-ROM on the host as described in Appendix C, "Procedures for CD/DVD-ROMs."
5. Uninstall any temporary test patches (TTPs), if they exist, in your old installation.

   If a TTP has been installed on a Service Pack, you must first uninstall the TTP. Otherwise, the TTP files will be treated as files modified by you and copied to the local directory in the new installation area.
6. Install the new version of the product on the same host as described in Chapter 2, "Performing an Installation."
   - Specify an installation directory that is different from the old installation directory so both versions of the product can co-exist.
   - Install products as services. These services overwrite the old stopped services.

   NOTICE

   If you need to continue to run the previous versions of the products, manually install services for them with unique names and start them.

   The installation program installs the 9.4.2 software.

7. Run the sm_migrate utility to copy user-customized files from the previous installation to the new 9.4.2 installation. "Migrating customizations on the same host" on page 76 provides instructions.

   NOTICE

   Run the sm_migrate utility immediately after the installation and before you start any services or modify any files in the new installation. The sm_migrate utility will not merge any files from the previous installation local directory, if the same files are present in the new installation BASEDIR/smarts/local directory.

8. Evaluate your security settings. "Migration of security configuration files" on page 85 provides more information.

9. Evaluate the environment variables in the old runcmd_env.sh file. "Migration of security configuration files" on page 85 provides more information.

10. Evaluate your custom code. Review the "Custom file migration use cases" on page 83 to plan your post-migration steps. The sm_migrate utility migrated all user-customized files from the previous installation to the BASEDIR/smarts/local directory in the new installation. It also made a backup copy of the files under the BASEDIR/smarts/.migrate.bkp.x.x directory (for example, .migrate.bkp.2.0.0.0). Review the output of the sm_migrate utility and evaluate if you would like to keep the user-customized files in the new installation.

11. Save your license in the proper location or (optional) update your license:

    - Temporary license—copy the license file, smarts.lic, to the *BASEDIR/smarts/local/conf* directory on the system where the EMC Smarts software is installed. If you installed multiple EMC Smarts products on the same system, each product requires a separate copy of smarts.lic.
    - Permanent license—use the procedures described in the *EMC Smarts System Administration Guide*.

    If you installed additional products and they are not licensed features, obtain and save a new license file as outlined in "Obtain and install a temporary license file" on page 95.

    Otherwise, existing licenses are supported for 9.4.2 products. No user action is required.

12. Depending on your deployment, ensure that the *BASEDIR/smarts/local/conf/runcmd_env.sh* file includes the environment variables, SM_TLS_PROTOCOLS and SM_ALLOW_LEGACY_CRYPTO.

    Use SM_TLS_PROTOCOLS set to the +TLSv1.1 value only if you need to interoperate with EMC Smarts products based on Foundation 9.0.0.0 Build 1345 through 9.2.x.

    Use SM_ALLOW_LEGACY_CRYPTO set to TRUE only if you need to interoperate with EMC Smarts products based on Foundation versions prior to 9.0.0.0 Build 1345.

    "Check the version number" on page 94 provides the sm_server --version command to determine the Foundation (DMT) version.

    a. Go to the *BASEDIR/smarts/bin* directory and enter this command to open the runcmd_env.sh file:

```
sm_edit conf/runcmd_env.sh
```

b. Search for the environment variables. If they do not exist, add one or both depending on your deployment:

```
SM_TLS_PROTOCOLS=+TLSv1.1
SM_ALLOW_LEGACY_CRYPTO=TRUE
```

c. Save and close the file.

13. Rename the repository file before reusing it.

    a. Locate the existing repository file that was copied to the BASEDIR/smarts/local/repos/icf directory in the new 9.4.2 installation.

    b. Rename the repository file by removing the version number extension. For example, the repository file INCHARGE-MPLS-ANALYSIS.rps.3.1.0.2 should be renamed to INCHARGE-MPLS-ANALYSIS.rps without the version number extension.

14. Optional for IP Manager, run the repository file migration utility (sm_migraterps) to make the repository file compatible with the newer 9.4.2 version of the software as described in "Automatically migrate topology for IP Manager using RPS utility" on page 88.

15. If you installed the products as services, start them for the first time. "Starting services on UNIX" on page 97 or "Starting services on Windows" on page 97 provide more information.

16. Verify the current state of the products and Broker. "Verify the product status" on page 102 provides more information.

17. For Server Manager,

    a. In the Domain Manager Administration Console, right-click on the ESM server (INCHARGE-ESM, by default) in the left pane and select the **Load All ESM Host monitoring data from Backup** option.

    b. Perform a discovery (**Topology › Discover All**) from the ESM server.

    All of the applications that were configured prior to the migration are restored and Server Manager starts to monitor those applications.

18. Decommission the previous version of the products. For instructions, refer to the uninstallation chapter in the installation guide for the previous software version.

Install and migrate on a different host

If you want to run the new version of the 9.4.2 product before decommissioning the previous version, you must:

1. Install the new version of the 9.4.2 product on a different host.
2. Migrate any customized configuration file changes to the new installation.

Detailed instructions are described in "Migration procedure for a different host" on page 61.

Since the two installations are on different hosts, you can run both installations in parallel. You have the option of:

- Having both installations connect to the same Global Manager and Broker.

  Managers registered with the same Broker must have unique names. In this scenario, stop and rename the services for the previous version and, when you install the 9.4.2 product, the installation program will use the default server names.

- Having multiple instances of the Global Manager and Broker with each instance assigned to a different version of the product.

For a production environment, EMC Corporation recommends that you decommission the previous version of product.

The order in which you upgrade products depends on whether the EMC M&R UI is included in your deployment. When deciding which Global Manager or underlying Domain Manager to migrate first, perform the migration in the following order:

1. Start with the top-most SAM server.
   - If EMC M&R is included, this is the Presentation SAM server.
   - If EMC M&R is not included, this is the top-most SAM server and related Service Assurance products and consoles in your deployment, either a SAM server or the top SAM server in a hierarchical SAM deployment.
2. If EMC M&R is included, migrate or update EMC M&R platform (core) components and the SolutionPack for EMC Smarts.

   Ensure that communication exists between the Presentation SAM server and the SolutionPack for EMC Smarts.

   For information, consult the *Service Assurance Suite Installation and Configuration Guide for EMC M&R*, the *SolutionPack for EMC Smarts Summary Sheet* article, and the *How to Set Up SAM, EMC M&R, and the SolutionPack for EMC Smarts* article.
3. An Aggregation SAM server if it is a hierarchical SAM deployment.
4. IP Manager.
5. Any order: Server Manager, MPLS Manager, Network Protocol Manager, and VoIP Availability Manager.

NOTICE

Presentation SAM server is the server that is configured in the SolutionPack for EMC Smarts for use with the EMC M&R UI. This does not mean that a hierarchical SAM is required.

Migration procedure for a different host

To migrate the previous version of the product to the new version on a different host, satisfy or perform the following tasks:

1. Review the important release issues for the 9.4.2 product, as described in the *EMC Smarts Release Notes for SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers*.

2. Determine that the products that you are installing are supported for your platform. The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides more information.
3. Determine if the host has enough disk space and memory to accommodate so both versions of the product can co-exist. The *EMC Smarts SAM, IP, ESM, MPLS, NPM, OTM, and VoIP Managers Support Matrix* provides more information.
4. Mount the CD/DVD-ROM on the host as described in Appendix C, "Procedures for CD/DVD-ROMs."
5. Uninstall any temporary test patches (TTPs), if they exist, in your old installation.

   If a TTP has been installed on a Service Pack, you must first uninstall the TTP. Otherwise, the TTP files will be treated as files modified by you and copied to the local directory in the new installation area.
6. Install the new version of the product on the different host as described in Chapter 2, "Performing an Installation."

   The installation program installs the 9.4.2 software.
7. Run the sm_migrate utility to copy user-customized files from the previous installation to the new 9.4.2 installation. "Migrating customizations to a different host" on page 78 provides instructions.

   NOTICE

   Run the sm_migrate utility immediately after the installation and before you start any services or modify any files in the new installation. The sm_migrate utility will not merge any files from the previous installation local directory, if the same files are present in the new installation BASEDIR/smarts/local directory.
8. Evaluate your security settings. "Migration of security configuration files" on page 85 provides more information.
9. Evaluate the environment variables in the old runcmd_env.sh file. "Migration of security configuration files" on page 85 provides more information.
10. Evaluate your custom code. Review the "Custom file migration use cases" on page 83 to plan your post-migration steps. The sm_migrate utility migrated all user-customized files from the previous installation to the BASEDIR/smarts/local directory in the new installation. It also made a backup copy of the files under the BASEDIR/smarts/.migrate.bkp.x.x directory (for example, .migrate.bkp.2.0.0.0). Review the output of the sm_migrate utility and evaluate if you would like to keep the user-customized files in the new installation.
11. Save your license in the proper location or (optional) update your license:
    - Temporary license—copy the license file, smarts.lic, to the *BASEDIR/smarts/local/conf* directory on the system where the EMC Smarts software is installed. If you installed multiple EMC Smarts products on the same system, each product requires a separate copy of smarts.lic.
    - Permanent license—use the procedures described in the *EMC Smarts System Administration Guide*.

If you installed additional products and they are not licensed features, obtain and save a new license file as outlined in "Obtain and install a temporary license file" on page 95.

Otherwise, existing licenses are supported for 9.4.2 products. No user action is required.

12. Depending on your deployment, ensure that the *BASEDIR/smarts/local/conf/runcmd_env.sh* file includes the environment variables, SM_TLS_PROTOCOLS and SM_ALLOW_LEGACY_CRYPTO.

    Use SM_TLS_PROTOCOLS set to the +TLSv1.1 value only if you need to interoperate with EMC Smarts products based on Foundation 9.0.0.0 Build 1345 through 9.2.x.

    Use SM_ALLOW_LEGACY_CRYPTO set to TRUE only if you need to interoperate with EMC Smarts products based on Foundation versions prior to 9.0.0.0 Build 1345.

    "Check the version number" on page 94 provides the sm_server --version command to determine the Foundation (DMT) version.

    a. Go to the *BASEDIR/smarts/bin* directory and enter this command to open the runcmd_env.sh file:

       ```
       sm_edit conf/runcmd_env.sh
       ```

    b. Search for the environment variables. If they do not exist, add one or both depending on your deployment:

       ```
       SM_TLS_PROTOCOLS=+TLSv1.1
       SM_ALLOW_LEGACY_CRYPTO=TRUE
       ```

    c. Save and close the file.

13. Rename the repository file before reusing it.

    a. Locate the existing repository file that was copied to the BASEDIR/smarts/local/repos/icf directory in the new 9.4.2 installation.

    b. Rename the repository file by removing the version number extension. For example, the repository file INCHARGE-MPLS-ANALYSIS.rps.3.1.0.2 should be renamed to INCHARGE-MPLS-ANALYSIS.rps without the version number extension.

14. Optional for IP Manager, run the repository file migration utility (sm_migraterps) to make the repository file compatible with the newer 9.4.2 version of the software as described in "Automatically migrate topology for IP Manager using RPS utility" on page 88.

15. If you installed the products as services, start them for the first time. "Starting services on UNIX" on page 97 or "Starting services on Windows" on page 97 provide more information.

16. Verify the current state of the products and Broker. "Verify the product status" on page 102 provides more information.

17. For Server Manager,

    a. In the Domain Manager Administration Console, right-click on the ESM server (INCHARGE-ESM, by default) in the left pane and select the **Load All ESM Host monitoring data from Backup** option.

    b. Perform a discovery (**Topology › Discover All**) from the ESM server.

All of the applications that were configured prior to the migration are restored and Server Manager starts to monitor those applications.

18. Decommission the previous version of the products. For instructions, refer to the uninstallation chapter in the installation guide for the previous software version.

Review license file migration

This section provides the procedure for migrating the license server. The *EMC Smarts System Administration Guide* provides complete information about EMC Smarts licensing, including deployment considerations and troubleshooting.

Before you begin, you need to be aware of the following considerations:

- You can use your existing license file, provided that you have not: acquired more features, increased the number of licenses, or changed machines (host IDs).

  If you have acquired more features, increased the number of licenses, or changed machines, then you must obtain a new license file. To obtain a permanent license file, complete a Support Request (SR) form, which you can find on the EMC support website http://support.emc.com.

- You will need to use the FlexNet 11.12.1.5 license server provided with EMC Smarts version 9.4.2 software. The setup instructions are described in the following subsection.

  FlexNet software is backward-compatible. For example, a newer license manager daemon (**lmgrd**) will work with older vendor daemons and older FlexNet-licensed products. So a FlexNet 11.12.1.5 license server provided with EMC Smarts version 9.4.2 software will work with FLEXlm license files distributed for EMC Smarts version 9.x software, but not the other way round.

This license migration procedure is similar to the procedure used to set up licensing for a new installation with the following differences:

- You can reuse your existing license file for step 3 .
- You stop the old license server in step 6 and uninstall it in step 8 .
- If you set up the new FlexNet license server on the same system as the old license server, you do not need to modify the SM_LICENSE variable for your other EMC Smarts software installations.

NOTICE

For the following procedure, you need administrative privileges for both the EMC Smarts software and the systems on which the software is running.

NOTICE

In this discussion, a temporary license file is referred to as ‹license_name›.lic and a permanent license file is referred to as *‹host_id›.‹license_name›.lic.* If you install a license server with the **install_license** *s*cript described later, you should be aware that the script changes the permanent license filename from ‹host_id›.‹license_name›.lic to ‹license_name›.lic.

Migrate permanent license and set up FlexNet license server

On the system where the EMC Smarts Broker resides, perform these steps to migrate the permanent license file and set up the new server:

1. If you have not already installed the 9.4.2 software, do so. Install the software on the same system in a different directory than the older software.

   If you installed the software on a different system, open a Support Request (SR) on the EMC support website http://support.emc.com to request a new license.

2. If you previously used a temporary license (copied *‹license_name›.lic* to the *BASEDIR/smarts/local/conf* directory), you need to delete it because it will cause the **install_license** script to fail later in step 5 .

3. Copy your existing permanent license file, *‹host_id›.‹license_name›.lic,* from the old installation directory to the new BASEDIR directory on the system where the license server will run.

   Typically, this location should be the same host and BASEDIR as for the EMC Smarts Broker. By default, BASEDIR is /opt/InCharge/*‹product›* for UNIX and C:\InCharge *‹product›* for Windows.

   If you obtained a new permanent license file, save the attachment to a file named *‹host_id›.‹license_name›.lic* in your BASEDIR directory on the system where the license server will run.

   NOTICE

   Do not save the permanent license file (*‹host_id›.‹license_name›.lic*) to the BASEDIR/smarts/local/conf directory. The install_license script will fail if it finds a permanent license file in this directory. Also, do not save a permanent license file to the BASEDIR/smarts/script or BASEDIR/smarts/conf directory.

   Later, as the result of step 5 , the **install_license** script installs the permanent license file into the BASEDIR/smarts/local/conf directory.

4. If necessary, you may need to change the port for the FlexNet license server (which will be installed in step 5). For example, if the default port, 1744, is used by another process, the FlexNet license server can run on a different port. Do not make any changes to the permanent license file unless you need to change the port.

   Use any text editor to open the *‹host_ID›.‹license_name›.lic* file. The first line of the permanent license file, labelled SERVER, contains the hostname, host ID, and port of the license server, as shown in the following example:

   ```
   SERVER this_host 8323fcbf 1744
   ```

   Change the port number from the default (“1744”) on the SERVER line and save the file.

   The *EMC Smarts System Administration Guide* for instructions contains information on deploying the FlexNet license server on the opposite side of a firewall from your other Smarts software installations.

5. Install the FlexNet license server using the **install_license** script. By default, this file is located in the BASEDIR/smarts/script directory.

   You must run the **install_license** script on the same system where the license server runs. This script requires superuser privileges (user ID 0) for UNIX, and administrator privileges for Windows. You must specify the full path to the permanent license file.

   For example, the command on UNIX systems is:

   ```
   ▼#/opt/InCharge/SAM/smarts/script>install_license.sh install
   <path to license file>/<host_ID>.<license_name>.lic ▲
   ```

   On Windows systems, for example, the command is:

   ```
   ▼  C:\InCharge\SAM\smarts\script>install_license.cmd install
   <path to license file>\<host_ID>.<license_name>.lic ▲
   ```

   NOTICE

   ▼▲ indicates this command should be typed as one line.

   In addition to installing the FlexNet license server, the **install_license** script performs other functions such as configuring the license server to start when the system reboots. The *EMC Smarts System Administration Guide* provides additional information.

6. Stop the old license server. Use the same command in step 7 except substitute stop for start.

7. Start the FlexNet license server. The FlexNet license server runs as a daemon on UNIX and as a service on Windows and automatically starts the vendor daemon for EMC Smarts. Run the command appropriate for your platform.

   Linux:

   ```
   # /etc/init.d/SMARTS-License start
   ```

   Windows:

   To manually start the license server, follow these steps as an administrator:

   1. Select **Start** › **Settings** › **Control Panel** › **Administrative Tools**.
   2. Select **Services**.
   3. Select the **FlexNet License Manager** service.
   4. Right-click and select **Start**.
   5. Verify that the new FlexNet license server started by checking your EMC Smarts Manager log file. To do so, start your EMC Smarts Manager and view the EMC Smarts Manager log file for two messages that indicate success:

   - ICF-N-LICENSEDFEATURE-Enabling
   - ICF-N-RESTOREFINISH-PersistenceManager: restore finished

   The log filename is based upon the EMC Smarts Manager's name (for example, INCHARGE-SA.log) and the log file is located in the BASEDIR/smarts/local/logs directory.

"Start services" on page 97 provides instructions on starting your EMC Smarts Manager.

NOTICE

On the system where the FlexNet license server and EMC Smarts Broker reside, for a permanent license file, you do not need to edit the SM_LICENSE variable in the runcmd_env.sh file for that product, because by default the **install_license** script adds the SM_LICENSE variable with the appropriate values.

If other products were already deployed on the same system, you do not need to manually edit the SM_LICENSE variable in the runcmd_env.sh file for those products if the new FlexNet license server is set up on the same system as the old license server.

If the new FlexNet license server is set up on a different system than the old license server or if you installed other 9.4.2 products on the same system, you need to manually edit the SM_LICENSE variable in the runcmd_env.sh file for those products. "Access to FlexNet license server using SM_LICENSE" on page 67 provides additional information.

For example, if the Service Assurance Manager and IP Manager reside on System1 and the **install_license** script is invoked from the /opt/InCharge/SAM/smarts/script directory, the script modifies the variable, but you will have to modify the variable for the 9.4.2 IP Manager.

8. Uninstall the old license server using the **install_license** script.

   For example, command on UNIX systems is:

   ```
   # /opt/InCharge/SAM/smarts/script>install_license.sh uninstall
   ```

   Command on Windows systems is:

   ```
   C:\InCharge\SAM\smarts\script>install_license.cmd uninstall
   ```

Access to FlexNet license server using SM_LICENSE

NOTICE

If you set up the new FlexNet license server on the same system as the old license server, you do not need to modify the SM_LICENSE variable for other EMC Smarts software installations. You can skip this task.

When you install EMC Smarts software on more than one system, you must ensure that the EMC Smarts software on each system can connect to the FlexNet license server in order to be able to check out licenses. For the system where you installed the FlexNet license server, the SM_LICENSE variable is added automatically by the **install_license** script. For other EMC Smarts software installations, you need to modify the variable.

To set up licensing for other products or the Global Console, you need to set the SM_LICENSE variable to specify the ‹*port*›@‹*lic_host*› of the FlexNet license server.

Use the **sm_edit** utility to edit the SM_LICENSE variable in the runcmd_env.sh file. The runcmd_env.sh file resides in the BASEDIR/smarts/local/conf directory of the product.

Perform the following steps:

1. For UNIX, invoke **sm_edit** from the BASEDIR/smarts/bin directory:

   ```
   % sm_edit conf/runcmd_env.sh
   ```

   To open runcmd_env.sh on Windows, invoke **sm_edit** utility as follows:

   ```
   C:\>sm_edit conf\runcmd_env.sh
   ```

   For example on Windows, type:

   ```
   C:\InCharge\SAM\smarts\bin>sm_edit conf\runcmd_env.sh
   ```

2. Set the SM_LICENSE variable to ‹*port*›@‹*lic_host*› of the FlexNet license server.

   The runcmd_env.sh file should resemble the following:

   ```
   SM_BROKER_DEFAULT=localhost:426
   SM_LICENSE=1744@SYSTEM1
   SM_SNMP_BUG_COMPATIBLE=TRUE
   SM_INCOMING_PROTOCOL=1,0
   SM_OUTGOING_PROTOCOL=1,0
   ```

3. Save the runcmd_env.sh file and close it.

   Any EMC Smarts program within a product started after this point will use the applicable environment variables specified in the runcmd_env.sh file. EMC Smarts programs that are already running need to be restarted for any new environment variable to take effect. “Start services” on page 97 provides instructions on starting services.

Configuring license server behind the firewall

If the FlexNet license server is deployed on the opposite side of a firewall from your IP installation, you need to perform the following changes in the permanent license file:

1. Open the permanent license file for editing in an appropriate editor.
2. Type `PORT=<port_number>` after the line
   `VENDOR sm_lmgrd92 /opt/InCharge/IP/smarts/bin/system/sm_lmgrd92`

   After making the changes, it must look similar to:
   `VENDOR sm_lmgrd92 /opt/InCharge/IP/smarts/bin/system/sm_lmgrd92 PORT=<port_number>`
3. Save and close the permanent license file.

Post-migration tasks

Perform these tasks after the data migration steps are complete:

1. “Rename the repository file” on page 69
2. “Ensure that the Broker host:port is updated in the runcmd_env.sh files” on page 69
3. “Remove the old out-of-date service entries” on page 70
4. “Change the secret phrase to match rest of deployment” on page 70
5. “Uninstall the old software” on page 70

Rename the repository file

For a same host or different host migration, the old repository file is copied to the BASEDIR/smarts/local/repos/icf directory in the 9.4.2 installation. Because the repository file has a version number extension (for example, .2.0 extension), rename the repository file without the .2.0 extension before using it.

As further information, regardless of whether the old installation is on a Windows system or a UNIX system, sm_migrate saves the old repository file and all other customization files in DOS (Windows) format. If the new installation is on a UNIX system, sm_migrate automatically converts the repository file and all other customization files to UNIX format.

Ensure that the Broker host:port is updated in the runcmd_env.sh files

If you are installing the 9.4.2 Broker during the installation to a location that is different from where the Broker for the previous installation resides, for each server that is registered with the Broker, you need to use the sm_edit utility to edit the SM_BROKER_DEFAULT variable in the runcmd_env.sh file in each of those server's BASEDIR/smarts/local/conf directory with the hostname (and port) of the host system that is running the Broker:

If the Broker host is resolved using a DNS name, this step is not necessary. It is recommended not to use Name Server Caching Daemon (NSCD) to cache DNS lookups (the host's database) in Linux.

1. Run BASEDIR/smarts/bin/sm_service show --cmdline (UNIX) or BASEDIR\smarts\bin\sm_service.exe show --cmdline (Windows) from your older product to get a listing of all installed services. Save the output. For example:

   ```
   C:\InCharge\IP\smarts\bin\sm_service.exe show --cmdline
   ```

2. For each service that you have installed, you will see output similar to the following:

   ```
   sm_service install --force --name=ic-broker
   --description="EMC Broker"
   --env=SM_CLIENTCONNECT=brokerConnect.conf --startmode=runonce
   C:\InCharge\IP\smarts\bin\brstart.exe --port=426
   --restore=C:\InCharge\IP\smarts/local/repos/broker/broker.rps
   --output
   ```

   where ic-broker is the name of the service for which you are interested.

NOTICE

While performing a migration, if you select to retain the security configuration files, ensure to update the parameters SM_LICENSE, SM_FIXED, SM_JAVAHOME in the runcmd_env.sh file with the 9.4.2 installation path.

Remove the old out-of-date service entries

Use the following command to remove all old services that are going to be replaced by the 9.4.2 product:

```
<BASEDIR>/smarts/bin/sm_service remove <service name>
```

If you are installing under Windows operating systems, you must restart the server to remove all traces of the services that you uninstalled. However, do not restart the server before the 9.4.2 product configuration (renaming services, servers, editing settings, and so on) is completed.

For UNIX, you also need to point the product to the new 9.4.2 services that will be installed. Do this by making a copy of /etc/init.d/ic-serviced, change the SMHOME variable to point to the 9.4.2 services, and place it in the 9.4.2 /etc/init.d directory.

Change the secret phrase to match rest of deployment

If the rest of the deployment uses a different site secret, and assuming that you want to employ secure communications between the component applications in the deployment, you need to change the site secret of this installation to match the rest of deployment. You do so by using the deployment's site secret to recreate and encrypt the clientConnect.conf, serverConnect.conf, brokerConnect.conf, and .imk.dat files in the BASEDIR/smarts/local/conf directory of this installation.

Use the sm_rebond command to encrypt the files. For example, from the BASEDIR/smarts/bin directory, enter:

```
sm_rebond --basedir=/opt/InCharge/IP/smarts
```

The *EMC Smarts System Administration Guide* provides complete information about the security files and encryption.

Uninstall the old software

If the new version of the product is functioning properly, all data has been migrated to the new version, and all services are functioning properly, you should uninstall the previous version of the product.

For Windows only, if you use the Windows "Add/Remove Programs" capability at this point, you will be incorrectly uninstalling version 9.4.2 instead of the previous version. Therefore, you must uninstall the older product applications by using the uninstaller.exe from the older base directory.

Uninstalling the previous version of the product will prevent conflicts if the previous version is started by mistake while 9.4.2 is running. Chapter 8, "Performing an Uninstallation," provides more information.

Uninstall will display errors if services were installed by the installation program when the old version was installed, but were removed manually in a later step. The uninstall process will display errors because it will not find the services when it tries to remove them.

CHAPTER 6
Migration Utilities

This chapter describes the migration utilities and provides procedures for using them. The chapter consists of the following topics:

- Customization migration utility overview 72
- sm_migrate function 74
- Customization migration procedures 76
- Perform a rollback 82
- Custom file migration use cases 83
- Three-way merge utility 86
- Automatically migrate topology for IP Manager using RPS utility 88
- Deployment utility overview 89

Customization migration utility overview

The sm_migrate utility is used to migrate user-customized files from an old installation to a new installation, where the old installation and the new installation are in different installation directories or, for an upgrade installation, in the same installation directory. User-customized files include user-modified files (using sm_edit), user-introduced files, and the repository file.

NOTICE

If TTPs (Temporary Test Patch) are installed on a previous installation of SAM, you must first uninstall the TTP and then run the utility. Else, TTP files will be treated as files modified by you and copied to the local directory in the new installation area.

NOTICE

When migrating a customized file from an old installation to a new installation, if a file with the same name exists in the local directory of the new installation, the Customization Migration Utility does not modify or overwrite it. The utility skips all such files being considered for merging. For files being considered to be copied-over, the utility migrates the files with the old version number appended to the file name.

sm_migrate modes of operation

The sm_migrate has seven command-line options:

- --old (or -o)
- --new (or -n)
- --archive (or -a)
- --upgrade (or -u)
- --rollback (or -r)
- --silent (or -s)
- --sitemod (or -l)
- --help (or -h)

These command-line options can be used in pairs in the command line to achieve eight different modes of operation described below.

SAME HOST MODE

This mode is used when the new installation and the old installation are on the same host, in two separate locations. In this mode, sm_migrate migrates all customizations (non-binary files that have been modified or introduced by you in the old installation) from the old installation to a new installation.

NOTICE

All files that were modified or newly introduced in the old installation must be present only under the BASEDIR/smarts/ directory.

When you use the --sitemod option, the migration utility will migrate all customized old files for all user created locals.

DIFFERENT HOST - OLD MODE

This mode is used when the new installation and the old installation are on different hosts. In this mode, sm_migrate backs up and creates tar or a zip archive (file) of the customizations in the old installation. The tar or zip file resides in the location specified by you while executing the utility.

NOTICE

To run the utility from an older version of a Smarts product that does not have the migration utility, you must copy the sm_migrate.pl script and certain Perl files (packaged in migratePerlPkg.zip file) and place them in the appropriate locations. The sm_migrate.pl must be placed in the bin directory and the Perl package must be placed under the BASEDIR/smarts/local folder and extracted there.

When you use the --sitemod option, the migration utility will migrate all customized old files for all user created locals.

After running DIFF_HOST_OLD mode and before running DIFF_HOST_NEW mode, you must manually move the tar or zip archive from the old host to the new host, preferably under the smarts directory of your new installation.

DIFFERENT HOST - NEW MODE

This mode is also used when the new installation and the old installation are on different hosts. In this mode, sm_migrate migrates the customizations from the tar or zip archive that was created in the old installation to the local directory under the new installation and attempts to merge the files from your new installation with the files present in the backup archive wherever applicable, and places them in your new local directory.

UPGRADE MODE

This mode is used during an in-place upgrade, where the installer creates a backup of the files modified or newly introduced by you in the old installation into a .migrate.bkp.‹old_version› backup directory and merges them into a new installation. This mode has been designed for the installer, but can be invoked by you too.

NOTICE

This mode must not be invoked by you if there are multiple .migrate.bkp.‹version› directories under the ‹BASEDIR/smarts directory.

ROLLBACK MODE

In any execution of the migration utility, before the utility migrates your customizations from the backup directory to your new installation, it creates a backup of certain files in your current new local and stores it in a .rollback_‹version_timestamp› directory. Also, it records the version and timestamp before any migration.

The rollback option allows you to reverse the changes made by the migration utility by restoring the local version in your new installations using files from the .rollback_‹version_timestamp› directory. Rollback will contain only those locals which are part of migration.

NOTICE

In some scenarios, if a file is copied to the new installation with .‹old_version› extension, then this file is not deleted when a rollback is performed.

The rollback action is restricted only to rollback points that were recorded in your current version. For example if you upgrade from 9.3.0.0 to 9.4.0.0, and then install a patch (for example, 9.4.0.1), the rollback utility will not allow you to rollback to your 9.4.0.0 local version. You have to manually uninstall the patch in order to rollback to 9.4.0.0.

NOTICE

You can use the rollback option only after an in-place upgrade or if you have previously run the migration utility either in the SAME_HOST, DIFFERENT_HOST or UPGRADE_NEW modes.

"Perform a rollback" on page 82 describes the procedure for carrying out a rollback.

sm_migrate function

The customization migration utility is capable of four major functions, which include:

- Copying all non-binary files from the ‹BASEDIR›/smarts/local folder that have been modified or introduced by you in the previous version of the product into the appropriate backup directories under the ‹BASEDIR›/smarts directory of the new installation. Table 11 on page 74 provides details on the backup directories created by the utility during the migration and upgrade process.

Table 11 Details of backup folders created by sm_migrate utility

Scenario	Name and location of backup folders under ‹BASEDIR›/smarts
Migration on same host	.migrate.bkp.‹old_version›, .rollback_‹version_timestamp›
Migration on different host old mode	user-defined tar or zip file name,
Migration on different host new mode	.rollback_‹version_timestamp›, .migrate.bkp.‹old_version›
Upgrade	.migrate.bkp.‹old_version›, .rollback_‹version_timestamp›

For files that have been modified by you, the utility also creates a copy of the base files from the ‹BASEDIR›/smarts folder. These files are backed up into .migrate.bkp.‹old_version› directory. The original and the local versions of the files from the old installation will be needed when the utility attempts to merge your changes with the new installation files.

Under the smarts/.migrate.bkp.‹old_version› and backup.tar or backup.zip directory you can find files with the following extensions:

- .custom - files from the ‹BASEDIR›/smarts/local folder introduced by you and are not part of the default installation
- .local - files from the ‹BASEDIR›/smarts/local folder that are part of the default installation and have been modified from their original version, using sm_edit.
- .base - the ‹BASEDIR›/smarts version of these files with .local extension

"Custom file migration use cases" on page 83 provide details.

- Copying the cacert.sso certificate file from ‹BASEDIR›/smarts/jre/lib/security directory into the .migrate.bkp.‹old_version›/jre/lib/security directory to retain the certificate file.
- Copying all files you have added into the ‹BASEDIR›/smarts/local folder of the new installation. This allows for an easy and automatic migration of all customer files to the new installation, so that no manual step is required for moving the files from the backup directory.

  NOTICE

  All files, customized or newly introduced in the existing installation, must be present under the ‹BASEDIR›/smarts/ folder only. The utility also copies the RPS files found in the old_local.

- Merging .asl, .import, .conf, .xml, .pl, .sh and .cmd files modified by you into the new installation. The utility first backs up the corresponding files from the old_base, and then migrates the files from .migrate.bkp.‹old_version› backup directory to the new installation.

  NOTICE

  This is an optional function and you may skip it.

  In order to merge the configurations from the existing installation into the new installation, the utility uses files from:

  - Original base installation (previous installation with ‹file_name›.base extension)
  - Local directory of the previous installation (files you have modified with a ‹file_name›.local extension)
  - New installation (with ‹file_name› extension)

  The files to be merged are put in the new_local after performing a three-way merge between the two files in the backup directory and the corresponding file in the new base.

- Rolling back changes made by the sm_migrate utility in your current installation. It creates a backup of the new_local, and allows you to rollback to multiple stages of backup, as long as the changes were carried out in your current version. The backup consists of all .conf, .import, .asl, .mdl, .xml, .template, .sh, .conflict, .automerge, .cmd, .dat, and .bat files found in the new_local.

NOTICE

Soft links created for product related files in the UNIX environment are not handled by sm_migrate utility.

Customization migration procedures

Run the sm_migrate utility immediately after the installation and before you start any services or modify any files in the new installation. Back up the BASEDIR/smarts/local directory in the new installation before you run sm_migrate.

NOTICE

When you run the sm_migrate utility, ensure that you run only one instance of sm_migrate utility.

On a Windows host, be aware that performing a migration takes a considerable amount of time. Be patient. Do not stop the migration process.

Migrating customizations on the same host

Use the following steps to migrate customizations on the same host:

1. Go to the BASEDIR/smarts/bin directory of the new installation and type the following command on one line to invoke the sm_migrate utility:

```
sm_perl sm_migrate.pl --old=<BASEDIR>/smarts (old installation)
--new=<BASEDIR>/smarts (new installation)
--sitemod=<BASEDIR>/smarts/local;local1
```

For example:

IP Manager

```
c:\InCharge93\IP\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge93\IP\smarts --new=c:\Incharge94\IP\smarts
--sitemod=c:\Incharge94\IP\smarts\local1;
c:\Incharge94\IP\smarts\local2
```

Service Assurance Manager

```
c:\InCharge\SAM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge\SAM\smarts --new=c:\Incharge\sam\smarts
--sitemod=c:\Incharge94\SAM\smarts\local1;
c:\Incharge94\SAM\smarts\local2
```

MPLS Manager

```
c:\InCharge93\MPLS\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge93\MPLS\smarts --new=c:\Incharge94\MPLS\smarts
--sitemod=c:\Incharge94\MPLS\smarts\local1;
c:\Incharge94\MPLS\smarts\local2
```

Server Manager

```
c:\InCharge\ESM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge\ESM\smarts --new=c:\Incharge\ESM\smarts
--sitemod=c:\Incharge94\ESM\smarts\local1;
c:\Incharge94\ESM\smarts\local2
```

Network Protocol Manager

```
c:\InCharge\NPM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge\NPM\smarts --new=c:\Incharge\NPM\smarts
--sitemod=c:\Incharge94\NPM\smarts\local1;
c:\Incharge94\NPM\smarts\local2
```

Optical Transport Manager

```
c:\InCharge\OTM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge\OTM\smarts --new=c:\Incharge\OTM\smarts
--sitemod=c:\Incharge\OTM\smarts\local1;
c:\Incharge\OTM\smarts\local2
```

VoIP Availability Manager

```
c:\InCharge\VoIP\smarts\bin>sm_perl sm_migrate.pl
--old=c:\Incharge\VoIP\smarts --new=c:\Incharge\VoIP\smarts
--sitemod=c:\Incharge94\VoIP\smarts\local1;
c:\Incharge94\VoIP\smarts\local2
```

The utility carries out the following steps:

- Verifies the presence of the existing installations in the specified directories.
- Determines the files in the old installation that must be copied.
- Lists the files that were modified by you. The utility skips files that were introduced by the patch but not modified by you.
- Copies the user-modified files to a backup directory in the BASEDIR/smarts/.migrate.bkp.‹old_version› directory in the new installation.

2. Press **y** or any other key to start the file merge utility (sm_merge), and then press **Enter**. The sm_merge utility is invoked individually for each of the files that may require a three-way merge. ("Three-way merge utility" on page 86 provides details.) Once the utility completes merging the files, a message is displayed that indicates successful completion of the process.

   or

   Press **n** to skip the invocation of the sm_merge utility.

3. Review the files (merged, auto-merged and .conflict) after the migration is over. Take appropriate actions as mentioned in the "User Action" column in "Custom file migration use cases" on page 83.

4. Press **y** or any other key to copy security configuration files, and then press **Enter**. This will copy the security configuration files from .migrate.bkp.‹version›/conf to local/conf of the new installation.

   or

   Press **n** to skip the copying of security configuration files.

Migrating customizations to a different host

Use the following steps to migrate customizations on remote hosts:

1. Prepare to archive the customizations made in the old installation into a tar or zip archive by copying the following files:
   - Perl packages: Copy migrateperlpkg.zip from the BASEDIR/smarts/perl directory in the new installation to the BASEDIR/smarts/local directory of the old installation. For Linux and CentOS, use the unzip migrateperlpkg.zip command, and on Windows use the WinZip software to extract the contents in the zipped file to the BASEDIR/smarts/local directory.
   - sm_migrate.pl utility: Copy this file from the BASEDIR/smarts/bin directory of the new installation to the BASEDIR/smarts/bin directory of your old installation.
2. Go to the BASEDIR/smarts/bin directory of your old installation and enter the following command on one line to generate an archive of the customizations:

```
sm_perl sm_migrate.pl --old=<BASEDIR>/smarts (old installation)
--archive=<BASEDIR>/smarts/<tar or zip file to contain
customizations> ----sitemod==<BASEDIR>\smarts\local1;
=<BASEDIR>\smarts\local2
```

NOTICE

It is recommended to save the archive with .zip extension if you are installing the 9.4.2 product on a Windows platform and .tar extension if you are installing the 9.4.2 product on Linux and CentOS platforms.

For example:

IP Manager

```
c:\InCharge93\IP\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge93\IP\smarts
--archive=c:\InCharge93\IP\smarts\backup.zip
--sitemod=c:\InCharge93\IP\smarts\local1;c:\InCharge93\IP\
smarts\local2
```

Service Assurance Manager

```
c:\InCharge\SAM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge\SAM\smarts
--archive=c:\InCharge\SAM\smarts\backup.tar
--sitemod=c:\InCharge\SAM\smarts\local1;c:\InCharge\SAM\
smarts\local2
```

MPLS Manager

```
c:\InCharge93\MPLS\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge93\MPLS\smarts
--archive=c:\InCharge93\MPLS\smarts\backup.zip
--sitemod=c:\InCharge93\MPLS\smarts\local1;c:\InCharge93\MPLS\
smarts\local2
```

Server Manager

```
c:\InCharge\ESM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge\ESM\smarts
--archive=c:\InCharge\ESM\smarts\backup.tar
--sitemod=c:\InCharge\ESM\smarts\local1;c:\InCharge\ESM\smarts\
local2
```

Network Protocol Manager

```
c:\InCharge\NPM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge\NPM\smarts
--archive=c:\InCharge\NPM\smarts\backup.tar
--sitemod=c:\InCharge\NPM\smarts\local1;c:\InCharge\NPM\
smarts\local2
```

Optical Transport Manager

```
c:\InCharge\OTM\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge\OTM\smarts
--archive=c:\InCharge\OTM\smarts\backup.tar
--sitemod=c:\InCharge\OTM\smarts\local1;c:\InCharge\OTM\
smarts\local2
```

VoIP Availability Manager

```
c:\InCharge\VoIP\smarts\bin>sm_perl sm_migrate.pl
--old=c:\InCharge\VoIP\smarts
--archive=c:\InCharge\VoIP\smarts\backup.tar
--sitemod=c:\InCharge\VoIP\smarts\local1;c:\InCharge\VoIP\smarts\
local2
```

The utility carries out the following functions:

- Verifies the presence of an existing installation in the specified directory.
- Determines the files that must be copied.
- Lists the files that were modified by you. The utility skips files that were introduced by the patch but not modified by you.
- Archives the backup directory into the specified tar or zip archive.

3. Transfer the tar or zip archive that is created in step 2 to the BASEDIR/smarts directory on the host with the 9.4.2 installation.
4. Go to the BASEDIR/smarts/bin directory of your new installation and enter the following command on one line to migrate the customizations from the old installation to your new installation:

```
sm_perl sm_migrate.pl --new=<BASEDIR>/smarts (new installation)
--archive=<BASEDIR>/smarts/<tar or zip file that contains
customizations>
```

For example:

IP Manager

```
c:\InCharge93\IP\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge93\IP\smarts\backup.zip
--new=c:\InCharge93\IP\smarts
```

Service Assurance Manager

```
c:\InCharge\SAM\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge\SAM\smarts\backup.tar
--new=c:\InCharge\SAM\smarts
```

MPLS Manager

```
c:\InCharge93\MPLS\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge93\MPLS\smarts\backup.zip
--new=c:\InCharge93\MPLS\smarts
```

Server Manager

```
c:\InCharge\ESM\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge\ESM\smarts\backup.tar
--new=c:\InCharge\ESM\smarts
```

Network Protocol Manager

```
c:\InCharge\NPM\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge\NPM\smarts\backup.tar
--new=c:\InCharge\NPM\smarts
```

Optical Transport Manager

```
c:\InCharge\OTM\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge\OTM\smarts\backup.tar
--new=c:\InCharge\OTM\smarts
```

VoIP Availability Manager

```
c:\InCharge\VoIP\smarts\bin>sm_perl sm_migrate.pl
--archive=c:\InCharge\VoIP\smarts\backup.tar
--new=c:\InCharge\VoIP\smarts
```

NOTICE

In a Windows environment, you may notice that it takes a longer time to extract the sm_migrate.pl utility and carry out a migration. This behavior is expected and hence do not stop the migration process.

The utility completes the following steps:

- Verifies the presence of the new installation in the specified directory and the existence of the specified tar or zip archive.
- Reads the tar or zip archive and determines the files that must be copied.
- Copies the files from the tar or zip archive to a backup directory in BASEDIR/smarts/.migrate.bkp.‹old_version›.
- Creates ‹BASEDIR›/smarts/.rollback_‹version_timestamp› directory
- Lists the files that were modified by you.

5. Press **y** or any other key to start the file merge utility (sm_merge), and then press **Enter**. The sm_merge utility is invoked individually for each of the files that may require a three-way merge. ("Three-way merge utility" on page 86 provides details.) Once the utility completes merging the files, a message is displayed that indicates successful completion of the process.

   or

   Press **n** to skip the invocation of the sm_merge utility.

6. Review the files (merged, auto-merged and .conflict) after the migration is over. Take appropriate actions as mentioned in the "User Action" column in "Custom file migration use cases" on page 83.

7. Press **y** or any other key to copy security configuration files, and then press **Enter**. This will copy the security configuration files from .migrate.bkp.‹version›/conf to local/conf of the new installation.

   or

   Press **n** to skip the copying of security configuration files.

Restoring customizations after an upgrade installation

During an upgrade, the installer creates a backup of your customizations and places them in the ‹BASEDIR›/smarts/.migrate.bkp.‹version› directory.

If during the installation you choose to skip migrating the files back into your new local directory, you may either manually migrate or merge the files into your new local installation directory or run the sm_migrate utility in the UPGRADE mode to perform this action.

Use the following steps to run the sm_migrate utility:

1. Go to the ‹**BASEDIR**›/smarts/bin folder.
2. Type the following command to migrate the backup directory to the new installation:

   ```
   ./sm_perl sm_migrate.pl
   --new=<new installation location up to and including smarts>
   --upgrade --silent
   ```

   NOTICE

   It is optional to specify the --silent option in the command. Setting the --silent option does not print any messages to the screen. Using this option with sm_migrate utility will invoke the sm_merge utility automatically and does not prompt for your input.

   For example:

   ```
   c:\InCharge\SAM\smarts\bin>sm_perl sm_migrate.pl
   --new=c:\InCharge\SAM\smarts --upgrade
   ```

   The utility carries out the following functions:

   - Identifies the ‹BASEDIR›/smarts/.migrate.bkp.‹old_version› directory. The directory contains all files that were introduced by you in the previous version of the application. It also contains files that have been modified by you in the previous install under local and the version of those files from ‹BASEDIR›.
   - Copies the files introduced by you back under ‹BASEDIR›/local.
   - Prompts you to run the sm_merge utility and merges the files in your new installation with the files contained in the backup directory wherever applicable, and places the resultant files in your new local directory.
   - Creates ‹BASEDIR›/smarts/.rollback_‹version_timestamp› directory
   - On completion, it lists the files which were introduced or modified by you and the merge status of the files.

3. Press **y** or any other key to start the file merge utility (sm_merge utility), and then press **Enter**. The utility is invoked individually for each of the files that may require a three-way merge. “Three-way merge utility” on page 86 provides details. Once the utility completes merging the files, a message is displayed indicating successful completion of the process.

   or

   Press **n** to skip the invocation of the file merge utility.

NOTICE

You may use an additional --silent option to avoid this prompt. In which case, by default, the utility will attempt the three-way merge.

4. Press **y** or any other key to copy security configuration files, and then press **Enter**. This will copy the security configuration files from .migrate.bkp.‹version›/conf to local/conf of the new installation.

   or

   Press **n** to skip the copying of security configuration files.

5. Review the files (merged, auto-merged and .conflict) after the migration is over. Take appropriate actions as mentioned in the 'User Action' column in "Custom file migration use cases" on page 83.

Perform a rollback

Use the following steps to rollback changes made by the sm_migrate utility:

1. Go to the ‹**BASEDIR**›/smarts/bin folder of your new installation, and type the following command to rollback the changes made by sm_migrate utility to your new installation:

   ```
   ./sm_perl sm_migrate.pl --new=<new_installation location _upto_and
   including smarts> --rollback [--silent]
   ```

   NOTICE

   It is optional to specify the [--silent] option in the command. The [--silent] option allows you to carry out the rollback without any prompts.

   For example:

   ```
   c:\InCharge\SAM\smarts\bin>sm_perl sm_migrate.pl
   --new=c:\InCharge\SAM\smarts --rollback
   ```

   The utility carries out the following steps:

   - Looks in the rollback record and displays the possible timestamps you can rollback to. If the utility finds more than one possible rollback timestamp, it allows you to choose a specific timestamp, and requests a confirmation for rollback. In the Silent mode, the utility chooses the latest timestamp by default, and proceeds with the rollback without an explicit request for confirmation.
   - Cleans the current local directory - the utility traverses the current local directory and deletes all the .conf, .import, .asl, .mdl, .xml, .template, .sh, .bat and .cmd files, except the clientConnect.conf, serverConnect.conf, brokerConnect.conf and runcmd_env.sh files.
   - Traverses the backup directory for rollback and copies back all the files into the current local directory.

Custom file migration use cases

The use cases for custom file migration and resulting backup and merge activities are described in Table 12 on page 83.

NOTICE

‹file_name› with no extension represents a base file that is present under the BASEDIR/smarts directory of the new installation.

Table 12 Custom file migration use cases (page 1 of 3)

Use case	Backup action	Merge Action	
Old installation	**New installation: BASEDIR/smarts/ .migrate.bkp.‹version›**	**New_installation: BASEDIR/smarts/local**	**User action**
There is a local copy of a file, and changes were introduced by you. The file is also used in the new base installation.	Back up the base and the local copies of the file. The base copy is backed up with “base” extension, as ‹file_name›.base. The local copy will be backed up with “local” extension, as ‹file_name›.local. Local name will be customized name of local. For example: ‹file_name›.local123.	Run sm_merge for: • ‹file_name›.base • ‹file_name›.local • ‹file_name› Merge Outcome: • Changes made by you are merged into the new file and placed in ‹New_installation›/smarts/local/‹file_name›.conf • If the changes made by you could not be merged without a conflict, a .conflict file is generated and placed in ‹New_installation›/smarts/local/‹file_name›.conflict	• Because the three-way merge utility works at a string level and not at a code level for files such as .asl, .xml, .cmd, and .sh, the merge result of these files is appended with .automerge extension. Review the files, and if the changes are acceptable, save the file without .automerge extension. • Files with .import and .conf extension are not appended with an automerge extension on successful merge. • For conflict files, review the conflict file, manually resolve the conflict, and save the file without a .conflict extension.
There is a file in old base, old local and the same file exists in new base.	No backup action.	No merge.	No user action required.
There is a file in old base and the same file exists in new base.	No backup action.	No merge.	No user action required.
The local copy of the file that was introduced by a patch and later modified by you. The file exists in the new base, but does not exist in the old base.	Back up the local copy of the file. The local copy will be backed up with “local” extension, as ‹file_name›.local. Local name will be customized name of local. For example: ‹file_name›.local123.	sm_merge utility will compare ‹file_name›.local and ‹file_name›. Merge Outcome: ‹file_name›.conflict	Review the conflict file, manually resolve the conflict and save the file without a .conflict extension.

Table 12 Custom file migration use cases (page 2 of 3)

Use case	Backup action	Merge Action	
Old installation	New installation: BASEDIR/smarts/ .migrate.bkp.‹version›	New_installation: BASEDIR/smarts/local	User action
There is a local copy of the file, and changes were introduced by you, but the file is no longer used in the new release.	Backup the base and the local copies of the file. The base copy is backed up with “base” extension, as ‹file_name›.base. The local copy will be backed up with “local” extension, as ‹file_name›.local. Local name will be customized name of local. For example: ‹file_name›.local123.	No merge	The files remain in the backup directory. Determine if the customization is still relevant to the new installation.
The local copy of the file was introduced by a patch, and changes were made by you. The file does not exist in either the new or old base.	Backup the local copy of the file. The local copy will be backed up with “local” extension, as ‹file_name›.local. Local name will be customized name of local. For example: ‹file_name›.local123.	No merge	Determine if the customization is still relevant to the new installation.
There is a local copy of the file, and changes were made by you. The file is also used in the new version, and there is already a local copy of the file in the new local.	Backup the local copy of the file. The local copy will be backed up with “local” extension, as ‹file_name›.local. Local name will be customized name of local. For example: ‹file_name›.local123.	No merge	The sm_merge gives precedence to the files in new_local. No changes will be made to the files that are already under new_local. Key exceptions to the rule are covered in the “Migration of security configuration files” on page 85.
There is a local copy of the file, and custom code was introduced by you. This code does not exist in either the old or the new base.	Back up the local copy of the file. The local copy will be backed up with “custom” extension, as ‹file_name›.custom.	No merge. Copy the files (without the .custom extension) from New Installation: BASEDIR/smarts/.migrate.bkp. ‹version› to New installation: BASEDIR/smarts/local	Determine whether these custom files are still needed in your new installation.
There is a local copy of the file, and custom code was introduced by you. This file is also used in the new base.	Back up the local copy of the file. The local copy will be backed up with “custom” extension, as ‹file_name›.custom.	No merge. Copy the files (without the .custom extension) from New Installation: BASEDIR/smarts/.migrate.bkp. ‹version› to New installation: BASEDIR/smarts/local The file is copied with .‹old_version› extension.	Determine whether these custom files are still needed in your new installation.

Table 12 Custom file migration use cases (page 3 of 3)

Use case	Backup action	Merge Action	
Old installation	New installation: BASEDIR/smarts/ .migrate.bkp.‹version›	New_installation: BASEDIR/smarts/local	User action
There is a local copy of the file, and changes were made by you. The file is also used in the new version, and there is already a local copy of the file in the new local introduced by a patch.	Back up the base and the local copies of the file. The base copy is backed up with “base” extension, as ‹file_name›.base. The local copy will be backed up with “local” extension, as ‹file_name›.local. Local name will be customized name of local. For example: ‹file_name›.local123.	Run sm_merge for: • ‹file_name›.base • ‹file_name›.local • ‹file_name› Merge Outcome: • Changes made by you are merged into the new file and placed in ‹New_installation›/smarts/local/‹file_name›.conf • If the changes made by you could not be merged without a conflict, a .conflict file is generated and placed in ‹New_installation›/smarts/local/‹file_name›.conflict	• Because the three-way merge utility works at a string level and not at a code level for files such as .asl, .xml, .cmd, and .sh, the merge result of these files is appended with .automerge extension. Review the files, and if the changes are acceptable, save the file without .automerge extension. • Files with .import and .conf extension are not appended with an automerge extension on successful merge. • For conflict files, review the conflict file, manually resolve the conflict, and save the file without a .conflict extension.

Migration of security configuration files

The sm_migrate utility prompts you for copying the security configuration files serverConnect.conf, clientConnect.conf, brokerConnect.conf, runcmd_env.sh and imk.dat. You can either choose to copy these files into the local directory of the new installation or configure these files later, manually.

If you choose to copy and have changed the site secret in your previous installation, you need to run the sm_rebond command to encrypt the files. For example:

```
./sm_rebond --basedir=C:\InCharge\IP\smarts
```

After copying the files, the data in the old runcmd_env.sh file is appended to the new runcmd_env.sh file and the new 9.4.2 version data is commented.

NOTICE

Migration of security configuration files is not supported on cross platforms.

Migration of dynamic model files

The dynamic model files (files with .mdl and .ldm extension) are backed up in the .migrate.bkp.‹version› directory. These files are not considered by sm_migrate utility for merging. Remove the .ldm file from the local directory of the new installation. Recompile the .mdl file before it is used in the new installation. A new .ldm file will be generated once you recompile the .mdl file.

The *EMC Smarts Dynamic Modeling Tutorial* explains the concepts and methods of dynamic modeling.

Three-way merge utility

The three-way merge utility, sm_merge, helps incorporate configuration changes (made in the .conf, .import .asl, .xml, .pl, .sh, and .cmd files) from an old installation into a new installation of a product. The utility performs a three-way merge on each of the files that you have modified.

The utility uses ‹file_name›.base, ‹file_name›.local, and ‹file_name›, and finds the largest sequence of lines that is common to all three files (this sequence need not necessarily be continuous lines). This largest sequence of lines is called the Longest Common Subsequence (LCS). Then, for each of the three files, it finds groups of lines in between two consecutive lines in the LCS. These groups are referred to as “content blocks.” The utility compares these content blocks to decide on merge as given in Table 12 on page 83.

Use cases for content block comparison

The scenarios for comparison of content blocks during the three-way merge process are described in Table 13 on page 86. In this table, X, Y, and Z represent the content blocks, one from each of the three files.

Table 13 Content block comparison use cases (page 1 of 2)

Scenario	Content block comparison	Result

XYY
• Content block in the ‹file_name›.base looks like X
• Content block in ‹file_name›.local looks like Y
• Content block in the ‹file_name› looks like Y
	The following content blocks are picked up:
	• Content block in ‹file_name›.base = X
	`AllowPrivateIPAsName FALSE`
	• Content block in ‹files_name›.local = Y
	`AllowPrivateIPAsName TRUE`
	• Content block in ‹file_name› = Y
	`AllowPrivateIPAsName TRUE`
		Result: Y
		Since the ‹file_name›.local version and the ‹file_name› version of the content blocks match, the Y version is picked.

XYX
• Content block in the ‹file_name›.base looks like X
• Content block in the ‹file_name›.local looks like Y
• Content block in ‹file_name› looks like X
	The following content blocks are picked up:
	• Content block in ‹file_name›.base = X
	`ERXIfExcludeSysPattern router*`
	• Content block in ‹files_name›.local = Y
	`ERXIfExcludeSysPattern *`
	• Content block in ‹file_name› = X
	`ERXIfExcludeSysPattern router*`
		Result : Y
		This is the case where the file modified by you (Y) is preserved and is written to new_local.

Table 13 Content block comparison use cases (page 2 of 2)

Scenario	Content block comparison	Result

X Y Z
• Content block in the ‹file_name›.base looks like X
• Content block in the ‹file_name›.local looks like Y
• Content block in the ‹file_name› looks like Z. This is the case where a .conflict file is created.
	The following blocks sections are picked up:
	• Content block in ‹file_name›.base = X
	`#Enable/Disable discovery of VLANs`
	`PropagateVRIfAlias FALSE`
	• Content block in ‹files_name›.local = Y
	`#Enable/Disable discovery of Router`
	`PropagateVRIfAlias TRUE`
	• Content block in ‹file_name› = Z
	`#Enable/Disable discovery of Multicast # New install changes`
	`PropagateVRIfAlias FALSE`
		Result: Conflict
		All three content blocks will be written into a .conflict file.

During this process, modifications done on each of the files in the old installation are merged into the new installation. The utility identifies the files to be copied and copies them into a predefined new directory in the new installation with an appropriate suffix. Table 12 on page 83 provides details on the files which will be copied:

The utility performs the following functions:

- Automated analysis of the differences between any two files (for example, File A and File B), while also considering the parent file.
- Incorporates the changes done to the parent file in File A and File B, and automatically merges the two changes. This type of merge is used in revision control systems.
- It maintains a record of the conflicts encountered during the merge process in a .conflict file.

In case the utility is unable to merge the files due to some conflict, it creates a .conflict file for each file. The .conflict file provides details of the files which were not completely merged by the three-way utility. Each conflicting instance is recorded in the .conflict file. You can review the .conflict files to spot the conflicts, and manually resolve the differences.

Configuration migration process logs

Table 14 on page 87 lists the logs files that are created for the modified customization migration process. These files are available under the BASEDIR/smarts/setup/logs directory.

Table 14 Log file and description (page 1 of 2)

Log file name	Description
Config_migration_copy.log	Logs information about files that were modified during the previous installation, and those which were backed up in the new installation.
Config_migration_merge.log	Logs information about the files on which three-way merge was performed. It also mentions whether the merge process was successful or if any conflicts arose during the process.

Table 14 Log file and description (page 2 of 2)

Log file name	Description
‹file_name›.conf.MergeLog ‹file_name›.asl.MergeLog ‹file_name›.import.MergeLog ‹file_name›.xml.MergeLog ‹file_name›.sh.MergeLog ‹file_name›.cmd.MergeLog	For each type of file (.conf, .import .asl, .xml, .sh, and .cmd) merge logs are created. These logs record the lines which the three-way merge process copied from the previous installation, lines which were retained as-is, and those where conflicts were observed.

Automatically migrate topology for IP Manager using RPS utility

The repository file (RPS) migration utility (sm_migraterps) automatically converts the RPS file created by the previous version of the software to an RPS file compatible with the newer version of the software. For example, you can use the utility to automatically convert the IP 9.3.0.0 RPS file into a compatible version of IP Manager 9.4. This tool allows the administrator to quickly migrate the product without going through a rediscovery of the entire topology.

The RPS migration utility supports migration from IP Manager 9.x.x versions to IP Manager 9.4.x and later.

If you are migrating from IP Manager 9.3.x, running the RPS migration utility is optional. For example, if you have an IP Manager 9.3 repository file that includes virtual switch systems in the topology, use the sm_migraterps utility to remove VirtualSwitchSystemLink and make the repository compatible for IP Manager 9.4.2.

This section covers the following:

- "Functions of RPS migration utility" on page 88
- "Running RPS migration utility" on page 88

Functions of RPS migration utility

The utility performs the following functions:

- Creates a temporary and a backup copy of the RPS file to be migrated. On successful migration, the backup file is deleted. The tool then renames the temporary file as the new RPS and, the original RPS file as the backup file with a .v70 suffix.
- Checks for the existence of the source RPS file. Users must ensure that they are using a valid source RPS file.

Running RPS migration utility

NOTICE

It is recommended to run the RPS migration utility only once. A second run will overwrite the older backup file.

To run the RPS migration utility:

1. Go to the ‹**BASEDIR**›/smarts/bin folder.

2. Copy the previous version of the RPS file to the ‹**BASEDIR**›/smarts/bin folder.
3. Type the following command:

```
sm_migraterps <rps_file> --trace <logfilename>
```

NOTICE

It is optional to specify the *--trace* option in the command. The *--trace* option provides a line-by-line description with regard to the RPS migration processing.

The RPS file is converted and written to a temporary file. If no errors are detected during the conversion, then the original RPS file will be renamed with a '.v70' suffix, and the temporary file will be renamed to the original. If any errors are encountered during file conversion, the original RPS file remains unchanged.

4. Copy the migrated RPS file into the *‹**BASEDIR**›/smarts/local/repos/icf* folder.
5. Use the *--ignore-restore-errors* option in the sm_service command to start the IP Manager with the migrated repository file. Otherwise, the IP Manager may generate errors and may not start up with the migrated repository file.
6. Initiate a full discovery (Discover All). Consult the discovery guide or user guide for your product for more information on this procedure.

NOTICE

A full discovery is required for the new version features and changes to take effect.

Deployment utility overview

The Deployment Utility allows you to deploy customizations and configuration changes from an existing installation to another installation on the same version of a product. The deployment can be carried out on the same host or between two different hosts running the same operating system.

The utility is useful if you have to apply the same configurations on multiple installations of a product. Use the utility if you have:

- Multiple new installation running on the same or multiple hosts that will need to share the same configuration and customizations.
- Multiple installations on the same or multiple hosts that are upgraded and will share the same configuration and customizations.

In both cases, you will need to start with one installation where you make all your modifications to configuration files, ‹BASEDIR›/smarts/local files and, create and compile dynamic models. Then, run the sm_deploy utility to create a package that contains your modifications. Use the sm_deploy utility to apply the files collected from the first installation to the rest of your installations.

The Deployment Utility performs the following three functions:

- Create a package
- Deploy the package
- Rollback

Create a package

The utility enables you to create a deployment package which consists of all the customizations made to files in an installation. In SAM, by specifying a broker and server information when you run the utility, you can collect configuration settings from RPS into the package.

Deploy the package

The utility enables you to deploy a previously collected deployment package into other installations of the same product running on the same version and operating system as the original installation. If you have collected configuration settings from SAM RPS, the configurations will be available in the file, *‹SAM_server›.xml* under *local/conf/ics* directory.

Rollback

Before deploying the package into an installation, the utility creates a rollback directory containing the backup copy of files from the current installation which will be used incase of a rollback action. You can rollback your configuration to that in your rollback directory, only if the version of your current installation is the same as the version of the installation when the rollback directory was created.

NOTICE

Soft links created for product related files in the UNIX environment are not handled by sm_deploy utility.

Running the Deployment utility

To run the Deployment utility, go to ‹BASEDIR›/smarts/bin directory and type the following command:

```
./sm_perl sm_deploy.pl <options>
```

where, *‹options›* refers to the options specified in the section,"sm_deploy modes of operation" on page 90.

sm_deploy modes of operation

The sm_deploy has the following command-line options:

- --install=‹dir› – To install the utility.
- --create=‹file› – To create the deployment package.
- --deploy=‹file› – To deploy the package.
- --rollback – To rollback the configuration changes.
- --broker – The broker to which the SAM server is attached. Use this option to collect configuration settings from SAM RPS.
- --server – The SAM server whose configuration settings from RPS are to be collected.
- --clean – To clean the files in the local directory.
- --silent

- --sitemod – To specify customer specific local directories.
- --help

The deployment utility must be used with at least one of these options.

NOTICE

If you want to run this utility from older versions of EMC Smarts products, you must copy the sm_migrate.pl script, sm_deploy.pl script and, the Perl files packaged in a .zip file from the 9.4.2 installation to the corresponding locations in the old installation.

To create a deployment package

1. Go to the ‹BASEDIR›/smarts/bin folder of your target installation, and type the following command:

   ```
   ./sm_perl sm_deploy.pl --install=<BASEDIR>/smarts
   --create=<archive-name.tar> --sitemod==<BASEDIR>/smarts/local
   ```

2. The utility identifies the files with customizations from the local directory under ‹BASEDIR›/smarts directory of the installation that need to be copied to the deployment package. Local directory can be local1, local2.
3. The utility copies the files from the local directory to the deployment backup directory *.deploy.bkp‹pdt›.‹version›* under ‹BASEDIR›/smarts, archives these files to a specified archive file and then deletes the backup directory.

Manage RPS file settings across multiple installations

The method of extracting the configuration settings from an RPS file into the deployment package varies between SAM, IP, and VoIP Managers.

For SAM, use the deployment utility to extract the configuration settings from the RPS file.

Go to the ‹BASEDIR›/smarts/bin folder of your target installation, and type the following command:

```
./sm_perl sm_deploy.pl --install=<BASEDIR>/smarts
--create=<archive-name.tar> --broker=<host:port>
--server=<SAM_server>
```

If a server is specified, the utility collects the configurations into the file, *‹SAM_server›.xml* under *local/conf/ics* directory.

This can be a convenient way to deploy the configurations of aggregate SAM domain since they often share the same configuration.

For IP, use the *sm_settings.pl* script of the *IP-Configuration Manager* tool to export the Polling and Threshold groups from an existing domain and import them into the IP-Configuration Manager to be deployed further on other domains.

For more information on loading settings into IP-Configuration Manager, refer to the *EMC Smarts IP Manager User Guide*.

For VoIP Availability Manager, Network Protocol Manager, MPLS Manager, and Server Manager, the configuration settings from an RPS file must be manually configured in all other installations of these products.

To deploy the package

1. Go to the ‹BASEDIR›/smarts/bin folder of your target installation, and type the following command:

   ```
   ./sm_perl sm_deploy.pl --install=<TargetBASEDIR>/smarts
   --deploy=<archive-name.tar>
   ```

   The utility extracts the archive into the backup directory *.deploy.bkp‹pdt›.‹version›* under ‹BASEDIR›/smarts.

2. Creates a rollback directory with the backup of files from the target installation which will be used incase of a rollback action. Rollback will contain local folders which are part of the deployment package.

3. Copies all the files from the deployment package to the local directory of the target installation.

4. Overwrites the files that are part of both, the deployment package and the local directory of the target installation.

5. If the *--clean* option is specified, the files in the local directory of the target installation that are not part of the deployment package are deleted.

   Or

   If *--clean* option is not specified, the files in the local directory of the target installation that are not part of the deployment package are retained.

To deploy the SAM RPS settings,

- Manually import the *‹SAM_server›.xml* file from local/conf/ics directory to the directory in the target installation by typing the following sm_config command:

```
./sm_config --server=<SAM_server> import --force <SAM_server>.xml
```

To Rollback

1. Go to the ‹BASEDIR›/smarts/bin folder of your target installation, and type the following command:

   ```
   ./sm_perl sm_deploy.pl --install=<TargetBASEDIR>/smarts --rollback
   ```

   The utility displays all the rollback directory locations to which you can rollback.

2. Copies the files from the local directory of the installation whose rollback directory you choose to rollback to, into the corresponding location in your current installation.

NOTICE

If your current directory is a rollback directory location, it will not be displayed in the list of rollback directory locations to which you can rollback.

CHAPTER 7
Verifying the Installation

This chapter describes tasks for confirming proper installation of the Service Assurance Manager, IP Manager, MPLS Manager, Server Manager, Network Protocol Manager, Optical Transport Manager, and VoIP Availability Manager. It consists of the following topics:

- Check the version number 94
- Obtain and install a temporary license file 95
- Start services 97
- Start programs 98
- Service and program startup options 99
- Start Smarts NOTIF 100
- Verify the product status 102
- Verify the FIPS 140 mode status 103
- Collect system information 104
- Configuration Scanner Tool 108

Check the version number

When you run a utility to report the version number of the software, you will see both the version number for the product as well as the version number for the underlying foundation software. These two version numbers might differ.

To verify the version number, enter the following command from the ‹BASEDIR›/smarts/bin directory:

```
sm_server --version
```

NOTICE

UNIX users: If the current directory is not set in your PATH variable, prefix the command with ./ (a period followed by a forward slash).

This command should return the following information:

- Operating system (OS) name on which the product is running and the OS version identifier.
- Version number of the product.
- Version number of the foundation (DMT) code, foundation build number, the date and time that the build was made as well as whether you have installed a 64-bit version of the software. If you installed the 64-bit version, you will see a “/64” after the foundation and the product version number.

The “sm_server --version” output is the following:

```
Operating System <Identifier>
<product>: V<Number>(<InternalBuild>), <Date>
Copyright 1995-2012, EMC Corporation - Build <Build>
Foundation V<Number>(<InternalBuild>), <Date>
Copyright 1995-2012, EMC - Build <Build>
```

For example, for IP Manager, the output might look similar to:

```
linux_rhAS50-x86-64/206320000
IP_NETWORK_SUITE: V9.4.2.0(152199), 13-Jul-2016 04:01:27 Copyright
   1995-2016, EMC Corporation - Build 29
Foundation V9.4.2.0(152138), 10-Jul-2016 15:01:00 Copyright 1995-2016,
   EMC Corporation - Build 8
```

The product version number is displayed during the Wizard mode installation on the InstallShield screen.

Be aware that product versions vary and do not always match the software foundation version number. For example, if you select the *About* from the *Help* menu in the Global Console, you may see a different number.

Obtain and install a temporary license file

To obtain a temporary (evaluation) license, complete a Support Request (SR) form, which you can find on the EMC support website http://support.emc.com.

Your EMC account team will send you a temporary (evaluation) ‹license_name›.lic file through email. Copy the license file to the BASEDIR/smarts/local/conf directory on the host system where you have installed the EMC Smarts software.

- If multiple products run on the same host, copy the license file to the BASEDIR/smarts/local/conf directory for each product.
- If a product runs on multiple hosts, copy the license file to the BASEDIR/smarts/local/conf directory on each host where the software is installed.

Edit the SM_LICENSE variable in runcmd_env.sh on each host where EMC Smarts software is installed to specify the full path and file name of a single license file. When multiple products are installed on the same host, each product will include a runcmd_env.sh in its BASEDIR/smarts/local/conf directory.

If the temporary license file has a different extension, do not rename it. Instead, ensure that the name that is entered for the SM_LICENSE variable matches that of the license file.

Temporary licenses are time-limited. At the end of the trial period, the software will no longer start. The trial license has an expiration date. The system generates two events alerting users about the expiration of the trial license: LicenseExpirationWarning and LicenseExpired. Table 15 on page 96 provides details on the events associated with the license expiration alert generation process.
For illustrative purposes, the following example is an excerpt of a smarts.lic file:

```
FEATURE DMC_CORR sm_lmgrd92 9.0 04-dec-2012 uncounted 123456789ABC \
HOSTID=DEMO SN=DO315530889 START=4-nov-2008
FEATURE AD_PEM sm_lmgrd92 9.0 04-dec-2012 uncounted 123456789ABC \
HOSTID=DEMO SN=DO315530889 START=4-nov-2012
FEATURE AP_ICSRV sm_lmgrd92 9.0 04-dec-2012 uncounted 123456789ABC \
HOSTID=DEMO SN=DO315530889 START=4-nov-2012
FEATURE DMC_DECS sm_lmgrd92 9.0 04-dec-2012 uncounted 123456789ABC \
HOSTID=DEMO SN=DO315530889 START=4-nov-2012
```

A temporary license file is not user-modifiable, and it consists of a list of applications or features; each line begins with the FEATURE keyword. Each FEATURE line includes the feature name, the vendor daemon name (sm_lmgrd92), the feature version, the expiration date, the number of concurrent licenses that is “uncounted” in this case, the authentication signature for the feature, the HOSTID=DEMO value that indicates that the feature is not bound to any particular host, the serial number (SN) to identify the FEATURE line, and a start date.

Events and attributes for license expired alert

Table 15 on page 96 and Table 16 on page 96 provides details on the event and attributes associated with the license expired alert generation process.

Table 15 Event for license expired alert generation

Event	Description	Subscribed to by the Global Manager
LicenseExpirationWarning	Indicates that the system license expiration has reached the remaining days threshold limit. This is defined as follows: (Number of license remaining days <= License expiration warning threshold). An event will be generated if the remaining days is less than the LicenseExpirationWarningThreshold value. The event will be cleared if: • The license expires • A permanent license is obtained *or* • The new trial license is valid for over 30 days	Yes - When the license expiration threshold is reached, a LicenseExpirationWarning notification is generated in the Service Assurance Manager server.
LicenseExpired	This event is generated when the number of days remaining for the expiration of a license reaches 0, that is, when the value for the NumberOfLicenseRemainingDays attribute reaches 0.	Yes - When the NumberOfLicenseRemainingDays value reaches 0, a notification is generated in the Service Assurance Manager server.

Table 16 Attributes for license expired alert generation

Attribute	Description	Default value
LicenseExpirationWarningThreshold	The number of days before license expiration for which the event will be generated. The default value is set to 30 days.	30
NumberOfLicenseRemainingDays	The number of days for which the license is effective. This is auto-calculated from expiration date and current date.	NA

The *EMC Smarts System Administration Guide* provides instructions for installing temporary and permanent licenses.

You will not be able to start new domain after a license expires. New devices can be added to the topology and discovery can be performed during the grace period, but new domains cannot be started using the same license. A fresh license is required to start new domain servers. You can extend the grace period on your license by a year. A special request asking for additional grace period on the AP_SYSTEM_VOLUME license feature has to be sent. Discovery and auto-discovery depends on this AP_SYSTEM_VOLUME license feature.

NOTICE

A new domain cannot be started even with this special license file. For example, if the license is expiring on 9/15/2011, and five domains are pointing towards the license server, then even after expiration, the five domains will continue to work till 9/15/2012. However, if we start a new domain server after 9/15/2011 and it is pointing towards the same license file, it will not work. You will need to a new license to start a new domain server. Also, if your temporary license expires and if you are within the grace period, you will not be able to either restart existing domain managers if they are stopped, or add any new device in the existing topology.

Start services

EMC Corporation recommends installing EMC Smarts products as services. If you installed the products as services, you must start them for the first time. These services start automatically upon system reboot.

NOTICE

Start the Broker service first if it is not running.

Starting services on UNIX

Verify the status of the service daemon before starting a service.

Verifying the status of the service daemon

Use the ic-serviced command to check the status of the service daemon. The path to the ic-serviced command varies by operating system.

CentOS

On CentOS systems, enter the following command to verify the status of the service daemon:

```
/etc/init.d/ic-serviced status
```

If the sm_serviced process does not respond, the process is not running. Start the service by entering the command:

```
/etc/init.d/ic-serviced start
```

Linux

On Linux systems, enter the following command to verify the status of the service daemon:

```
/etc/init.d/ic-serviced status
```

If the sm_serviced process does not respond, the process is not running. Start the service by entering the command:

```
/etc/init.d/ic-serviced start
```

Starting services

To start or stop an EMC Smarts service, use the sm_service utility. Type the command from the BASEDIR/smarts/bin directory:

```
sm_service start <service_name> [<service_name> ...]
```

where *‹service_name›* is each service you need to start. Table 17 on page 99 provides a list of service names.

Starting services on Windows

To start an EMC Smarts service from the Windows desktop:

1. Select **Start › Settings › Control Panel › Administrative Tools.**
2. Select **Services.**

3. Right-click the EMC Smarts service.
4. Select **Start**.

Start programs

You can start EMC Smarts programs from the terminal when the program is not intended to be long-running or to perform testing. EMC Corporation does not recommend using this method in a production environment.

The *EMC Smarts System Administration Guide* provides a complete description of the command syntax.

To start a program, type the command with the appropriate options on one line.

- For UNIX, invoke the command from the BASEDIR/smarts/bin directory. Prefix the command with ./ (a period followed by a forward slash).
- For Windows, invoke the command from the C:\BASEDIR\smarts\bin directory.

Starting the EMC Smarts Broker

```
./brstart --port=426 --output
```

Starting a Manager

```
▼ ./sm_server --name=<server_name>
      --config=<config_directory>
      --port=0
      --ignore-restore-errors
      --output ▲
```

NOTICE

▼▲ indicates the command must be typed on one line.

For UNIX, to run the program in the background, use the daemon option.

NOTICE

Service Assurance Manager Console crashes when running commands on a Linux platform since the FIPS library fails to load. SELinux prevents the shared libraries, libcryptocme2.so and libccme_base.so from loading because of the existence of text relocation in the library.

The following workarounds are available to avoid the SAM Console crash:

1. Run the following commands to change the file context for the shared libraries, libcryptocme2.so and libccme_base.so to **textrel_shlib_t**:

   ```
   chcon -t textrel_shlib_t libcryptocme2.so
   chcon -t textrel_shlib_t libccme_base.so
   ```

2. Set the parameter **setenforce** to 0 to run SELinux in permissive mode.
3. Navigate to Edit */etc/selinux/config* and set the parameter **SELINUX** to **Disabled**.

Service and program startup options

Table 17 on page 99 lists service names, server names, and configuration directories for EMC Smarts products.

Table 17 Default service names, server names, and configuration directories (page 1 of 2)

Product	Service name	Server name	Config directory
Broker	ic-broker	Not applicable	Not applicable
IP Manager			
IP Availability Manager	ic-am-server	INCHARGE-AM	icf
IP Performance Manager	ic-pm-server	INCHARGE-PM	icf
IP Availability and Performance Manager	ic-am-pm-server	INCHARGE-AM-PM	icf
Service Assurance Manager			
Service Assurance Manager Server	ic-sam-server	INCHARGE-SA	ics
Service Assurance Manager Adapter Platform Server	ic-icoi-server	INCHARGE-OI	icoi
SNMP Trap Adapter	ic-trapd-receiver	TRAP-INCHARGE-OI	icoi
Syslog Adapter	ic-syslog-adapter	SYSLOG-INCHARGE-OI	Not applicable
Business Impact Manager	MBIM	INCHARGE-MBIM	bim
MPLS Manager			
MPLS Analysis Server	ic-mpls-analysis	INCHARGE-MPLS-ANALYSIS	mpls-a
MPLS Monitoring Server	ic-mpls-monitoring	INCHARGE-MPLS-MONITORING	mpls-m
MPLS Topology Server	ic-mpls-topology	INCHARGE-MPLS-TOPOLOGY	mpls-t
MPLS VPN-Tagging Server	ic-vpn-tagging	VPN-TAGGING	vpn-tagging
Server Manager			
Server Manager	ic-esm-server	INCHARGE-ESM	esm
Network Protocol Manager products			
Network Protocol Manager for BGP	ic-npm-bgp-server	INCHARGE-BGP	conf/bgp
Network Protocol Manager for EIGRP	ic-npm-eigrp-server	INCHARGE-EIGRP	conf/eigrp
Network Protocol Manager for IS-IS	ic-npm-isis-server	INCHARGE-ISIS	conf/isis
Network Protocol Manager for OSPF	ic-npm-ospf-server	INCHARGE-OSPF	conf/ospf
Optical Transport Manager			
Optical Transport Manager for Next Generation WDM	ic-wdm-ng-server	OTM-WDM-NG	wdm-ng
Optical Transport Manager for SDH (Topology)	ic-sdh-topology-server	OTM-SDH-TOPOLOGY	osm-t
Optical Transport Manager for SDH (Analysis)	ic-sdh-analysis-server	OTM-SDH-ANALYSIS	osm-a

Table 17 Default service names, server names, and configuration directories (page 2 of 2)

Product	Service name	Server name	Config directory
Optical Transport Manager for PDH (Topology)	ic-pdh-topology-server	OTM-PDH-TOPOLOGY	pdh-t
Optical Transport Manager for PDH (Analysis)	ic-pdh-analysis-server	OTM-PDH-ANALYSIS	pdh-a
Optical Transport Manager for WDM (Topology)	ic-wdm-topology-server	OTM-WDM-TOPOLOGY	wdm-t
Optical Transport Manager for WDM (Analysis)	ic-wdm-analysis-server	OTM-WDM-ANALYSIS	wdm-a
Optical Transport Manager for IP Cross Domain Analysis	ic-xd-otm-ip-server	OTM-WDM-TOPOLOGY	icxd-ao
TMF814 Cisco CTM Adapter for OTM	ic-tmf814-cisco-ctm-adapter	OTM-CISCO-ADAPTER	tmf814Cisco
TMF814 Ciena On-Center Adapter for OTM	ic-tmf814-ciena-onctr-adapter	OTM-CIENA-ADAPTER	tmf814Ciena
VoIP Availability Manager			
VoIP Availability Manager	ic-voip-server	VoIP-AM	conf/voip
VoIP Notification Trap Adapter	ic-voip-notification-trapd-receiver	TRAP-INCHARGE-VOIP	conf/voip

- Appendix B, "Manually Installing Services," provides the default service and program parameters that are used for the service install commands.
- The *EMC Smarts System Administration Guide* provides information in regard to the sm_server, sm_adapter, and sm_trapd programs.

Start Smarts NOTIF

To start Smarts NOTIF:

1. Set an environment variable in the **BASEDIR** directory path to ensure that Java can be successfully started for Smarts NOTIF. In **BASEDIR**/smarts/local/conf/**runcmd_env.sh**, add the following line:

   ```
   SM_JAVA_ENABLED=YES
   ```

2. Configure the SNMP Trap Adapter to use the Notif-trap_mgr_parse.asl script instead of the default trap_mgr_parse.asl script so that Smarts NOTIF processes SNMP traps. For example:

   ```
   ./sm_service install --force --unmanaged --startmode=runonce \
   '--name=ic-notif-trap' \
   '--description=Notif Trap Receiver' \
   '/opt/InCharge/SAM/smarts/bin/sm_trapd' \
   '--name=NOTIF-TRAP' \
   '--server=INCHARGE-OI' \
   '--output' \
   '--config=icoi' \
   '--port=1162' \
   '--model=sm_actions' \
   '--rules=icoi-trapd/Notif-trap_mgr_parse.asl'
   ```

NOTICE

The *--daemon* option only works on UNIX systems, not Microsoft Windows systems. Any customizations made by the customer to the original trap_mgr_parse.asl file in the BASEDIR/smarts/rules/icoi-trapd directory must be incorporated into the Notif-trap_mgr_parse.asl file in the BASEDIR/smarts/rules/icoi-trapd directory.

3. Configure the Syslog Adapter to use the Notif-SysLog_mgr.asl script instead of the default SysLog_mgr.asl script in order for Smarts NOTIF to process Cisco system log files.

   For example:

```
./sm_service install --force --unmanaged --startmode=runonce \
'--name=ic-notif-syslog' \
'--description=Notif Syslog Adapter' \
'/opt/InCharge/SAM/smarts/bin/sm_adapter' \
'--name=NOTIF-SYSLOG' \
'--server=INCHARGE-OI' \
'--output' \
'--config=icoi' \
'--port=1162' \
'--model=sm_actions' \
'--model=sm_system'\
'--rules=icoi-syslog/Notif-SysLog_mgr.asl'\
'--tail=/opt/InCharge/SAM/smarts/local/logs/sample.txt'
```

   NOTICE

   One or more adapters can feed a single Smarts NOTIF server.

4. Launch the Smarts NOTIF Editor by selecting **Start** › **Programs** › **InCharge** › **Smarts NOTIF Editor**.

   NOTICE

   You can also launch the editor by double-clicking the **NotifGui.bat** file (for Windows systems) or the **NotifGui.sh** file (for UNIX systems) in the BASEDIR/smarts/notif/editor directory.

5. Use the Smarts NOTIF Editor to connect to the running SAM server or Adapter Platform server. Select **Remote** › **Edit a server's settings** in the Smarts NOTIF Editor. The **Connect to a Server** dialog box appears, showing the list of available Adapter Platform and SAM server connections.

6. Choose a server from the list of available server connections in the **Connect to a Server** dialog box and click **OK**.

   If server connections are not displayed, perform the following to populate the list of server connections:

   a. Click **More** in the **Connect to a Server** dialog box. The **Manage Connections** dialog box appears where you can add server connections.

   b. Click **Add** in the **Manage Connections** dialog box. The **Input** dialog box appears.

   c. Enter a connection reference name (for example, “Remote Smarts NOTIF OI server”) in the **Input** dialog box and click **OK**.

d. Fill in the new connection record in the right pane of the **Manage Connections** dialog box.

e. Click **OK** to save the connection setup.

The **Remote Server Settings** dialog box appears that shows the server's current settings.

7. Select the **Activate Smarts NOTIF** checkbox, and then click **OK**.

NOTICE

You can also change other server settings in the **Remote Server Settings** dialog box if necessary.

8. Restart your SAM server or Adapter Platform server.

NOTICE

Server setting changes made in the Smarts NOTIF Editor **Remote Server Settings** dialog box are persistent. When you change server settings in the **Remote Server Settings** dialog box and click **OK**, the changes are saved to the **Notif_Settings.import** file that is generated and saved to the **BASEDIR**/smarts/local/conf/‹*icoi* or *ics*› directory in the Adapter Platform or SAM server where Smarts NOTIF is running. Server setting changes made in the Smarts NOTIF Editor are preserved even if the repository is deleted. For example, if the repository is erased because you used the **--norestore** option for server startup, the server uses the last saved settings from the Smarts NOTIF Editor saved in **BASEDIR**/smarts/local/conf/‹*icoi* or *ics*›/**Notif_Settings.import**.

NOTICE

The *EMC Smarts Notification Module User Guide* includes information on how to use the Smarts NOTIF Editor.

Verify the product status

You can determine the current state of the products that register with the Broker by typing the following command from the BASEDIR/smarts/bin directory:

```
./brcontrol
```

This command displays a list of EMC Smarts Managers and adapters that are registered with the Broker, their states (RUNNING, DEAD, UNKNOWN), process IDs, port numbers, and the last time that their states changed.

Also check any log files for the products. Typically, these log files are in BASEDIR/smarts/local/logs.

NOTICE

More than one log file may be generated due to changes in the foundation code that supports internationalization. The *EMC Smarts System Administration Guide* provides additional information on log files.

If only one log file per server is desired, use sm_edit to update the BASEDIR/smarts/local/conf/runcmd_env.sh file. To get a single log file, set the following environment variables:

```
export SM_LOCALE=en_US (or appropriate locale code)
export SM_ENCODING_OUTPUT=UTF-8
```

Verify the FIPS 140 mode status

To verify if the installation is running in FIPS-140 mode, run the following command in the dmctl mode:

```
get SM_System::SM-System::FIPS
```

The value for this parameter must be TRUE.

You can also check for the status of FIPS 140 in the log files in the BASEDIR/smarts/local/logs directory. When the Broker and server start in FIPS 140 mode, a message similar to the following one is written to the Broker and server log files:

```
RSA BSAFE: MES 3.2.4 26-May-2012/64(0), FIPS: RSA BSAFE Crypto-C Micro
   Edition FIPS 140-2 Module 3.0.0.0/64(0), May 31 2008 13:19:56
```

Common issues

Domain registers with the broker, but appears DEAD after a few minutes

The domain is in FIPS 140 mode but the broker is not.

Domain is not able to register with the broker

The Broker is in FIPS 140 mode but the domain is not.

Broker or Domain log entry

```
CI-N-EWHILE-While executing function "queue_work”CI-EFLOWID-For flow
   CI_FlowTCP_U [Flow in negotiations Accepted physical flow] PHYSICAL
   @0x0000000000a38db  . *:v4:44445 KS N/A, KR N/A  . Open fd=10, conn
   August 17, 2011 3:27:43 PM EDT, disc N/A,  . 127.0.0.1:44445 ->
   127.0.0.1:58347, tmo 0 00:00:15 N/S 1/0 CI-EWHILE-While executing
   function ""CI_FlowTLS_U::handshake”” 
   CI-BSAFE-error:1407609C:SSLroutines:SSL23_GET_CLIENT_HELLO:http
   request: ; in file "s23_srvr.c" at line 746
```

The entry might also appear as: *SSL routines:SSL23_GET_CLIENT_HELLO:unknown protocol*.

This may be because the Domain (or Broker) is in FIPS 140 mode but the client is not. It may also be that the client is a non-Smarts client (for example a load balancer’s HTTP check). In that case, switch the load balancer to HTTPS check.

Client error

```
CI-E-EWHILE-While executing function
   ""CI_FlowTLS_U::handshake”” CI-BSAFE-error:1408F10B:SSL
   routines:SSL3_GET_RECORD:wrong version number: ; in file "s3_pkt.c"
   at line 553CI-TLSPE-TLS protocol error
```

This may be because the Domain or Broker is not FIPS 140 capable but the client is operating in FIPS 140 mode.

Log errors

```
[July 11, 2011 5:09:41 PM EDT +385ms] t@31 PollingQueue
   #8CI-E-EDECRYPT-Cannot decrypt.CI-EDECRYPT-Cannot decrypt.[July 11,
   2011 5:09:41 PM EDT +386ms] t@31 PollingQueue
   #8IA-E-ERROR_EXECUTING_ACTION-Error executing action
   MA-PerlScript-sihou513a.CI-EDECRYPT-Cannot decrypt.
```

This may be because the Imk.dat version or the password does not match between domains. Ensure that the password and the version matches across all installs that inter operate.

Error on startup of domain or other tools

```
[August 8, 2011 8:29:07 PM EDT +466ms] t@3916876800 <Primary
   Thread>CI-F-EBLACKSTRING_CONTEXT-While creating the
   contextCRPT-CRYPTO_MD5_INIT_FAILED-Failed to initialize the context
   for MD5 algorithm
```

This may be because you are trying to use a v1 imk.dat file in FIPS 140 mode. Ensure that you use v2.1 for FIPS 140 compatibility.

Collect system information

The sm_getinfo utility is used to collect data for troubleshooting EMC Smarts Manager (server) problems. The utility backs up the current configuration for a server by creating a tar archive of all files and user customizations that are essential to troubleshooting the server. Customers then email the tar archive to EMC Customer Support for problem resolution.

sm_getinfo files

The sm_getinfo utility, which is supported on CentOS, Linux, and Windows, creates four types of files in the installation directory area from which it is invoked. The files are shown described in Table 18 on page 104.

Table 18 Files created by the sm_getinfo utility (page 1 of 2)

Filename	Description
Files in BASEDIR/smarts/local/logs directory	
sm_getinfo‹date›.tar.gz Example: sm_getinfo26Mar2012-015952.tar.gz	A compressed tar archive in which the sm_getinfo utility stores a server ‘s log files, repository files, core files (CentOS, Linux) or dump files (Windows), user-modified files (using sm_edit), user-introduced files, and system environment information. The actual content of the tar archive depends on the user-specified options on the sm_getinfo invocation command line. The name of the tar archive includes the date when the tar archive was created.
MANIFEST	A text file that lists all of the files that the sm_getinfo utility includes in the tar archive.
Files in BASEDIR/smarts/local/logs/smgetinfo_files directory	

Table 18 Files created by the sm_getinfo utility (page 2 of 2)

Filename	Description
smgetinfo-versions.log.‹date› Example: smgetinfo-versions.log.26Mar2012-020004 Example of other files in smgetinfo_files: TTP-Installed-versions.log.26Mar2012-020005	A log file in which the sm_getinfo utility writes information about a server's log file or repository file that is larger than 700 megabytes (MB). The sm_getinfo utility does not include any log or repository file in a server's tar archive that exceeds 700 MB. In addition, sm_getinfo writes system information to the log file. The name of the log file includes the date when the log file was created.
Final_sm_getinfo‹timestamp›.tar Example: Final_sm_getinfo20Sep2012-005855.tar	The -k or --smconfigscan command invokes the Configuration Scanner tool, and generates the Final_getinfo-‹timestamp›.tar, along with other Configuration Scanner tool-related files. **Notice:** If the sm_getinfo utility is run without the -k or --smconfigscan command, a getinfo-‹timestamp›.tar output file will be generated without Final_ appended to the output. This implies that you will be running the sm_getinfo tool as usual.

sm_getinfo command-line syntax

You run the sm_getinfo utility from the BASEDIR/smarts/bin directory. The options that you specify on the invocation command line determine which files are included in the sm_getinfo-created tar archive.

Here is the command line syntax for sm_getinfo:

```
sm_perl sm_getinfo.pl
| --server <server name> --pid <server process ID>
| --broker <location>
| --log [<number of latest logs>]
| --nolog
| --repos [--latest]
| --norps
| --core
| --all
| --version
| --help
| --smmonitor "<sm_monitor options>"
| --flush
| --smconfigscan
```

where:

- ‹› Angle brackets are user-supplied parameter values (variables).
- [ ] Square brackets are optional entries.
- | Vertical bar symbols are alternate selections.

The command-line options are described in Table 19 on page 106.

Table 19 Command-line options for the sm_getinfo utility (page 1 of 2)

Option	Description
--server ‹server name› --pid ‹server process ID› | -s ‹server name› -p ‹server process ID›	Specifies the EMC Smarts server name and PID against which the sm_getinfo utility will collect information. To dump a core file for a running server on CentOS or Linux, the pid option must be provided. Also, the server name is used to invoke the sm_monitor tool.
--broker ‹location› | -b ‹location›	Specifies an alternate broker location as host:port.
--pid ‹pid› | -p ‹pid›	PID of Domain Manager used to run gcore.Not applicable on Windows.
--log [‹number of latest logs›] | -l [‹number of latest logs›]	For each EMC Smarts server, collects and stores a user-specified number of latest logs or all generated log files that are in the BASEDIR/smarts/local/logs directory. Note that whenever collecting a log, the related .audit and .archive files should be collected as well. If a server name is specified, only the files that correspond to the server will be collected. To avoid generating a too-large tar archive (too large to email), any log file that is larger than 700 MB will be excluded and its information will be logged in smgetinfo-versions.log‹date›.
--nolog | -g	Excludes log files when collecting local files. This option and --log are mutually exclusive.
--repos [--latest] | -r [-t]	For each EMC Smarts server, collects and stores the latest repository file or all repository files. If a server name is specified, only the file corresponding to the server will be collected. Any repository file that is larger than 700 MB will be excluded and its information will be logged in smgetinfo-versions.log‹date›.
--norps | -n	Excludes repository files when collecting local files. This option and --repos are mutually exclusive.
--core | -c	Collects and stores the core files (CentOS, Linux) or dump files (Windows) that are generated by the EMC Smarts software, and the corresponding logs.
--all | -a	All data and files in BASEDIR/smarts/local and BASEDIR/smarts/setup directories will be collected and stored. If --all option is specified, the other options will be ignored except --server and --pid.
--version | -v	Print version information and exit.
--help | -h	Print usage information and exit.
--smmonitor “‹sm_monitor options›” | -m “‹sm_monitor options›”	Specifies the options for running sm_monitor, which will override the default options “-m run-all -z.” Approximately two cycles are run to collect the required information. The collected information is output to the BASEDIR/smarts/local/logs/SM-Monitor-‹server name› directory.

Table 19 Command-line options for the sm_getinfo utility (page 2 of 2)

Option	Description
--flush | -f	Force a flush. Needed when the sm_getinfo utility is invoked from a remote host.
--smconfigscan | -k **Notice:** This option is available for IP Manager only.	Invokes the configuration scanner tool to provide a snapshot of all the customizations introduced by you in your current installation. "Configuration Scanner Tool" on page 108 provides more information on how to use the tool.

sm_getinfo invocation examples

To gather the five latest logs, enter:

```
sm_perl sm_getinfo.pl  --logs 5
```

To gather the latest repository data and core files, enter:

```
sm_perl sm_getinfo.pl  --repos --latest --core
```

To gather the entire BASEDIR/smarts/local directory, enter:

```
sm_perl sm_getinfo.pl  --all
```

To invoke sm_monitor, enter:

On Linux:

```
sm_perl sm_getinfo.pl -s <server name> -m "-m correlation -z"
```

On Windows:

```
sm_perl sm_getinfo.pl -s <server name>  -m "-m mem"
```

sm_getinfo data collection

If no command-line option is specified, the sm_getinfo utility will store the following information in the tar archive:

- For each server, the latest server log file in BASEDIR/smarts/local/logs and the related .audit and .archive files in BASEDIR/smarts/local/logs. If a server name is specified, only the files that correspond to the server will be collected. To avoid generating a too-large tar archive (too large to email), any log file that is larger than 700 MB will be excluded and its information will be logged in smgetinfo-versions.log‹date›.
- For each server, the latest repository file in BASEDIR/smarts/local/repos. If a server name is specified, only the repository file for the server will be archived. Any repository file that is larger than 700 MB will be excluded and its information will be logged in smgetinfo-versions.log‹date›.
- The local files that are not in the BASEDIR/smarts/local/logs and repos directories and changed since last temporary test patch (TTP) and patch.
- The new local files that are not in the BASEDIR/smarts/local/logs and repos directories and were added since the last TTP and patch.

- All local files except the files in logs and repos directories if no TTP or patch is installed.
- All files in the BASEDIR/smarts/setup/info and BASEDIR/smarts/setup/logs directories.
- Core files (UNIX) or dump files (Windows) that are generated by the EMC Smarts software, and the corresponding server log files. On Linux, some library (lib) files that are related to the cores are also collected.
- EMC Smarts TTP or patch version information. Additionally, it verifies MD5 checksum for the installed TTP files and the files that are listed in manifest.md5 in the BASEDIR/smarts/setup/info directory.
- The data collected by sm_monitor. If a server name is specified, only the files that correspond to the server will be collected.
- The data generated by the EMC Smarts Health Monitor (SHM).
- System environment information.

Configuration Scanner Tool

NOTICE

This tool is available only for IP Manager.

The Configuration Scanner tool scans for configuration changes in your current installation. It scans for customizations with regard to the following:

- **Polling and threshold settings:** The tool presents the non-default values and settings. That is, the tool generates a list of polling settings and threshold parameters that have changed from their default values, along with details of all the groups they are associated with. The output also includes tagging settings. In case of CLI settings, the tool collects and displays the username and the associated matching criteria.
- **Configuration files:** The tool generates a list of files that have changed from the default installation. The tool scans the files in the SM_SITEMOD and base installation and does a two-way difference analysis to figure out what files have changed, and displays the list of files, flagged appropriately as modified or added. For discovery.conf, name-resolver.conf and tpmgr-param.conf files, the tool parses through the content and presents the difference at an attribute->value pair level.

  NOTICE

  The clientConnect.conf, serverConnect.conf, brokerConnect.conf, .imk.dat files and the l10n classes and Perl directories are excluded from the scan.

NOTICE

The tool ignores service pack and patch files that are not modified by you.

Running the Configuration Scanner tool from the sm_getinfo utility

To run the Configuration Scanner tool:

1. Go to the ‹**BASEDIR**›/smarts/bin folder.

   In this document, the term **BASEDIR** represents the location where EMC Smarts software is installed. For example:

   For UNIX, this location is: /opt/InCharge/‹*product*›.

   For Windows, this location is: C:\InCharge\‹*product*›.

   On UNIX operating systems, IP Availability Manager is, by default, installed to: /opt/InCharge/IP/smarts. On Windows operating systems, this product is, by default, installed to: C:\InCharge\IP\smarts. This location is referred to as **BASEDIR**\smarts. Optionally, you can specify the root of **BASEDIR** to be something different, but you cannot change the ‹*product*› location under the root directory.

2. Type the following command:

   ```
   sm_perl sm_getinfo <options> -k (or --smconfigscan)
   ```

   An example for the command is provided below:

   ```
   sm_perl sm_getinfo --broker=localhost:5086 --server=INCHARGE-AM
   --smconfigscan
   ```

   or

   ```
   sm_perl sm_getinfo -b localhost:5086 -s pserver --smconfigscan
   ```

   The tool has four command-line options: --broker and --server. You can use these options in various combinations and in any order. The details of the options are provided below:

- --broker= ‹location› or -b ‹location› is the name of the broker if you are using a broker other than your default broker. For example: localhost:400.

  NOTICE

  It is optional to specify a broker. If a broker is not specified, the tool picks up the broker in the runcmd_env.sh file as the default.

- --server=‹name› or -s ‹name› is the name of the Smarts server.
  For example: --server=INCHARGE-AM.

  NOTICE

  It is optional to specify a server. If a server is not specified, the tool skips the scan for polling and threshold settings, and does only a configuration file scan. However, if the server is running from a location other than the current working directory, the tool scans for polling and threshold settings, but skips the check for file differences and proceeds with packaging the output.

  Once you run the command, the tool carries out the following steps:

  - Connects to the IP server and scans for changes to the polling and threshold setting values, and writes the findings to an output file.

NOTICE

When prompted for domain login credentials, type the username and password for connecting to the domain.

- Maintains lists of files it has determined as modified or introduced by you and lists of files that were changed by TTPs, if any.
- For some special files, that is, discovery.conf, tpmgr-param.conf and name-resolver.conf), the tool invokes an adapter to parse the contents of the modified and base version of these files. It presents a detailed account of the changes you have made at an attribute-›value pair level in the sm_configscan_report-‹time_stamp›.txt report file.

NOTICE

As the tool starts the adapter and accesses your running server to gather information, you will be prompted for login credentials. Type the credentials you provided earlier for connecting to the domain.

- Creates a sm_configscan.‹time_stamp›.tar file at ‹BASEDIR›/smarts/local/logs/sm_getinfo-‹time_stamp›.tar, which contains the .configscan.‹version_number› directory, report file and the logs.
- Cleans up your environment by removing any directories and files it had created, except for the tar file and the report file. It closes any servers or brokers it had started.

CHAPTER 8
Performing an Uninstallation

This chapter describes how to uninstall the EMC Smarts Service Assurance Manager, EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, EMC Smarts Optical Transport Manager, and EMC Smarts VoIP Availability Manager. It consists of the following topics:

- Before uninstallation 112
- Uninstall EMC Smarts products 117

Before uninstallation

You should complete the following tasks before uninstalling the product:

- "Remove manually installed services" on page 112
- "Determine order for removing products (UNIX only)" on page 112
- "Uninstall when same product software is installed twice (Windows only)" on page 113
- "Detect and stop programs" on page 113
- "Uninstall the FlexNet License Server" on page 116

Remove manually installed services

Services that you manually installed with sm_service command are not removed by the uninstallation program. You must remove these services manually before uninstalling the product software.

To remove a service, invoke sm_service from the BASEDIR/smarts/bin directory:

1. Use sm_service to list installed services.

   ```
   sm_service show
   ```

2. Remove the manually installed service.

   ```
   sm_service remove ic-<service name>
   ```

   where ‹service name› is the name of the service. For example, ic-am-server or ic-sam-server.

Determine order for removing products (UNIX only)

When uninstalling EMC Smarts products from the same server, the product that was installed first must be uninstalled last. During the installation of the first product, the EMC Smarts Service Database is created and the other products subsequently access it. Uninstalling the product installed first will also uninstall the Service Database that will disable the sm_service command for those products, prevent their proper operation and uninstallation.

You can determine what product software was installed first by performing this check:

1. Use a text editor to open the **ic-serviced** script.
   - For CentOS, **ic-serviced** is located in the /etc/init.d directory
   - For Linux, **ic-serviced** is located in the /etc/init.d directory
2. Find the value of the SMHOME variable.

   The value of SMHOME indicates which product was installed first.

Uninstall when same product software is installed twice (Windows only)

If you installed the same product to different locations on the same host system, do not use Add/Remove Programs to uninstall. Uninstall the EMC Smarts product as follows:

1. Open a command-line prompt, go to the BASEDIR_uninst directory of the target EMC Smarts product, and enter the following command to initiate a Wizard mode uninstallation:

   uninstaller.exe

2. Complete the uninstallation beginning with step 2 as described in "Uninstall using Wizard mode" on page 117.

Detect and stop programs

Before upgrading or uninstalling your product, you must stop all EMC Smarts services, EMC Smarts scheduled jobs, and any other process that uses programs or libraries running from the EMC Smarts product.

Detecting programs

The sm_plist utility identifies all EMC Smarts programs that are running for any product on your machine. You can use the sm_plist utility whenever you need to identify EMC Smarts programs that are running (for example, before applying a service pack or patch and uninstalling the product software).

To use the utility, invoke it from the BASEDIR/smarts/script directory. The utility displays active programs in a window:

1. Go to the BASEDIR/smarts/script directory.
2. Start the sm_plist utility:

   On UNIX, enter

   ./sm_plist.sh *<BASEDIR2>*

   On Windows, enter

   cscript sm_plist.vbs *<BASEDIR2>*

   where BASEDIR is the directory where the sm_plist utility is installed and BASEDIR2 represents the location of any EMC Smarts product.

Stopping active programs (UNIX)

To stop active EMC Smarts programs (UNIX):

1. Stop active EMC Smarts services using the sm_service utility from BASEDIR/smarts/bin:

   ./sm_service stop --all

   NOTICE

   sm_serviced waits 30 minutes after sending a shutdown request to a process. If the process is still running after 30 minutes, sm_serviced terminates it.

2. Determine if any EMC Smarts services are still running by using the brcontrol utility from BASEDIR/smarts/bin:

   ```
   ./brcontrol -b <host>:<port>
   ```

   Based on the location of the Broker, go to the appropriate step, as indicated in Table 20 on page 114.

Table 20 Next steps for detecting and stopping programs

The Broker is on the . . .	And this displays . . .	Do this . . .
Same host	"Error attaching to Broker" message	The Broker is not running. Go to step 4 .
	List of servers registered with the Broker	• The Broker or service daemon did not shut down. • If any servers are still running on the host, these did not shut down. Go to step 3 .
Different host	List of servers registered with the Broker	• If any servers are still running on the host where you will install the EMC Smarts software, these did not shut down. Go to step 3 .

3. Stop any EMC Smarts server that is still running. If the Broker is on the host, stop the local Broker:

   - To stop any server that is still running, use the dmquit utility from BASEDIR/smarts/bin:

     ```
     ./dmquit --server=<server name> -b <host>:<port>
     ```

   - To stop the local Broker from BASEDIR/smarts/bin:

     ```
     ./brquit --broker=localhost:<port>
     ```

4. Determine if any other EMC Smarts processes are still running and shut the processes down:

   - Detect the processes using the following command:

     ```
     ps -ef | grep "sm_"
     ```

     If a list is displayed, note the process ID (pid) of these active EMC Smarts processes.

     NOTICE

     Do not stop or kill the service daemon process, sm_serviced.

   - Shut down these EMC Smarts processes (except sm_serviced) using the following command:

     ```
     kill <pid>
     ```

Stopping active programs (Windows)

To stop a service from the Windows desktop, use the Microsoft Management Console:

1. Select **Settings** › **Control Panel**.
2. At the **Control Panel**, select **Administrative Tools**.
3. At the **Administrative Tools** folder, select **Services**.
4. At the **Services** window, locate any running EMC Smarts services. These services start with the words "EMC Smarts," "Smarts," or "InCharge." For each of these services, right-click the service and then select **Stop**.

   NOTICE

   Do not stop the Broker service.

5. Repeat step 4 until all EMC Smarts services are stopped.
6. Open a command prompt and determine if any Managers are running by using the brcontrol utility from BASEDIR\smarts\bin:

   ```
   brcontrol -b <host>:<port>
   ```

7. Stop any EMC Smarts server that is still running using the dmquit utility from BASEDIR/smarts/bin:

   ```
   ./dmquit --server=<server name> -b <host>:<port>
   ```

8. If the Broker is installed on the same host, use the brquit utility from BASEDIR/smarts/bin to stop it:

   ```
   brquit --broker=localhost:<port>
   ```

9. Press **Ctrl+Alt+Delete**. The **Windows Security** dialog box appears.
10. Click **Task Manager**. The **Windows Task Manager** appears.
11. Select the **Processes** tab.

    NOTICE

    Allow up to 30 minutes before performing the next step. EMC Smarts servers with large topologies can take considerable time to stop while saving the topology to the repository. Stopping processes prematurely may corrupt your repository file.

12. In the **Processes** tab, look in the column labeled **Image Name** for sm_server. Right-click each sm_server, and then select **End Process**.
13. In the **Processes** tab, look for other Image Names that start with sm_, for example, sm_notify, sm_adapter, sm_beacon, and so on. Right-click each instance, and then select **End Process**.

    NOTICE

    Do not shut down any sm_authority or sm_logger processes. The sm_authority and sm_logger processes are child processes of an EMC Smarts server. The child processes will stop when the parent process stops.

Uninstall the FlexNet License Server

When uninstalling all of your EMC Smarts products that use a specific FlexNet License Server, you must also uninstall the FlexNet License Server.

NOTICE

If any EMC Smarts products will remain in your network and use the FlexNet License Server, do not uninstall either the license server or the EMC Smarts product where the permanent license file resides.

If you uninstall EMC Smarts products without uninstalling the FlexNet License Server, a message displays that the FlexNet (lmgrd) service is still running. Remember that an EMC Smarts application will not start if it is unable to contact the license server.

To stop and uninstall the FlexNet License Server:

1. Stop the FlexNet License Server.

   CentOS

   ```
   /etc/init.d/SMARTS-License stop
   ```

   Linux

   ```
   /etc/init.d/SMARTS-License stop
   ```

   Windows

   To manually stop the license server on Windows, do the following:

   - Select **Start** › **Settings** › **Control Panel** › **Administrative Tools**.
   - Select **Services**.
   - Select the FlexNet License Server service.
   - Right-click and select **Stop**.

2. Run the install_license script, with the **uninstall** command, from BASEDIR/smarts/script.

   On UNIX, enter:

   ```
   install_license.sh uninstall
   ```

   On Windows, enter:

   ```
   install_license.cmd uninstall
   ```

Uninstall EMC Smarts products

EMC Smarts product software uses the InstallShield program to install and uninstall products. For UNIX, you invoke the uninstallation program from the system prompt. For Windows, you use the Add/Remove Programs, except when the same product is installed in multiple locations on the same host system. Failure to use the appropriate method will result in an unstable system and/or inconsistent product directories.

NOTICE

Do not manually delete the installed product directories.

NOTICE

Also, if you plan to reinstall the product, save all of the customized files that are in the BASEDIR/smarts/local directory before performing the uninstallation. *The uninstallation program will remove all of the files and directories in the BASEDIR/smarts directory, and then remove the smarts directory.*

Uninstall using Wizard mode

Wizard mode provides a graphical user interface to the uninstallation program for UNIX and Windows platforms.

On UNIX systems, Wizard mode uses the X Window System to display the installation wizard. The host on which you install the EMC Smarts software and the host where you log in must be configured to run the X Window System. Before starting the installation program, verify that the X Window System is running.

1. Invoke the uninstaller program:
   - On UNIX, go to the BASEDIR/_uninst directory and enter:

     ```
     uninstaller.bin
     ```

   - On Windows, use Windows Control Panel:
     a. Click **Start** › **Settings** › **Control Panel**.
     b. Double-click **Programs and Features**.
     c. From the **Program and Features** window, select the appropriate product.
     d. Click **Uninstall/Remove.**
2. Click **Next** in the **Welcome** screen to continue.
3. In the **Product Selection** screen, click **Next** to uninstall the entire product (by default, all products are selected) or deselect products that should remain installed.
4. Review the list of products that will be uninstalled and the target installation directory. Once you click **Next**, you cannot cancel the uninstallation process.

   If necessary, click **Back** to return to the **Product Selection** screen to revise your selections.

   To uninstall the products, click **Next**; the **Uninstallation Progress** screen appears.

5. Upon completion, the **Uninstallation Summary** shows informational messages such as successful confirmations, error messages, and warnings. Investigate any errors or warnings.

   If **Next** appears, your system needs to be rebooted. Click **Next** and then reboot your system. Otherwise, click **Finish** to exit the uninstallation.

   The uninstallation program will remove all of the files and directories in the BASEDIR/smarts directory, and then remove the smarts directory.

   The uninstallation program will also write an uninstall log file to the BASEDIR directory, unless the uninstallation fails at the very start, in which case the installation program will write the log file to the /tmp directory. The log file is a text file with the naming convention Uninstall.‹product›.‹productversionNumber›.log.

Uninstall using CLI mode

To uninstall an EMC Smarts product or product:

1. Go to the BASEDIR/_uninst directory and enter the following command:

   ```
   uninstaller.bin -console
   ```

   During the uninstallation processes, you are prompted with a series of steps and menus. You can either accept the default value or select another choice. The default values are indicated in brackets or as predefined selections (checkmarks) in menus. To accept the default value, press **Enter**.

   When replying to a prompt, you can either accept the default value or select another choice.
   To reply yes, enter **Y**
   To reply no, enter **N**.
   Do not press **Delete**; doing so will cause the process to terminate with an error message.

   For selections in menus, you can accept default selections or type the number of the item and press **Enter**. An X appears next to the item. When you are finished making selections, type zero (**0**) and press **Enter**.

   If you incorrectly type an entry, press **5** to repeat the prompt and select the correct value. Arrow keys and the backspace key are not supported.

   Upon completion, the **Uninstallation Summary** displays informational messages such as successful confirmations, error messages, and warnings.

2. Press **Enter** to continue. If necessary, the installation program will prompt to restart your computer.

3. Press **1** to restart immediately or press **2** to restart later.

4. If you chose not to restart your computer, press **3** to finish.

5. Upon completion, the uninstallation program will remove all of the files and directories in the BASEDIR/smarts directory, and then remove the smarts directory.

   The uninstallation program will also write an uninstall log file to the BASEDIR directory, unless the uninstallation fails at the very start, in which case the installation program will write the log file to the /tmp directory. The log file is a text file with the naming convention Uninstall.‹product›.‹productversionNumber›.log.

Uninstall using Unattended mode

The Unattended mode enables you to automate the removal of the EMC Smarts products.

1. Invoke the uninstallation program with appropriate options for the operating system:
   - On UNIX systems, go to the BASEDIR/_uninst directory and enter the following command:

     ```
     uninstaller.bin -silent
     ```

   - On Windows system, go to the BASEDIR_uninst directory and enter the following command:

     ```
     uninstaller.exe -silent
     ```

2. Upon completion, the uninstallation program will remove all of the files and directories in the BASEDIR/smarts directory, and then remove the smarts directory.

   The uninstallation program will also write an uninstall log file to the BASEDIR directory, unless the uninstallation fails at the very start, in which case the installation program will write the log file to the /tmp directory. A non-zero status indicates a failure. The log file is a text file with the naming convention Uninstall.‹product›.‹productversionNumber›.log.

APPENDIX A
The sm_edit utility

This appendix describes how to use the sm_edit utility. It consists of the following topics:

- sm_edit 122
- sm_edit example 122

sm_edit

As part of the EMC Smarts deployment and configuration process, you need to modify certain files. User modifiable files include configuration files, rule set files, templates, and seed files that contain encrypted passwords. Original versions of these files are installed into appropriate subdirectories under the BASEDIR/smarts/ directory.

The original versions of files should not be altered. If a file must be modified, a new version should be created and then stored as a local copy of the file in BASEDIR/smarts/local or one of its subdirectories.

When EMC Smarts software requires one of these files, it is designed to first search for a modified file in BASEDIR/smarts/local or one of its subdirectories. If a modified version of a file is not found in the local area, EMC Smarts software then searches corresponding BASEDIR/smarts directories for the original version of the file.

To ease file editing and storage, EMC Corporation provides the sm_edit utility with the every EMC Smarts product. When invoked, sm_edit opens the specified file in a text editor. This utility ensures that modified files are always saved to the appropriate local area and that non-local copies of all files remain unchanged. If an appropriate subdirectory does not exist for the file you are modifying, sm_edit creates the appropriate subdirectory before saving the modified file to that location. For files with header information set for encryption, sm_edit encrypts certain fields in the file. In addition, sm_edit preserves the file permissions of modified files, which helps ensure that important configuration files are not altered by unauthorized users.

The *EMC Smarts System Administration Guide* provides instructions on how to configure the utility to use a specific editor.

sm_edit example

To use sm_edit from the command line, specify the file name and include the subdirectory under BASEDIR/smarts/local where the file resides. For example, to edit the trapd.conf, enter the following command from the BASEDIR/smarts/bin directory:

```
sm_edit conf/trapd/trapd.conf
```

In this example, sm_edit searches in the BASEDIR/smarts/local/conf/trapd directory for the trapd.conf file. If it finds the trapd.conf file, it opens the file in a text editor. If sm_edit does not find the trapd.conf file in the BASEDIR/smarts/local/conf/trapd directory, it creates a local copy of the trapd.conf file and writes it to the BASEDIR/smarts/local/conf/trapd directory.

The *EMC Smarts System Administration Guide* provides additional information about the sm_edit utility.

APPENDIX B
Manually Installing Services

This appendix describes how to install services manually for the EMC Smarts Service Assurance Manager, EMC Smarts IP Manager, EMC Smarts MPLS Manager, EMC Smarts Server Manager, EMC Smarts Network Protocol Manager, EMC Smarts Optical Transport Manager, and EMC Smarts VoIP Availability Manager. It consists of the following topics:

- Overview 124
- Broker services 124
- Services for the IP Manager 125
- Services for the Service Assurance Manager 131
- Services for the MPLS Manager 137
- Services for the Server Manager 139
- Services for the Network Protocol Manager installation 140
- Services for the Optical Transport Manager 143
- Services for the VoIP Availability Manager 148

Overview

If you did not install services when you installed the EMC Smarts products, you may install services manually. Services are programs that, once started, are generally intended to run continuously. Components installed as services start automatically upon system reboot; those not installed as services (manual processes or disabled processes) require that you issue commands to start and stop them as necessary.

EMC Corporation recommends that EMC Smarts products be installed as services whenever possible. Typical reasons to install products as services include the following conditions:

- (IP Manager only) There is a need to install services for a single product instead of the combined IP Availability Manager and IP Performance Manager products (for example, IP Availability Manager alone or IP Performance Manager alone). "Selection of bootstrap files when installing services" on page 124 provides more information.
- During installation of the product software, you chose to start product components manually and now want to run the components as services.
- Multiple instances of a single product component running as a service are required. During installation, you can install only a single instance of a product component as a service.

To manually install a product as a service, use the sm_service install command with the appropriate set of options.

The *EMC Smarts System Administration Guide* provides a complete description of the command syntax.

Selection of bootstrap files when installing services

When you install IP Manager 9.4.2 with all services selected, both IP Availability Manager and IP Performance Manager services are installed. The default configuration file, bootstrap.conf, is used by the IP Manager 9.4.2 installer.

If your deployment supports only IP Availability Manager or IP Performance Manager, you must manually install these services for the IP Manager(s) using a bootstrap file different from bootstrap.conf.

Broker services

This section provides the default UNIX and Windows commands that are used to install the service manually for the Broker. Type the command on one line.

UNIX

```
▼BASEDIR/smarts/bin/sm_service install
   --force
   --name=ic-broker
   "--description= EMC Smarts Broker"
   --env=SM_CLIENTCONNECT=brokerConnect.conf
   --startmode=runonce
   BASEDIR/smarts/bin/brstart
   --port=426
   --output
   --restore=BASEDIR/smarts/local/repos/ broker/broker.rps ▲
```

Windows

```
▼BASEDIR\smarts\bin\sm_service install
   --force
   --name=ic-broker
   "--description= EMC Smarts Broker"
   --env=SM_CLIENTCONNECT=brokerConnect.conf
   --startmode=runonce
   BASEDIR\smarts\bin\brstart.exe
   "--port=426"
   "--output"
   "--restore=BASEDIR\smarts\local\repos\ broker\broker.rps"▲
```

NOTICE

▼▲ indicates that this command must be typed as one line.

Services for the IP Manager

Here are the UNIX commands used to install services manually for the underlying servers in the IP Manager.

IP Availability Manager-only server

UNIX

```
▼/opt/InCharge/IP/smarts/bin/sm_service install
   --force
   --name=ic-am-server
   "--description= EMC Smarts IP Availability Manager Server"
   --startmode=runonce
   /opt/InCharge/IP/smarts/bin/sm_server
   --name=INCHARGE-AM
   --config=icf
   --bootstrap=bootstrap-am.conf
   --port=0
   --subscribe=default
   --ignore-restore-errors
   --output▲
```

Windows

```
▼C:\InCharge\IP\smarts\bin\sm_service install
   --force
   --name=ic-am-server
   "--description= EMC Smarts IP Availability Manager Server"
   --startmode=runonce
   C:\InCharge\IP\smarts\bin\sm_server.exe
   "--name=INCHARGE-AM"
   "--config=icf"
   "--bootstrap=bootstrap-am.conf"
   "--port=0"
   "--subscribe=default"
   "--ignore-restore-errors"
   "--output"▲
```

IP Availability Manager-only server (interacting with EMC M&R)

Use this syntax for the IP Availability Manager if you plan use the EMC M&R UI to configure IP Manager settings.

The *Service Assurance Suite How to Maintain IP Manager Settings* article explains how to use the IP Availability Manager with the Configuration Manager to configure IP Manager settings. The *SolutionPack for EMC Smarts Summary Sheet* article provide information on viewing notifications from the EMC M&R user interface. The *Service Assurance Suite Documentation Index*, available on the EMC Community Network (ECN), provides links to related documentation.

UNIX

```
▼ /opt/InCharge/IP/smarts/bin/sm_service install
   --force
   --name=ic-am-server
   "--description= EMC Smarts IP Availability Manager Server"
   --startmode=runonce
   /opt/InCharge/IP/smarts/bin/sm_server
   --name=INCHARGE-AM
   --config=icf
   --bootstrap=bootstrap-am.conf
   --port=0
   --edaa=ip/2.0
   --ignore-restore-errors
   --output▲
```

Windows

```
▼ C:\InCharge\IP\smarts\bin\sm_service install
   --force
   --name=ic-am-server
   "--description= EMC Smarts IP Availability Manager Server"
   --startmode=runonce
   C:\InCharge\IP\smarts\bin\sm_server.exe
   "--name=INCHARGE-AM"
   "--config=icf"
   "--bootstrap=bootstrap-am.conf"
   "--port=0"
   "--edaa=ip\2.0"
   "--ignore-restore-errors"
   "--output"▲
```

IP Performance Manager-only Server

UNIX

```
▼ /opt/InCharge/IP/smarts/bin/sm_service install
   --force
   --name=ic-pm-server
   "--description= EMC Smarts IP Performance Manager Server"
   --startmode=runonce
   /opt/InCharge/IP/smarts/bin/sm_server
   --name=INCHARGE-PM
   --config=icf
   --bootstrap=bootstrap-pm.conf
   --port=0
   --subscribe=default
   --ignore-restore-errors
   --output▲
```

Windows

```
▼C:\InCharge\IP\smarts\bin\sm_service install
  --force
  --name=ic-pm-server
  "--description= EMC Smarts IP Performance Manager Server"
  --startmode=runonce
  C:\InCharge\IP\smarts\bin\sm_server.exe
  "--name=INCHARGE-PM"
  "--config=icf"
  "--bootstrap=bootstrap-pm.conf"
  "--port=0"
  "--subscribe=default"
  "--ignore-restore-errors"
  "--output"▲
```

IP Performance Manager-only Server (interacting with EMC M&R)

Use this syntax for the IP Performance Manager if you plan use the EMC M&R UI to configure IP Manager settings.

The *Service Assurance Suite How to Maintain IP Manager Settings* article explains how to use the IP Performance Manager with the Configuration Manager to configure IP Manager settings. The *SolutionPack for EMC Smarts Summary Sheet* article provide information on viewing notifications from the EMC M&R user interface. The *Service Assurance Suite Documentation Index*, available on the EMC Community Network (ECN), provides links to related documentation.

UNIX

```
▼/opt/InCharge/IP/smarts/bin/sm_service install
  --force
  --name=ic-pm-server
  "--description= EMC Smarts IP Performance Manager Server"
  --startmode=runonce
  /opt/InCharge/IP/smarts/bin/sm_server
  --name=INCHARGE-PM
  --config=icf
  --bootstrap=bootstrap-pm.conf
  --port=0
  --edaa=ip/2.0
  --ignore-restore-errors
  --output▲
```

Windows

```
▼C:\InCharge\IP\smarts\bin\sm_service install
  --force
  --name=ic-pm-server
  "--description= EMC Smarts IP Performance Manager Server"
  --startmode=runonce
  C:\InCharge\IP\smarts\bin\sm_server.exe
  "--name=INCHARGE-PM"
  "--config=icf"
  "--bootstrap=bootstrap-pm.conf"
  "--port=0"
  "--edaa=ip\2.0"
  "--ignore-restore-errors"
  "--output"▲
```

IP Availability and Performance Manager Server

UNIX

```
▼/opt/InCharge/IP/smarts/bin/sm_service install
 --force
 --name=ic-am-pm-server
 "--description= EMC Smarts IP Availability Manager and Performance
 Manager Server"
 --startmode=runonce
 /opt/InCharge/IP/smarts/bin/sm_server
 --name=INCHARGE-AM-PM
 --config=icf
 --bootstrap=bootstrap-am-pm.conf
 --port=0
 --subscribe=default
 --ignore-restore-errors
 --output▲
```

Windows

```
▼C:\InCharge\IP\smarts\bin\sm_service install
 --force
 --name=ic-am-pm-server
 "--description= EMC Smarts IP Availability Manager and Performance
 Manager Server"
 --startmode=runonce
 C:\InCharge\IP\smarts\bin\sm_server.exe
 "--name=INCHARGE-AM-PM"
 "--config=icf"
 "--bootstrap=bootstrap-am-pm.conf"
 "--port=0"
 "--subscribe=default"
 "--ignore-restore-errors"
 "--output"▲
```

IP Availability and Performance Manager Server (interacting with EMC M&R)

Use this syntax for the IP Availability and Performance Manager if you plan use the EMC M&R UI to configure IP Manager settings.

The *Service Assurance Suite How to Maintain IP Manager Settings* article explains how to use the IP Availability and Performance Manager with the Configuration Manager to configure IP Manager settings. The *SolutionPack for EMC Smarts Summary Sheet* article provide information on viewing notifications from the EMC M&R user interface. The *Service Assurance Suite Documentation Index*, available on the EMC Community Network (ECN), provides links to related documentation.

UNIX

```
▼/opt/InCharge/IP/smarts/bin/sm_service install
 --force
 --name=ic-am-pm-server
 "--description= EMC Smarts IP Availability Manager and Performance
 Manager Server"
 --startmode=runonce
 /opt/InCharge/IP/smarts/bin/sm_server
 --name=INCHARGE-AM-PM
 --config=icf
 --bootstrap=bootstrap-am-pm.conf
 --port=0
 --edaa=ip/2.0
 --ignore-restore-errors
 --output▲
```

Windows

```
▼C:\InCharge\IP\smarts\bin\sm_service install
   --force
   --name=ic-am-pm-server
   "--description= EMC Smarts IP Availability Manager and Performance
   Manager Server"
   --startmode=runonce
   C:\InCharge\IP\smarts\bin\sm_server.exe
   "--name=INCHARGE-AM-PM"
   "--config=icf"
   "--bootstrap=bootstrap-am-pm.conf"
   "--port=0"
   "--edaa=ip\2.0"
   "--ignore-restore-errors"
    "--output"▲
```

IP Configuration Manager

UNIX

```
/opt/InCharge/IP/smarts/bin/sm_service install
   --force
   --name=ic-ip-configuration
   "--description=EMC Smarts IP Configuration Manager"
   --startmode=runonce
   /opt/InCharge/IP/smarts/bin/sm_server
   --name=INCHARGE-CM
   --config=icf-c
   --bootstrap=bootstrap.conf
   --port=0
   --subscribe=default
   --ignore-restore-errors
   --nodx
   --output
```

Windows

```
C:\InCharge\IP\smarts\bin\sm_service install
   --force
   --name=ic-ip-configuration
   "--description=EMC Smarts IP Configuration Manager"
   --startmode=runonce
   C:\InCharge\IP\smarts\bin\sm_server.exe
   "--name=INCHARGE-CM"
   "--config=icf-c"
   "--bootstrap=bootstrap.conf"
   "--port=0"
   "--subscribe=default"
   "--ignore-restore-errors"
   "--nodx"
   "--output"
```

IP Configuration Manager (interacting with EMC M&R)

Use this syntax for the Configuration Manager if you plan use the EMC M&R UI to configure IP Manager settings.

The *Service Assurance Suite How to Maintain IP Manager Settings* article explains how to use the Configuration Manager to configure IP Manager settings. The *SolutionPack for EMC Smarts Summary Sheet* article provide information on viewing notifications from the EMC M&R user interface. The *Service Assurance Suite Documentation Index*, available on the EMC Community Network (ECN), provides links to related documentation.

UNIX

```
/opt/InCharge/IP/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-ip-configuration-edaa
   "--description=EMC Smarts IP Configuration Manager for EDAA"
   /opt/InCharge/IP/smarts/bin/sm_server
   --name=INCHARGE-CM
   --config=icf-c
   --bootstrap=bootstrap.conf
   --port=0
   --edaa=ip/2.0
   --ignore-restore-errors
   --nodx
   --output
```

Windows

```
C:\InCharge\IP\smarts\bin\sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-ip-configuration-edaa
   "--description=EMC Smarts IP Configuration Manager for EDAA"
   C:\InCharge\IP\smarts\bin\sm_server.exe
   "--name=INCHARGE-CM"
   "--config=icf-c"
   "--bootstrap=bootstrap.conf"
   "--port=0"
   "--edaa=ip\2.0"
   "--ignore-restore-errors"
   "--nodx"
   "--output"
```

Services for the Service Assurance Manager

This section provides default service parameters for the EMC Smarts Service Assurance Manager.

EMC Smarts Broker

UNIX

```
▼ /opt/InCharge/SAM/smarts/bin/sm_service install
  --force
  --startmode=runonce
  --name=ic-broker
  --description="EMC Smarts Broker"
  --env=SM_CLIENTCONNECT=brokerConnect.conf
  /opt/InCharge/SAM/smarts/bin/brstart
  --port=426
  --restore=/opt/InCharge/SAM/smarts/local/repos/broker/broker.rps
  --output▲
```

Windows

```
▼ C:\InCharge\SAM\smarts\bin\sm_service.exe install
  --force
  --startmode=runonce
  --name=ic-broker
  --description="EMC Smarts Broker"
  --env=SM_CLIENTCONNECT=brokerConnect.conf
  C:\InCharge\SAM\smarts\bin\brstart.exe
  --port=426
  --restore=C:\InCharge\SAM\smarts\local\repos\broker\broker.rps▲
```

Service Assurance Manager (Presentation SAM server)

UNIX

```
/opt/InCharge/SAM/smarts/bin/sm_service install
--force
--unmanaged
--startmode=runonce
--name=ic-sam-server-pres
--description=”EMC Smarts Service Assurance Manager Server
   (notification cache publishing)”
/opt/InCharge/SAM/smarts/bin/sm_server
-n INCHARGE-SA-PRES
--config=ics
--port=0
--edaa=sam-presentation/2.0
--bootstrap=bootstrap-amqp.conf
--ignore-restore-errors
--output
```

Windows

```
C:\InCharge\SAM\smarts\bin\sm_service install --force  --unmanaged
   --startmode=runonce
“--name=ic-sam-server-pres”
“--description=EMC Smarts Service Assurance Manager Server
   (notification cache publishing)”
C:\InCharge\SAM\smarts\bin\sm_server
“-n INCHARGE-SA-PRES”
“--config=ics”
“--port=0”
“--edaa=sam-presentation\2.0”
“--bootstrap=bootstrap-amqp.conf”
“--ignore-restore-errors”
“--output”
```

Service Assurance Manager (Global Manager)

UNIX

```
▼ /opt/InCharge/SAM/smarts/bin/sm_service install
  --force
  --unmanaged
  --name=ic-sam-server
  --startmode=runonce
  --description="EMC Smarts Service Assurance Manager
     Server"
  /opt/InCharge/SAM/smarts/bin/sm_server
  --name=INCHARGE-SA
  --config=ics
  --port=0
  --ignore-restore-errors
  --output▲
```

Windows

```
▼ C:\InCharge\SAM\smarts\bin\sm_service.exe install
  --force
  --name=ic-sam-server
  --startmode=runonce
  --description="EMC Smarts Service Assurance Manager
     Server"
  C:\InCharge\SAM\smarts\bin\sm_server.exe
  --name=INCHARGE-SA
  --config=ics
  --port=0
  --ignore-restore-errors
  --output▲
```

Business Impact Manager server

UNIX

```
▼/opt/InCharge/SAM/smarts/bin/sm_service install
  --startmode=runonce
  --name=MBIM
  --description=”EMC Smarts MBIM – Maintenance and Business Impact
  Manager Server”
  /opt/InCharge/SAM/smarts/bin/sm_server
  --name=INCHARGE-MBIM
  --config=bim
  --port=0
  --ignore-restore-errors
  --output▲
```

Windows

```
▼C:\InCharge\SAM\smarts\bin\sm_service.exe install
  --startmode=runonce
  --name=MBIM
  --description=”EMC Smarts MBIM – Maintenance and Business Impact
  Manager Server”
  C:\InCharge\SAM\smarts\bin\sm_server.exe
  --name=INCHARGE-MBIM
  --config=bim
  --port=0
  --ignore-restore-errors
  --output▲
```

Adapter Platform

UNIX

```
▼ /opt/InCharge/SAM/smarts/bin/sm_service install
  --force
  --unmanaged
  --name=ic-icoi-server
  --startmode=runonce
  --description="EMC Smarts SAM Adapter Platform Server"
  /opt/InCharge/SAM/smarts/bin/sm_server
  --name=INCHARGE-OI
  --config=icoi
  --port=0
  --ignore-restore-errors
  --output▲
```

Windows

```
▼ C:\InCharge\SAM\smarts\bin\sm_service.exe install
  --force
  --name=ic-icoi-server
  --startmode=runonce
  --description="EMC Smarts SAM Adapter Platform Server"
  C:\InCharge\SAM\smarts\bin\sm_server.exe
  --name=INCHARGE-OI
  --config=icoi
  --port=0
  --ignore-restore-errors
  --output▲
```

Business Dashboard

UNIX

```
▼ /opt/InCharge/CONSOLE/smarts/bin/sm_service install
  --force
  --unmanaged
  --name=ic-business-dashboard
  --startmode=runonce
  --description="EMC Smarts Servlet Engine"
  /opt/InCharge/CONSOLE/smarts/bin/sm_tomcat
  --output
  start▲
```

Windows

```
▼ C:\InCharge\CONSOLE\smarts\bin\sm_service.exe install
  --force
  --name=ic-business-dashboard
  --startmode=runonce
  --description="EMC Smarts Servlet Engine"
  C:\InCharge\CONSOLE\smarts\bin\sm_tomcat.exe
  --output
  start▲
```

Syslog Adapter

Before you configure the Syslog Adapter, identify the location of the SYSFILE you want the adapter to tail and parse and ensure that sm_service install command line for the ic-syslog-adapter identifies this location. The *EMC Smarts Service Assurance Manager Adapter Platform User Guide* provides more information on configuring the Syslog Adapter.

UNIX

▼
```
/opt/InCharge/SAM/smarts/bin/sm_service install
--force
--unmanaged
--name=ic-syslog-adapter
--startmode=runonce
--description="EMC Smarts Syslog Adapter"
/opt/InCharge/SAM/smarts/bin/sm_adapter
--name=SYSLOG-INCHARGE-OI
--rserver=INCHARGE-OI
--tail=/var/log/syslog
--model=sm_system
--model=sm_actions
--output icoi-syslog/syslog_mgr.asl▲
```

Windows

▼
```
C:\InCharge\SAM\smarts\bin\sm_service.exe install
--force
--name=ic-syslog-adapter
--description="EMC Smarts Syslog Adapter"
--startmode=runonce
C:\InCharge\SAM\smarts\bin\sm_adapter.exe
--name=SYSLOG-INCHARGE-OI
--rserver=INCHARGE-OI
--tail=/var/log/syslog
--model=sm_system
--model=sm_actions
--output icoi-syslog/syslog_mgr.asl▲
```

SNMP Trap Adapter

UNIX

▼
```
/opt/InCharge/SAM/smarts/bin/sm_service install
--force
--unmanaged
--name=ic-trapd-receiver
--startmode=runonce
--description="EMC Smarts SNMP Trap Adapter"
/opt/InCharge/SAM/smarts/bin/sm_trapd
--name=TRAP-INCHARGE-OI
--server=INCHARGE-OI
--config=icoi
--port=162
--seed=seedfile
--model=sm_actions
--output
--rules=icoi-trapd/trap_mgr_parse.asl▲
```

Windows

```
▼ C:\InCharge\SAM\smarts\bin\sm_service.exe install
  --force
  --name=ic-trapd-receiver
  --startmode=runonce
  --description="EMC Smarts SNMP Trap Adapter"
  C:\InCharge\SAM\smarts\bin\sm_trapd.exe
  --name=TRAP-INCHARGE-OI
  --server=INCHARGE-OI
  --config=icoi
  --port=162
  --seed=seedfile
  --model=sm_actions
  --output
  --rules=icoi-trapd/trap_mgr_parse.asl▲
```

Notif trap Adapter

UNIX

```
▼ /opt/InCharge/SAM/smarts/bin/sm_service install --force -unmanaged
  --startmode=runonce
  --name=ic-notif-trapd-receiver
  --description="EMC Smarts NOTIF SNMP Trap Adapter"
  /opt/InCharge/SAM/smarts/bin/sm_trapd
  --name=NOTIF-TRAP-INCHARGE-OI
  --server=INCHARGE-OI
  --config=icoi
  --port=162
  --model=sm_actions
  --rules=icoi-trapd/Notif-trap_mgr_parse.asl
  --seed=seedfile
  --output▲
```

Windows

```
▼C:\InCharge\SAM\smarts\bin>sm_service install --force
  --name=ic-notif-trapd-receiver
  --description="EMC Smarts NOTIF SNMP Trap Adapter"
  C:\InCharge\SAM\smarts\bin\sm_trapd.exe
  --name=NOTIF-TRAP-INCHARGE-OI
  --server=INCHARGE-OI
  --config=icoi
  --port=162
  --model=sm_actions
  --rules=icoi-trapd/Notif-trap_mgr_parse.asl
  --seed=seedfile
  --output▲
```

Notif syslog adapter

UNIX

```
▼/opt/InCharge/SAM/smarts/bin/sm_service install --force --unmanaged
  --startmode=runonce
  --name=ic-notif-syslog-adapter
  --description="EMC Smarts Syslog Adapter"
  /opt/InCharge/SAM/smarts/bin/sm_adapter
  --name=NOTIF-SYSLOG-INCHARGE-OI
  --rserver=INCHARGE-OI
  --tail=/var/log/syslog
  --model=sm_system
  --model=sm_actions
  --output icoi-syslog/Notif-SysLog_mgr.asl▲
```

Windows

```
▼C:\InCharge\SAM\smarts\bin\sm_service install --force
   --name=ic-notif-syslog-adapter
   --description="EMC Smarts Syslog Adapter"
   C:\InCharge\SAM\smarts\bin\sm_adapter.exe
   --name=NOTIF-SYSLOG-INCHARGE-OI
   --rserver=INCHARGE-OI
   --tail=/var/log/syslog
   --model=sm_system
   --model=sm_actions
   --output icoi-syslog/Notif-SysLog_mgr.asl▲
```

EMC Smarts Data Web Applications (Tomcat)

UNIX

```
/opt/InCharge/SAM/smarts/bin/sm_service install --force --unmanaged
--startmode=runonce
--name=smarts-tomcat
--description=”EMC Smarts Data Web Applications (Tomcat)”
/opt/InCharge/SAM/smarts/bin/sm_tomcat
--ignoreme
```

Windows

```
C:\InCharge\SAM\smarts\bin\sm_service install --force  --unmanaged
--startmode=runonce
“--name=smarts-tomcat”
“--description=EMC Smarts Data Web Applications (Tomcat)”
C:\InCharge\SAM\smarts\bin\sm_tomcat
“--ignoreme”
```

EMC Smarts Notification Exchange (Rabbit MQ)

UNIX

```
/opt/InCharge/SAM/smarts/bin/sm_service install --force
--unmanaged  --startmode=runonce
--name=smarts-rabbitmq
--description=”EMC Smarts Notification Exchange (Rabbit MQ)”
/opt/InCharge/SAM/smarts/bin/sm_rabbitmq
--ignoreme
```

Windows

```
C:\InCharge\SAM\smarts\bin\sm_service install --force
--unmanaged  --startmode=runonce
“--name=smarts-rabbitmq”
“--description=EMC Smarts Notification Exchange (Rabbit MQ)”
C:\InCharge\SAM\smarts\bin\sm_rabbitmq
“--ignoreme”
```

EMC Smarts Notification Cache (ElasticSearch)

UNIX

```
/opt/InCharge/SAM/smarts/bin/sm_service install --force
--unmanaged  --startmode=runonce
--name=smarts-elasticsearch
--description=”EMC Smarts Notification Cache (ElasticSearch)”
/opt/InCharge/SAM/smarts/bin/sm_elasticsearch
--ignoreme
```

Windows

```
C:\InCharge\SAM\smarts\bin\sm_service install --force
--unmanaged  --startmode=runonce
"--name=smarts-elasticsearch"
"--description=EMC Smarts Notification Cache (ElasticSearch)"
C:\InCharge\SAM/smarts\bin\sm_elasticsearch
"--ignoreme"
```

Services for the MPLS Manager

This section provides the default UNIX and Windows commands that are used to install services manually for the MPLS Manager. Type the command on one line.

For the MPLS Manager, when you install the services manually, if you specify custom service and server names instead of the default names listed in Table 17 on page 99, you must run a script next. Running the script is required so that proper domain communication can be established. Appendix D, "Using the MPLS server_config Utility," provides information about the script.

MPLS Topology Server

When you start the MPLS Manager for the first time (and only the first time) after migrating from the previous version to the new version, you must start the MPLS Topology Server with the --ignore-restore-errors option.

UNIX

```
▼/opt/InCharge/MPLS/smarts/bin/sm_service install
  --force
  --unmanaged
  --startmode=runonce
  --name=ic-mpls-topology
  --description="EMC Smarts MPLS Topology Server"
  /opt/InCharge/MPLS/smarts/bin/sm_server
  --name=INCHARGE-MPLS-TOPOLOGY
  --config=mpls-t
  --ignore-restore-errors
  --output▲
```

Windows

```
▼C:\InCharge\MPLS\smarts\bin\sm_service.exe install
  --force
  --unmanaged
  --startmode=runonce
  --name=ic-mpls-topology
  --description="EMC Smarts MPLS Topology Server"
  C:\InCharge\MPLS\smarts\bin\sm_server.exe
  --name=INCHARGE-MPLS-TOPOLOGY
  --config=mpls-t
  --ignore-restore-errors
  --output▲
```

MPLS Monitoring Server

UNIX

```
▼/opt/InCharge/MPLS/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-mpls-monitoring
   --description="EMC Smarts MPLS Monitoring Server"
   /opt/InCharge/MPLS/smarts/bin/sm_server
   --name=INCHARGE-MPLS-MONITORING
   --config=mpls-m
   --ignore-restore-errors
   --output▲
```

Windows

```
▼C:\InCharge\MPLS\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-mpls-monitoring
   --description="EMC Smarts MPLS Monitoring Server"
   C:\InCharge\MPLS\smarts\bin\sm_server.exe
   --name=INCHARGE-MPLS-MONITORING
   --config=mpls-m
   --ignore-restore-errors
   --output▲
```

MPLS Analysis Server

UNIX

```
▼/opt/InCharge/MPLS/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-mpls-analysis
   --description="EMC Smarts MPLS Analysis Server"
   /opt/InCharge/MPLS/smarts/bin/sm_server
   --name=INCHARGE-MPLS-ANALYSIS
   --config=mpls-a
   --ignore-restore-errors
   --output▲
```

Windows

```
▼C:\InCharge\MPLS\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-mpls-analysis
   --description="EMC Smarts MPLS Analysis Server"
   C:\InCharge\MPLS\smarts\bin\sm_server.exe
   --name=INCHARGE-MPLS-ANALYSIS
   --config=mpls-a
   --ignore-restore-errors
   --output▲
```

MPLS VPN-Tagging Server

UNIX

```
▼/opt/InCharge/MPLS/smarts/bin/sm_service install
  --force
  --unmanaged
  --startmode=runonce
  --name=ic-vpn-tagging
  --description="EMC Smarts MPLS VPN-Tagging Server"
  /opt/InCharge/MPLS/smarts/bin/sm_server
  --name=VPN-TAGGING
  --config=vpn-tagging
  --ignore-restore-errors
  --output▲
```

Windows

```
▼C:\InCharge\MPLS\smarts\bin\sm_service.exe install
  --force
  --unmanaged
  --startmode=runonce
  --name=ic-vpn-tagging
  --description="EMC Smarts MPLS VPN-Tagging Server"
  C:\InCharge\MPLS\smarts\bin\sm_server.exe
  --name=VPN-TAGGING
  --config=vpn-tagging
  --ignore-restore-errors
  --output▲
```

Services for the Server Manager

This section provides the default UNIX and Windows commands that are used to install the service manually for the EMC Smarts Server Manager. Type the command on one line.

Server Manager

UNIX

```
▼opt/InCharge/ESM/smarts/bin/sm_service install
  --force
  --unmanaged
  --name=ic-esm-server
  --description="EMC Smarts Server Manager (ESM)"
  --startmode=runonce
  opt/InCharge/ESM/smarts/bin/sm_server
  --name=INCHARGE-ESM
  --config=esm
  --subscribe=default
  --output
  --ignore-restore-errors▲
```

Windows

```
▼C:\InCharge\ESM\smarts\bin\sm_service.exe install
  --force
  --unmanaged
  --name=ic-esm-server
  --description="EMC Smarts Server Manager (ESM)"
  --startmode=runonce
  C:\InCharge\ESM\smarts\bin\sm_server.exe
  --name=INCHARGE-ESM
  --config=esm
  --subscribe=default
  --output
  --ignore-restore-errors▲
```

Services for the Network Protocol Manager installation

This section provides the default UNIX and Windows commands that are used to install services manually for the Network Protocol Manager. Type the command on one line.

Network Protocol Manager for BGP

UNIX (IPv6 and IPv4 mode)

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-bgp-server
   --description="EMC Smarts NPM for BGP Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-BGP
   --config=bgp
   --port=0
   --subscribe=default
   --output
```

Windows (IPv6 and IPv4 mode)

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-bgp-server
   --description="EMC Smarts NPM for BGP Server"
   --startmode=runonce
   C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-BGP
   --config=bgp
   --port=0
   --subscribe=default
   --output
```

UNIX (IPv4 mode only)

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-bgp-server
   --description="EMC Smarts NPM for BGP Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-BGP
   --config=bgp
   --port=0
   --bootstrap=bootstrap-ipv4.conf
   --subscribe=default
   --output
```

Windows (IPv4 mode only)

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-bgp-server
   --description="EMC Smarts NPM for BGP Server"
   --startmode=runonce
   C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-BGP
   --config=bgp
   --bootstrap=bootstrap-ipv4.conf
   --port=0
   --subscribe=default
   --output
```

Network Protocol Manager for EIGRP

UNIX

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-eigrp-server
   --description="EMC Smarts NPM for EIGRP Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-EIGRP
   --config=eigrp
   --port=0
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-eigrp-server
   --description="EMC Smarts NPM for EIGRP Server"
   --startmode=runonce
   C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-EIGRP
   --config=eigrp
   --port=0
   --subscribe=default
   --ignore-restore-errors
   --output
```

Network Protocol Manager for IS-IS

UNIX (IPv6 and IPv4 mode)

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-isis-server
   --description="EMC Smarts NPM for ISIS Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-ISIS
   --config=isis
   --port=0
   --subscribe=default
   --output
```

Windows (IPv6 and IPv4 mode)

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-isis-server
   --description="EMC Smarts NPM for ISIS Server"
   --startmode=runonce
   C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-ISIS
   --config=isis
   --port=0
   --subscribe=default
   --output
```

UNIX (IPv4 mode only)

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-isis-server
   --description="EMC Smarts NPM for ISIS Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-ISIS
   --config=isis
   --port=0
   --bootstrap=bootstrap-ipv4.conf
   --subscribe=default
   --output
```

Windows (IPv4 mode only)

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-isis-server
   --description="EMC Smarts NPM for ISIS Server"
   --startmode=runonce
   --C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-ISIS
   --config=isis
   --port=0
   --bootstrap=bootstrap-ipv4.conf
   --subscribe=default
   --output
```

Network Protocol Manager for OSPF

UNIX (IPv6 and IPv4 mode)

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-ospf-server
   --description="EMC Smarts NPM for OSPF Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-OSPF
   --config=ospf
   --port=0
   --subscribe=default
   --output
```

Windows (IPv6 and IPv4 mode)

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-OSPF-server
   --description="EMC Smarts NPM for OSPF Server"
   --startmode=runonce
   C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-OSPF
   --config=ospf
   --port=0
   --subscribe=default
   --output
```

UNIX (IPv4 mode only)

```
/opt/InCharge/NPM/smarts/bin/sm_service install
   --force
   --name=ic-npm-OSPF-server
   --description="EMC Smarts NPM for OSPF Server"
   --startmode=runonce
   /opt/InCharge/NPM/smarts/bin/sm_server
   --name=INCHARGE-OSPF
   --config=ospf
   --port=0
   --bootstrap=bootstrap-ipv4.conf
   --subscribe=default
   --output
```

Windows (IPv4 mode only)

```
C:\InCharge\NPM\smarts\bin\sm_service.exe install
   --force
   --name=ic-npm-OSPF-server
   --description="EMC Smarts NPM for OSPF Server"
   --startmode=runonce
   C:\InCharge\NPM\smarts\bin\sm_server.exe
   --name=INCHARGE-OSPF
   --config=ospf
   --port=0
   --bootstrap=bootstrap-ipv4.conf
   --subscribe=default
   --output
```

Services for the Optical Transport Manager

This section provides the default UNIX and Windows commands that are used to install the services manually for the EMC Smarts Optical Transport Manager. Type the command on one line.

EMC Smarts Optical Transport Manager for Next Generation WDM

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-wdm-ng-server
   --description="EMC Smarts Optical Transport Manager for Next
   Generation WDM"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-WDM-NG
   --config=wdm-ng
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-wdm-ng-server
   --description="EMC Smarts Optical Transport Manager for Next
   Generation WDM"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-WDM-NG
   --config=wdm-ng
   --subscribe=default
   --ignore-restore-errors
   --output
```

EMC Smarts Optical Transport Manager for SDH (Topology)

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-sdh-topology-server
   --description="EMC Smarts Optical Transport Manager for SDH
   Topology"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-SDH-TOPOLOGY
   --config=osm-t
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-sdh-topology-server
   --description="EMC Smarts Optical Transport Manager for SDH
   Topology"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-SDH-TOPOLOGY
   --config=osm-t
   --subscribe=default
   --ignore-restore-errors
   --output
```

EMC Smarts Optical Transport Manager for SDH (Analysis)

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-sdh-analysis-server
   --description="EMC Smarts Optical Transport Manager for SDH
   Analysis"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-SDH-ANALYSIS
   --config=osm-a
   --subscribe=default
   --norestore
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-sdh-analysis-server
   --description="EMC Smarts Optical Transport Manager for SDH
   Analysis"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-SDH-ANALYSIS
   --config=osm-a
   --subscribe=default
   --norestore
   --output
```

EMC Smarts Optical Transport Manager for PDH (Topology)

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-pdh-topology-server
   --description="EMC Smarts Optical Transport Manager for PDH
   Topology"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-PDH-TOPOLOGY
   --config=pdh-t
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-pdh-topology-server
   --description="EMC Smarts Optical Transport Manager for PDH
   Topology"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-PDH-TOPOLOGY
   --config=pdh-t
   --subscribe=default
   --ignore-restore-errors
   --output
```

EMC Smarts Optical Transport Manager for PDH (Analysis)

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-pdh-analysis-server
   --description="EMC Smarts Optical Transport Manager for PDH
   Analysis"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-PDH-ANALYSIS
   --config=pdh-a
   --subscribe=default
   --norestore
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-pdh-analysis-server
   --description="EMC Smarts Optical Transport Manager for PDH
   Analysis"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-PDH-ANALYSIS
   --config=pdh-a
   --subscribe=default
   --norestore
   --output
```

EMC Smarts Optical Transport Manager for WDM (Topology)

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-wdm-topology-server
   --description="EMC Smarts Optical Transport Manager for WDM
   Topology"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-WDM-TOPOLOGY
   --config=wdm-t
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-wdm-topology-server
   --description="EMC Smarts Optical Transport Manager for WDM
   Topology"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-WDM-TOPOLOGY
   --config=wdm-t
   --subscribe=default
   --ignore-restore-errors
   --output
```

EMC Smarts Optical Transport Manager for WDM (Analysis)

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-wdm-analysis-server
   --description="EMC Smarts Optical Transport Manager for WDM
   Analysis"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-WDM-ANALYSIS
   --config=wdm-a
   --subscribe=default
   --norestore
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-wdm-analysis-server
   --description="EMC Smarts Optical Transport Manager for WDM
   Analysis"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-WDM-ANALYSIS
   --config=wdm-a
   --subscribe=default
   --norestore
   --output
```

EMC Smarts Optical Transport Manager for IP Cross Domain Analysis

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-xd-otm-ip-server
   --description="EMC Smarts Optical Transport Manager - IP CrossDomain
   Analysis Server"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-WDM-TOPOLOGY
   --config=icxd-ao
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-xd-otm-ip-server
   --description="EMC Smarts Optical Transport Manager - IP CrossDomain
   Analysis Server
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-WDM-TOPOLOGY
   --config=icxd-ao
   --subscribe=default
   --ignore-restore-errors
   --output
```

EMC Smarts TMF814 Cisco CTM Adapter for OTM

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-tmf814-cisco-ctm-adapter
   --description="EMC Smarts TMF814 Cisco CTM Adapter for OTM"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-CISCO-ADAPTER
   --config=tmf814Cisco
   --subscribe=default
   --norestore
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-tmf814-cisco-ctm-adapter
   --description="EMC Smarts TMF814 Cisco CTM Adapter for OTM"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-CISCO-ADAPTER
   --config=tmf814Cisco
   --subscribe=default
   --norestore
   --output
```

EMC Smarts TMF814 Ciena On-Center Adapter for OTM

UNIX

```
opt/InCharge/OTM/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-tmf814-ciena-onctr-adapter
   --description="EMC Smarts TMF814 Ciena On-Center Adapter for OTM"
   opt/InCharge/OTM/smarts/bin/sm_server
   --name=OTM-CIENA-ADAPTER
   --config=tmf814Ciena
   --subscribe=default
   --norestore
   --output
```

Windows

```
C:\InCharge\OTM\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-tmf814-ciena-onctr-adapter
   --description="EMC Smarts TMF814 Ciena On-Center Adapter for OTM"
   C:\InCharge\OTM\smarts\bin\sm_server.exe
   --name=OTM-CIENA-ADAPTER
   --config=tmf814Ciena
   --subscribe=default
   --norestore
   --output
```

Services for the VoIP Availability Manager

This section provides the default UNIX and Windows commands that are used to install services manually for the VoIP Availability Manager. Type the command on one line.

VoIP Availability Manager

UNIX

```
/opt/InCharge/VoIP/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-voip-server
   --description="EMC Smarts VoIP Availability Manager"
   --env=SM_JAVA_ENABLED=YES
   /opt/InCharge/VoIP/smarts/bin/sm_server
   --name=VoIP-AM
   --config=voip
   --port=0
   --subscribe=default
   --ignore-restore-errors
   --output
```

Windows

```
C:\InCharge\VoIP\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-voip-server
   "--description=EMC Smarts VoIP Availability Manager"
   "--env=SM_JAVA_ENABLED=YES"
   C:\InCharge\VoIP\smarts\bin\sm_server.exe
   "--name=VoIP-AM"
   "--config=voip"
   "--port=0"
   "--subscribe=default"
   "--ignore-restore-errors"
   "--output"
```

VoIP Notification Trap Adapter

UNIX

```
/opt/InCharge/VoIP/smarts/bin/sm_service install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-voip-notification-trapd-receiver
   --description="EMC VoIP Notification Trap Adapter"
   /opt/InCharge/VoIP/smarts/bin/sm_trapd
   --name=TRAP-INCHARGE-VOIP
   --server=INCHARGE-OI
   --config=voip
   --port=9002
   --model=sm_actions
   --rules=voip/voip_trap_mgr_parse.asl
   --output=TRAP-INCHARGE-VOIP
```

Windows

```
C:\InCharge\VoIP\smarts\bin\sm_service.exe install
   --force
   --unmanaged
   --startmode=runonce
   --name=ic-voip-notification-trapd-receiver
   --description="EMC VoIP Notification Trap Adapter"
   C:\InCharge\VoIP\smarts\bin\sm_trapd.exe
   --name=TRAP-INCHARGE-VOIP
   --server=INCHARGE-OI
   --config=voip
   --port=9002
   --model=sm_actions
   --rules=voip\voip_trap_mgr_parse.asl
   --output=TRAP-INCHARGE-VOIP
```

APPENDIX C
Procedures for CD/DVD-ROMs

This appendix includes commands and examples for working with a CD/DVD-ROM to install or upgrade product software. It consists of the following topics:

- Mounting a CD/DVD-ROM on UNIX systems 152
- Loading a CD/DVD-ROM on Windows 153

Mounting a CD/DVD-ROM on UNIX systems

Use the following procedure to find the instructions appropriate for your operating system:

1. Insert the CD/DVD-ROM into the optical drive.
2. If the CD/DVD-ROM is automatically mounted, continue to step 3 . Otherwise, select the appropriate mount command as shown in Table 21 on page 152.

Table 21 Mounting the CD/DVD-ROM for UNIX operating systems

Operating system	Commands and examples

CentOS	`# mount -o ro -F hsfs <device> /mnt`
	
	Example:
	`# mount -o ro -F hsfs /dev/dsk/c0t6d0s0 /mnt`

Linux	`# mount <device>`
	
	Example:
	`# mount /dev/cdrom /mnt/cdrom`

where *‹device›* is the mount point for the optical drive.	

3. Change to the CD/DVD-ROM directory by typing the appropriate command from Table 22 on page 152.

Table 22 Changing to the CD/DVD-ROM directory in UNIX operating systems

Operating system	Command

CentOS	If Volume Manager (VM) is running:
	`# cd /cdrom/<os>/<product>_SUITE/suite`
	
	If VM is not running:
	`# cd /mnt/suite`

Linux	If Automount is running:
	`# cd /cdrom/<os>/<product>_SUITE/suite`
	
	If Automount is not running:
	`# cd /mnt/cdrom/suite`

where: *‹os›* is the operating system, for example, CentOS_64, linux_64, or winnt_64. *‹product›* is the product software, for example, IP or MPLS.	

Loading a CD/DVD-ROM on Windows

The installation program starts automatically on Windows systems when AutoPlay or AutoRun is enabled:

1. Insert the CD/DVD-ROM into the optical drive. If AutoPlay or AutoRun is enabled, the installation program starts automatically using the Wizard mode.
2. If the installation program does not start, use Windows Explorer to locate the top-level folder of the mounted CD/DVD-ROM.
3. Locate the *product* directory on the CD/DVD-ROM and double-click the **setup** executable.

If you want to run CLI mode or Unattended mode on a Windows system, you need to disable the AutoPlay or AutoRun feature. To do so, press and hold the **Shift** key for approximately 10 seconds while inserting the CD/DVD-ROM into the optical drive.

APPENDIX D
Using the MPLS server_config Utility

This appendix pertains to the MPLS Manager. It provides an overview of the split topology architecture, an overview of the server_config utility used to rename domain groups and domains, and instructions on how to run the script.

- Use the server_config.pl script to change domain names 156

Use the server_config.pl script to change domain names

Purpose

When installed and unless the default domain name is changed during installation, MPLS Manager is configured with the default domain group name of INCHARGE-MPLS.

From this default domain group name, the three MPLS Manager server names are constructed by appending the function specific suffix to the default domain group name:

- INCHARGE-MPLS-TOPOLOGY
- INCHARGE-MPLS-MONITORING
- INCHARGE-MPLS-ANALYSIS

NOTICE

TOPOLOGY, MONITORING, and ANALYSIS are always appended to the Domain Group name to generate the three MPLS Manager domain managers.

A script (*server_config.pl*) is provided to make it easier to define server names, to update names, and populate the domain names changes to the default configurations files. Once updated, these new domain names are used by the TOPOLOGY, MONITORING and ANALYSIS servers.

Run the script

After the different servers have been installed with the default domain manager's names, you can use the server_config script to customize the domain managers' names.

The MPLS Manager post installation script uses the *sm_perl* command from either the MPLS BASEDIR/smarts/bin directory or from the location where the *server_config.pl* post installation script is located.

From the Perl /bin directory

Invoke the post installation script from the directory where the MPLS Manager post installation script is located.

```
sm_perl server_config.pl -o <OldGroupName> -n <NewGroupName> -b <BASEDIR>
```

From the MPLS installation directory

Invoke the post installation script from the directory where Perl is installed.

```
./sm_perl <BASEDIR>/smarts/script/mpls-tma/server_config.pl -o <OldGroupName> -n
   <NewGroupName> -b <BASEDIR>
```

Invoke the command line script *server_config.pl* options from the *BASEDIR/smarts/bin/* directory as follows:

- Install services with default name if they have not been installed previously (see Example).

  server_config.pl -i -o ‹OldGroupName› -n‹NewGroupName› -b‹BASEDIR›

- Rename services that have been installed previously (see Example).

server_config.pl -o ‹OldGroupName› -n‹NewGroupName› -b‹BASEDIR›

- Generate a list of services that have been installed previously (see Example).

  server_config.pl -s -b ‹BASEDIR›

- Display information on how to run the script with examples (see Example).

  server_config.pl -h

Example 1
```
server_config.pl -i -o "INCHARGE-MPLS" -n "HQ-MPLS" -b
   opt/InCharge/MPLS/smarts/
```

Example 2
```
server_config.pl -o "INCHARGE-MPLS" -n "HQ-MPLS" -b
   opt/InCharge/MPLS/smarts/
```

Example 3
```
server_config.pl -s -b opt/InCharge/MPLS/smarts/
```

Example 4
```
server_config.pl -h
```

Script options

Following are the required and optional command line script parameters:

NOTICE

Avoid using the following special characters when entering text strings for ‹OldGroupName› and ‹NewGroupName›: $ / \

Table 23 server_config.pl script command line options (page 1 of 2)

Option	Purpose
--install-service or -i	Indicates that the service needs to be installed. • This parameter must be used with the --old-group, --new-group, and --basedir parameters. • If the services are not installed, they are installed. • If services are already installed, they are uninstalled and reinstalled with the NewGroupName.
--old-group="‹OldGroupName›" or -o "‹OldGroupName›"	A required value that specifies the old group name to be changed. • You must include the OldGroupName variable string in double quotes. • This parameter must be used with the --new-group and --basedir parameters. • If services are running, will terminate without doing anything.
--new-group="‹NewGroupName›" or -n "‹NewGroupName›"	A required value that specifies the new group name. • You must include the NewGroupName variable string in double quotes. • This parameter must be used with the --old-group and --basedir parameters. • If services are running, will terminate without doing anything.
--basedir=‹BASEDIR› or -b ‹BASEDIR›	A required value which specifies the installation base directory. • This parameter must be used with the --old-group and --new-group parameters. • If services are running, will terminate without doing anything.

Table 23 server_config.pl script command line options (page 2 of 2)

Option	Purpose
--show or -s	Indicates that you want to see the current group names, services and Domain Manager names. • With this option, no changes are made to either the service or the configuration file. • This parameter must be used with the --basedir parameter.
--help or -h	--help or -h shows command line parameters and examples. This parameter is used alone.

NOTICE

The order of the parameters is not important.

NOTICE

Always include the BASEDIR of the installed services in the command line. The only instances where you do not have to include it is when using the Help (-h) option.

Following are the steps that the script performs once invoked:

1. If the local directory *BASEDIR/smarts/local/conf/mpls-tma* does not already exist, it is created and a copy of the original mpls-tma.conf file from the *BASEDIR/smarts/conf/mpls-tma* directory is copied to it.
2. If a service corresponding to the ‹OldGroupName› is installed, the following process is initiated:
   a. If the service is running and the user command line argument is not -s or --show, the script displays an error message and exits. You must stop the services before you can rename them.
   b. If the service is not running and the Service Daemon is running, then the script uninstalls the service for the current ‹OldGroupName›, installs the service for the ‹NewGroupName›, then continues to step 4.
   c. If the service is not running and the Service Daemon is not running, then the script displays a warning that there is potential for mismatch, uninstalls the service for the current ‹OldGroupName›, installs the service for the ‹NewGroupName›, then continues to step 4.
3. If a service corresponding to the ‹OldGroupName› is not installed, the following process is initiated:
   a. If the installation option (--i or -install-service) is not specified, the scripts does not install the service.
   b. If the installation option (--i or -install-service) is specified and if the Service Daemon is running, the script installs the service corresponding to the ‹NewGroupName›.
   c. If the installation option (--i or -install-service) is specified and if the Service Daemon is not running, the script warns you that you must start it and exits without further action.

4. After step 2 or step 3 are performed, the script copies the previous local configuration file to a backup file named .‹OldGroupName›‹.bak›
5. The script then replaces the ‹OldGroupName› with ‹NewGroupName› in *BASEDIR/smarts/local/conf/mpls-tma/mpls-tma.conf* and terminates.

APPENDIX E
EMC Smart Optical Transport Manager Configuration

This appendix provides instructions on configuring EMC Smarts Optical Transport Manager to communicate with the Global Manager component of the EMC Smarts Service Assurance Manager.

This appendix consists of the following topics:

- Prerequisites 162
- Configuring Optical Transport Manager 163
- Configuring the Service Assurance Manager 171
- Configuring the presentation layer Global Manager 172

Prerequisites

Optical Transport Manager

Before you configure Optical Transport Manager, one or more of the following Optical Transport Manager domain managers must be installed:

- Optical Transport Manager for SONET/SDH
- Optical Transport Manager for PDH
- Optical Transport Manager for WDM
- Optical Transport Manager for Next Generation WDM

Except for the OTM for Next Generation WDM, each of the above domain managers has a Topology/Monitoring server and an Analysis server.

If you installed the Optical Transport Manager for WDM NG (Next Generation), you must install and configure EMC M&R, the SolutionPack for Optical Wavelength Services, and the SolutionPack for EMC Smarts. The *Service Assurance Suite Documentation Index*, available on the EMC Community Network (ECN), provides links to these documents.

Note: In each domain, except for the OTM for Next Generation WDM domain, both Topology server and Analysis server must be installed and configured. In addition, OTM-IP XD may be installed and configured.

Note: The Optical Transport Manager and adapters do not need to be installed on the same host. However, you must register each component with the same EMC Broker that the Global Manager which manages the component is registered with.

SAM servers used with OTM

When OTM is connected to an IP XD Manager (IP cross-domain manager), three SAM servers should be started:

1. Connect the first SAM server to the OTM domains only.
2. Connect the second SAM server to the IP domain servers only.
3. Connect the third SAM server to the SAM servers described in steps 1 and 2 (connecting OTM domains and other analysis domains) and to the OTM-IP XD Manager server.

Global Manager

To configure and use the Global Manager with OTM, the following components must be installed on appropriate hosts in your network:

- Broker
- Global Console
- Global Manager

Configuring Optical Transport Manager

OTM settings

The various Optical Transport Manager Domain Manager servers, except for the Next Generation WDM Domain Manager, need to know the names of the other servers in order to communicate with each other for the following purposes:

- For importing topology from a Topology server to an Analysis server within a given domain. For example, from the SDH Topology server to the SDH Analysis server.
- For running post-processing in one domain after a topology change or update in another domain.

All OTM Domain Managers use this same file for configuration. The file is named **otm-settings.conf** and is found in the **BASEDIR/smarts/conf** directory.

To modify the otm-settings.conf file, use the sm_edit utility as described in Appendix A, "The sm_edit utility."

The configurable parameters, by default, look like this:

```
wdmTopologyServerName="OTM-WDM-TOPOLOGY"
sdhTopologyServerName="OTM-SDH-TOPOLOGY"
pdhTopologyServerName="OTM-PDH-TOPOLOGY"
wdmAnalysisServerName="OTM-WDM-ANALYSIS"
sdhAnalysisServerName="OTM-SDH-ANALYSIS"
pdhAnalysisServerName="OTM-PDH-ANALYSIS"
```

Change the names of the servers as needed for your configuration. Comment out any servers you are not using by adding a pound sign ("#") at the beginning of the line.

IMPORTANT

You must specify both Topology and Analysis servers of any Domain Manager.

Configuring EMC M&R for the OTM Next Generation WDM Manager

To configure EMC M&R for the OTM Next Generation WDM Manager, you need to specify the EMC M&R service location and EMC M&R login credentials. Perform these steps:

1. Specify the EMC M&R service location.

   The OTM Next Generation WDM Manager fetches topology data from the EMC M&R time-series database, using the EMC M&R Web-service APIs. You need to configure the M&R host or hosts (in case of multiple databases) which run the Web Service Backend with the OTM Next Generation WDM Manager.

   a. Open the *‹BASEDIR›/smarts/mnr-adapter/MNR.conf* file with the sm_edit utility:

      ```
      bin/sm_edit conf/mnr-adapter/MNR.conf
      ```

b. Locate the following section. Remove the comment characters (#) and make the required changes:

```
# <MnR_InstanceName> {
# HostName = <FQDN of the Host where the M&R server is running.
Default is "localhost">
# Port = <The port on which the M&R frontend is running. Default
is 58080>
# ListenerPort = <The port on which the M&R HTTP Listener is
running. Default is 55442>
# Protocol = HTTP/HTTPS <Protocol for accessing the M&R server.
Default is HTTP>
# }
#
```

For example:

```
itops-tco-116.lss.emc.com {
HostName = itops-tco-116.lss.emc.com
}
```

c. If your deployment has multiple M&R hosts (in case of multiple databases) which run the Web Service Backend, copy the code section in Step b and modify it accordingly.

d. Save the file.

2. Supply the EMC M&R login credentials for the OTM Next Generation WDM Manager.

a. Open the **Service Assurance Manager Global Console** attached to the OTM Next Generation WDM Manager (OTM-WDM-NG, for example).

b. In the **Topology Browser Console**, select **Configure › Domain Manager Administration Console**.

c. In the **Domain Manager Administration Console**, select **Configure › Polling and Thresholds**.

d. Select the **Device Access** tab.

e. Expand **EMC M&R Access Configuration › EMC M&R Access › Settings** and select **MnR Access Setting**.

f. Type the EMC M&R username (admin, for example) for the UserID field and the password for the Password field.

g. Click **Apply** to save the changes.

h. (Required) Reconfigure the OTM Next Generation WDM Manager.

Once you specify the EMC M&R login credentials, they persisted in the domain manager's repository in an encrypted format. Repeat this step only if the EMC M&R access credentials need to be changed.

Configure the RabbitMQ service for the OTM Next Generation WDM Domain Manager

To configure the RabbitMQ service for OTM Next Generation WDM Manager, you need to set the SM_AMQP_LOCATION environment variable in the runcmd_env.sh file and ensure the RabbitMQ security credentials are correct in the clientConnect.conf file. Perform these steps:

1. Specify the RabbitMQ location.

   The OTM Next Generation WDM Domain Manager receives events from EMC M&R though the RabbitMQ service. The default RabbitMQ service which is part of the EMC Smarts Service Assurance manager is used for this purpose. You need to set SM_AMQP_LOCATION environment variable in the OTM runcmd_env.sh file.

   a. Go to the *BASEDIR/smarts/bin* directory and enter this command to open the runcmd_env.sh file:

      ```
      sm_edit conf/runcmd_env.sh
      ```

   b. Add the SM_AMQP_LOCATION environment variable with the RabbitMQ location:

      ```
      SM_AMQP_URL=amqp://<host>:5672/
      ```

      The default AMQP port is 5672. If a different port is in use for some reason, use that port for the SM_AMQP_URL environment variable.

   c. Save and close the file.

2. Ensure the RabbitMQ credentials are correct.

   The security credentials for the RabbitMQ server are read from the OTM clientConnect.conf file.

   - If the default username or password is not changed in the RabbitMQ, this step is not required.
   - If the RabbitMQ credentials are changed for some reason, specify the new credentials in the OTM clientConnect.conf file.

   To do so, perform:

   a. Go to the *BASEDIR/smarts/bin* directory and enter this command to open the clientConnect.conf file:

      ```
      sm_edit conf/clientConnect.conf
      ```

   b. Add the following line in the clientConnect.conf file anywhere before the "*:*:admin:changeme" line at the end.

      ```
      *:AMQP-C/*:<username>:<password>
      ```

OTM-Extensions

The OTM-Extensions module is installed as part of the SAM installation. It provides additional OTM functionality to an existing installation of the Service Assurance Manager.

Configuration scenarios

There are multiple scenarios in which OTM can be configured with SAM. These are covered in the following sections:

- "Configuring OTM for a two-level hierarchical SAM" on page 166
- "Configuring OTM for a single SAM installation" on page 169
- "Configuring OTM for a three-level hierarchical SAM" on page 169

Configuring OTM for a two-level hierarchical SAM

Two-level hierarchy could mean either of the following scenarios:



Figure 4 Two-level hierarchical SAM: Scenario A



Figure 5 Two-level hierarchical SAM: Scenario B

In Scenario B, the SAM-AGG configuration is the same as that for SAM-OTM in Scenario A since this is the SAM that is directly attached to the OTM servers. Therefore, the configuration procedure is the same for both scenarios.

To configure OTM for a two-level hierarchical SAM, perform the following steps:

1. Create a directory for SAM-PRES. For purposes of this procedure, the term top-sam is used.
   a. cd {SAM BASEDIR}/smarts/local/conf
   b. mkdir top-sam
2. A new parameter *XDUpdateImpactList* is introduced. By setting this parameter to TRUE, a synchronization between SAM-PRES and SAM-OTM (in case of Figure 1) or SAM-PRES to SAM-AGG (in case of Figure 2) and SAM-OTM occurs whenever an OTM notification status update is detected for processing.

   From the {SAM BASEDIR}/smarts/local/conf/ics folder, edit the dxa-sam.conf file.

   Note: Modifying the dxa-sam.conf file is applicable in all instances where a top-level SAM installation communicates with an underlying SAM installation.

   a. Open dxa-sam.conf
   b. Add the following line to the end of the file:

      ```
      XDUpdateImpactList TRUE
      ```

   c. Save and close the file.

3. Traverse to the top-sam directory.
   a. cd {SAM BASEDIR}/smarts/local/conf/top-sam
4. Copy the contents of the {SAM BASEDIR}/smarts/conf/ics and {SAM BASEDIR}/smarts/local/conf/ics directories to the {SAM BASEDIR}/smarts/local/conf/top-sam directory.
   a. cp -p {SAM BASEDIR}/smarts/conf/ics/*.* .
   b. cp -p {SAM BASEDIR}/smarts/local/conf/ics/*.* .
5. In the top-sam directory, edit the dxa-sam.conf file.
   a. Open dxa-sam.conf using the sm_edit utility.
   b. Add these lines to the bottom of the file after the *"#Subscribe to a Notification List"* comment section.

```
# NLName/n
sub     Default/n
#sub    ALL_NOTIFICATIONS/n
notification
attr UserDefined1
attr UserDefined2
attr UserDefined3
attr UserDefined4
attr UserDefined5
attr UserDefined6
attr UserDefined7
attr UserDefined8
attr UserDefined9
attr UserDefined10
```

6. In the top-sam directory, you must copy the following lines to the weights.conf file.

Note: This step is applicable for all top-level SAM installations.

   a. Copy the following lines:

```
ClassWeight OpticalNetworkElement          0
ClassWeight TopologicalLink                0
NotificationClassWeight HighOrder_Circuit             1
NotificationClassWeight LowOrder_Circuit              1
NotificationClassWeight ClientCircuit                 1
NotificationClassCheck TopologicalLink
NotificationClassCheck DropSideTopologicalLink
NotificationClassCheck BBFiberLink
NotificationClassCheck BBTopologicalLink
NotificationClassCheck BBDropSideTopologicalLink
NotificationClassCheck Equipment
NotificationClassCheck Card
NotificationClassCheck EquipmentProtectionGroup
NotificationClassCheck FiberLink
NotificationClassCheck FiberBundle
NotificationClassCheck OpticalNetworkElement
NotificationClassCheck HighOrder_Trail
NotificationClassCheck LowOrder_Trail
NotificationClassCheck Transponder
NotificationClassCheck Amplifier
NotificationClassCheck PTP
NotificationClassCheck Conduit
```

   b. Open the weights.conf file using the sm_edit utility.

c. Paste the lines that you copied to the end of this file.

d. Save and close the file.

7. Restart the server for the new settings to take effect.

Note: This procedure is used as the baseline for other configuration scenarios in this appendix.

Configuring OTM for a single SAM installation



Figure 6 Single OTM and SAM installation

Note: The procedure for the standard two-level hierarchical SAM configuration, "Configuring OTM for a two-level hierarchical SAM" on page 166, is used as the baseline procedure for this configuration.

Perform step 6 from the standard two-level hierarchical SAM configuration to copy lines to the weights.conf file. Ignore the reference to the top-sam directory in this step.

Configuring OTM for a three-level hierarchical SAM

Three-level hierarchical SAM includes SAM-presentation, SAM-AGG (aggregate), and SAM-OTM (SAM to which OTM servers directly attach).



Figure 7 Three-level hierarchical SAM

In the three-level hierarchical configuration, SAM-Pres and SAM-AGG implementation could be:

- running out of the same installation (same SAM BASEDIR) or
- running out of separate installations (two separate SAM BASEDIRs).

Configuring SAM-Pres and SAM-AGG having same SAM BASEDIR

Note: The procedure for the standard two-level hierarchical SAM configuration, "Configuring OTM for a two-level hierarchical SAM" on page 166, is used as the baseline procedure for this configuration.

The following would be the differences from the standard two-level hierarchical SAM configuration and a three-level hierarchical SAM configuration using the same SAM {BASEDIR} to prepare the configuration.

Note: As in the two-level SAM hierarchical configuration, the SAM base installation will be considered to be the SAM-OTM area.

- Create and configure Presentation SAM by following the steps detailed in "Configuring OTM for a two-level hierarchical SAM" on page 166.
- Start the SAM-PRES (presentation level SAM) using the following command:

  ```
  ./sm_server -b <broker name & Port No> -n SAM-PRES -c top-sam
  --ignore-restore-errors --output --daemon
  ```

  Where top-sam is the name of the configuration directory created for SAM-PRES.

Configuring SAM-Pres and SAM-AGG having different SAM BASEDIRs

Note: The procedure for the standard two-level hierarchical SAM configuration, "Configuring OTM for a two-level hierarchical SAM" on page 166, is used as the baseline procedure for this configuration.

The following would be the differences between the standard two-level hierarchical SAM configuration and a three-level hierarchical SAM configuration using different SAM {BASEDIR}.

- The server to be used for SAM-OTM (1st level SAM) must have the configuration steps done that pertain to SAM-OTM from the two-level hierarchical configuration. See "Configuring OTM for a two-level hierarchical SAM" on page 166.
- The server to be used for SAM-AGG (2nd level SAM) must have the configuration steps done that pertain to top-sam directory level from the two-level hierarchical configuration. This configuration must be done in the BASEDIR area (/local/conf/ics) for this SAM installation. See "Configuring OTM for a two-level hierarchical SAM" on page 166.
- The server to be used for SAM-PRES (3rd level SAM) must have the configuration steps done that pertain to top-sam directory level from the two-level hierarchical configuration. This configuration would be done in the BASEDIR area (/local/conf/ics) for this SAM installation. See "Configuring OTM for a two-level hierarchical SAM" on page 166.

Note: When starting the three SAMs which could be located on different machines, care must be taken to use the same broker:port for all of them in the runcmd_env.sh files. For example "SM_BROKER_DEFAULT=machinename:6666", where machinename is the name of the machine, where the Broker and the OTM-SAM were started.

Configuring the Service Assurance Manager

Configure the Service Assurance Manager (Global Manager) to specify each Optical Transport Manager as its source:

1. In the Global Console attached to the Global Manager, select **Configure › Global Manager Administration Console** to open the Global Manager Administration Console.
2. In the left panel, select **ICS Configuration › IC Domain Configuration › Domains**.
3. Select the domain name for your Optical Transport Manager to display its configuration window (right panel). Depending upon your deployment, the domain names may include:
   - OTM-SDH-ANALYSIS
   - OTM-SDH-TOPOLOGY
   - OTM-PDH-ANALYSIS
   - OTM-PDH-TOPOLOGY
   - OTM-WDM-ANALYSIS

- OTM-WDM-TOPOLOGY
- OTM-IP-XD

4. In the configuration window, ensure that the **Enabled** checkbox is selected.

   If the **Enabled** checkbox is not selected:

   a. Select the **Enabled** checkbox.

   b. Click the **Reconfigure** button, then the **Yes** button.

   c. In the **Server Reconfiguration** information dialog box, click **Close**.

For complete information about the Global Manager Administration Console and Service Assurance configuration tasks, consult the *EMC Smarts Service Assurance Manager Configuration Guide*.

Configuring the presentation layer Global Manager

If you are deploying Optical Transport Manager in a hierarchical configuration, you will need to configure the presentation layer Global Manager as described in this section.

The hierarchical aggregation configuration shown in Figure 8 on page 173, uses multiple Global Managers at the aggregation layer to address the following configurations:

- **More than 10 underlying domains:** EMC Corporation recommends that each Global Manager at the aggregation layer supports a maximum of 10 EMC Smarts domains. The example in Figure 8 on page 173, therefore, could support 20 domains.
- **Geographically separate groups of domains**: Using a standard Global Manager configuration would force some domains to connect to a Global Manager over a high-latency link. Additional Global Managers at the aggregation layer would be located in the same geographical area as the domains.

To ensure that acknowledgements and ownership of notifications are properly propagated, Service Assurance clients should only connect to the Global Manager at the top-level, presentation layer.



Figure 8 Hierarchical aggregation Domain Manager configuration

Hierarchical aggregation is one example of hierarchical configuration.

The presentation layer Global Manager, or any Global Manager that does not connect directly to a OTM Domain Manager, needs to be configured using the following procedure to avoid duplicate OTM processing in the top level.

Note: This configuration should only be made to the top-level Global Manager or Managers, not the Global Managers which are directly connected to OTM servers.

Refer "Configuring OTM for a two-level hierarchical SAM" on page 166 for further instructions.

APPENDIX F
Configuration Scanner tool Sample Output

This appendix provides sample output for the Configuration Scanner tool. It consists of the following topics:

- Files created by Configuration Scanner tool 176
- Sample outputs 176

Files created by Configuration Scanner tool

The following files are created by the tool:

- sm_configscan_report-‹time_stamp›.txt: This is the report file created by the Configuration Scanner tool. This file contains:
  - List of files installed by the TTP, if any
  - List of files introduced by the user
  - Modifications made to the discovery.conf, tpmgr-param.conf and name-resolver.conf files
  - List of file differences for each modified file
  - List of modifications found in the server

  "Report when server is specified" on page 177 and "Report when server is not specified" on page 182 provides sample outputs.
- sm_configscan-‹time_stamp›.tar: This tar file contains the following:
  - A copy of the Configuration Scanner report file
  - sm_configscanner.log
  - A copy of runcmd_env.sh
  - ConfigScanAdapter.log
  - PnTallOutput.txt: lists all the settings found on the server
  - A directory containing the DIFF files for each modified files

The output files for the configuration scanner tool is available under the ‹**BASEDIR**›/smarts/local/logs/Final_sm_getinfo‹timesatamp›.tar file.

Sample outputs

This section provides sample outputs for the following:

- "Running Configuration Scanner tool with server name" on page 176
- "Report when server is specified" on page 177
- "Running Configuration Scanner tool without server name" on page 182
- "Report when server is not specified" on page 182

Running Configuration Scanner tool with server name

You can run the tool by specifying a running server in the command line. In this scenario, the tool scans for changes you have made in the values of both the polling and threshold settings and configuration files. A sample output is provided:

```
C:\InCharge\IP\smarts\bin>sm_perl sm_getinfo -s INCHARGE-AMPM -k
Executing sm_configscan ...
==============================================================sm_moni
   tor about to run!
Please enter the correct credentials in clientConnect.conf
Or be prepared to enter the credentials below:
```

```
=============================================================Getting
   hardware Info...
Getting AMPM show-dm-process info...
MAIN-N-Closing this log file at August 28, 2012 4:02:24 AM EDT;
   continuing in
C:\InCharge\IP\smarts\local\logs\AMPM-show-dm-proc-28Aug2012-040223_en
   _US_UTF-8.log
Getting AMPM stacktrace info...
Exiting eval via last at C:/InCharge/IP/smarts/bin//sm_monitor.pl line
   180.
Getting AMPM queues info...
Getting AMPM subscriptions info...
Getting AMPM threads info...
Getting AMPM flows info...
Getting AMPM clients info...
Getting netstat info...
Getting tasklist info...
Getting log file...
Getting rps files...
Getting Monitor...
Getting Accessor Ping...
Getting Accessor Poll...
Getting Problems...
Getting instrumentation for IP...
MAIN-N-Closing this log file at August 28, 2012 4:05:13 AM EDT;
   continuing in
C:\InCharge\IP\smarts\local\logs\AMPM-instrumentation-28Aug2012-040223
   _en_US_UTF-8.log
Deleting files:
   C:\InCharge\IP\smarts\local\logs\smgetinfo_files\*smgetinfo-version
   s.log*
Getting the Smarts server version ...
Getting the Executable versions ...
Getting the Local lib versions ...
Getting the lib versions ...
Getting the list of installed TTPs ...
No TTPs currently installed
No patches currently installed.
Archiving the files...
Writing to sm_getinfo28Aug2012-040132.tar.zip ...
... Done writing to Final_sm_getinfo28Aug2012-040132.tar.zip
Please send the file:
   C:\InCharge\IP\smarts\local\logs\Final_sm_getinfo28Aug2012-040132.t
   ar.zip to EMC Support
```

Report when server is specified

The following is the sample of the report when the tool is run specifying a running server in the command line:

```
Version: IP.9.1.0.0
These files have been modified in the installation:
=====================================================
C:/InCharge/IP/smarts/local/conf/discovery/discovery.conf
C:/InCharge/IP/smarts/local/conf/discovery/name-resolver.conf
C:/InCharge/IP/smarts/local/conf/discovery/oid2type_Cisco.conf
C:/InCharge/IP/smarts/local/conf/discovery/oid2type_Misc.conf
C:/InCharge/IP/smarts/local/conf/discovery/tpmgr-param.conf
These files have been introduced in the installation:
=====================================================
C:/InCharge/IP/smarts/local/repos/icf/INCHARGE-AMPM.rps
C:/InCharge/IP/smarts/local/repos/icf/INCHARGE-AMPM.rps.bak
Server Name: INCHARGE-AMPM
The following Polling and Threshold settings were modified in the
   installation:
```

```
==========================================================
POLLING::Polling Groups::5620 SAM Managed Systems::Connectivity
   Polling - External Poller::InstrumentCards
  Current Value : TRUE
  Default Value : FALSE
POLLING::Polling Groups::ComputeFabric::Environment
   Polling::PollingInterval
  Current Value : 120
  Default Value : 240
POLLING::Polling Groups::ComputeFabric::Environment Polling::Retries
  Current Value : 4
  Default Value : 3
POLLING::Polling Groups::ComputeFabric::Connectivity
   Polling::PollingInterval
  Current Value : 30
  Default Value : 240
POLLING::Polling Groups::Routers::Environment Polling::PollingInterval
  Current Value : 30
  Default Value : 240
THRESHOLD::Interface Groups::1 Gb Ethernet::Ethernet Interface/Port
   Performance::BroadcastThreshold
  Current Value : 10
  Default Value : 15
The following changes were made to some special configuration files:
==========================================================
File: C:/InCharge/IP/smarts/local/conf/discovery/discovery.conf
  Attribute Name : MetroEthernetEnabled
    Current Value  : TRUE
    Default Value  : FALSE
    Comment        : Modified
  Attribute Name : defaultTimeout
    Current Value  : 2000
    Default Value  : 1000
    Comment        : Modified
  Attribute Name : defaultRetries
    Current Value  : 8
    Default Value  : 5
    Comment        : Modified
  Attribute Name : defaultSNMPAutoRetries
    Current Value  : 4
    Default Value  : 3
    Comment        : Modified
  Attribute Name : DiscoveryAddrPref
    Current Value  : "IPV4FIRST_IPV6NEXT"
    Default Value  : "IPV6FIRST_IPV4NEXT"
    Comment        : Modified
  Attribute Name : numberProbeThreads
    Current Value  : 15
    Default Value  : 10
    Comment        : Modified
  Attribute Name : LicenseThresholdPercentage
    Current Value  : 40
    Default Value  : 90
    Comment        : Modified
File: C:/InCharge/IP/smarts/local/conf/discovery/name-resolver.conf
  Attribute Name : NameFormat
    Current Value  : "TM_USESEEDNAME"
    Default Value  : "TM_USEAUTONAME"
    Comment        : Modified
  Attribute Name : TM_USEAGENTADDRESS
    Current Value  : 3
    Default Value  : 4
    Comment        : Modified
  Attribute Name : TM_USEPRIVATEIP
    Current Value  : 4
    Default Value  : 3
```

```
    Comment        : Modified
File: C:/InCharge/IP/smarts/local/conf/discovery/tpmgr-param.conf
  Attribute Name : maxOIDsPerPacketForASNMP
    Current Value  : 15
    Default Value  : 19
    Comment        : Modified
  Attribute Name : GetBulkPattern-.1.3.6.1.4.1.1872.1.15
    Current Value  : TRUE
    Default Value  :
    Comment        : Newly added
  Attribute Name : GetBulkRetriesOverrideRatio-.1.3.6.1.4.1.1872.1.15
    Current Value  : 1.5
    Default Value  :
    Comment        : Newly added
  Attribute Name : GetBulkTimeoutOverrideRatio-.1.3.6.1.4.1.1872.1.15
    Current Value  : 2.5
    Default Value  :
    Comment        : Newly added
  Attribute Name : IFTypePatternIFExt.1.3.6.1.4.1.119.1.3.13.4
    Current Value  :
    Default Value  : 39|53|1
    Comment        : Removed
  Attribute Name : IFTypePattern-SwitchPort.1.3.6.1.4.1.119.1.14.8
    Current Value  :
    Default Value  : 37
    Comment        : Removed
The following are two way text differences:
==========================================
<--- C:/InCharge/IP/smarts/conf/discovery/discovery.conf --->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 54 to 54 >>>>>>>>>>>>>>
defaultRetries = 5
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 54 to 54 <<<<<<<<<<<<<<
defaultRetries = 8
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 61 to 61 >>>>>>>>>>>>>>
defaultTimeout = 1000
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 61 to 61 <<<<<<<<<<<<<<
defaultTimeout = 2000
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 82 to 82 >>>>>>>>>>>>>>
defaultSNMPAutoRetries = 3
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 82 to 82 <<<<<<<<<<<<<<
defaultSNMPAutoRetries = 4
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 97 to 97 >>>>>>>>>>>>>>
numberProbeThreads = 10
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 97 to 97 <<<<<<<<<<<<<<
numberProbeThreads = 15
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 280 to 280 >>>>>>>>>>>>>>
DiscoveryAddrPref =  "IPV6FIRST_IPV4NEXT"
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
```

```
<<<<<<<<<<<<<< From line: 280 to 280 <<<<<<<<<<<<<<
DiscoveryAddrPref =  "IPV4FIRST_IPV6NEXT"
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 287 to 287 >>>>>>>>>>>>>>
MetroEthernetEnabled = FALSE
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 287 to 287 <<<<<<<<<<<<<<
MetroEthernetEnabled = TRUE
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 290 to 290 >>>>>>>>>>>>>>
LicenseThresholdPercentage = 90
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 290 to 290 <<<<<<<<<<<<<<
LicenseThresholdPercentage = 40
<=============== End Difference ===============>
<------------------------------------------------>
<--- C:/InCharge/IP/smarts/conf/discovery/name-resolver.conf --->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 19 to 18 >>>>>>>>>>>>>>
#NameFormat = "TM_USESEEDNAME"
NameFormat = "TM_USEAUTONAME"
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 18 to 19 <<<<<<<<<<<<<<
NameFormat = "TM_USESEEDNAME"
#NameFormat = "TM_USEAUTONAME"
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 30 to 29 >>>>>>>>>>>>>>
AutoNameOrder 3 TM_USEPRIVATEIP
AutoNameOrder 4 TM_USEAGENTADDRESS
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 29 to 30 <<<<<<<<<<<<<<
AutoNameOrder 3 TM_USEAGENTADDRESS
AutoNameOrder 4 TM_USEPRIVATEIP
<=============== End Difference ===============>
<------------------------------------------------>
<--C:/InCharge/IP/smarts/conf/discovery/oid2type_Cisco.conf ->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 12369 to 12370 >>>>>>>>>>>>>>
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 12370 to 12384 <<<<<<<<<<<<<<
.1.3.6.1.4.1.9.1.916 {
TYPE = Firewall
VENDOR = Cisco
MODEL = ciscoASA5580sc
CERTIFICATION = CERTIFIED
CONT = Cisco-Entity
HEALTH = Cisco-Entity
INSTRUMENTATION:
CPU/Memory = CiscoRouter:DeviceID
Interface-Fault = MIB2
Interface-Performance = MIB2
}
<=============== End Difference ===============>
<------------------------------------------------>
<--C:/InCharge/IP/smarts/conf/discovery/oid2type_Misc.conf -->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 8816 to 8806 >>>>>>>>>>>>>>
```

```
.1.3.6.1.4.1.10734.1.3.8 {
TYPE = Firewall
VENDOR = TippingPoint
MODEL = TippingPointIPS
CERTIFICATION = CERTIFIED
CONT = MIB2-IfStack
INSTRUMENTATION:
Interface-Fault = MIB2
Interface-Performance     = MIB2
}
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 8806 to 8816 <<<<<<<<<<<<<<
#.1.3.6.1.4.1.10734.1.3.8 {
# TYPE = Firewall
# VENDOR = TippingPoint
# MODEL = TippingPointIPS
# CERTIFICATION = CERTIFIED
# CONT = MIB2-IfStack
#
#INSTRUMENTATION:
# Interface-Fault = MIB2
# Interface-Performance = MIB2
#}
<================ End Difference ================>
<------------------------------------------------------------>
<--C:/InCharge/IP/smarts/conf/discovery/tpmgr-param.conf --->
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 40 to 40 >>>>>>>>>>>>>>>
IFTypePatternIFExt.1.3.6.1.4.1.119.1.3.13.4 39|53|1
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 40 to 40 <<<<<<<<<<<<<<
#IFTypePatternIFExt.1.3.6.1.4.1.119.1.3.13.4 39|53|1
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 125 to 125 >>>>>>>>>>>>>>>
IFTypePattern-SwitchPort.1.3.6.1.4.1.119.1.14.8 37
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 125 to 125 <<<<<<<<<<<<<<
#IFTypePattern-SwitchPort.1.3.6.1.4.1.119.1.14.8 37
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 554 to 554 >>>>>>>>>>>>>>>
#GetBulkPattern-.1.3.6.1.4.1.1872.1.15 TRUE
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 554 to 554 <<<<<<<<<<<<<<
GetBulkPattern-.1.3.6.1.4.1.1872.1.15 TRUE
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 565 to 565 >>>>>>>>>>>>>>>
#GetBulkTimeoutOverrideRatio-.1.3.6.1.4.1.1872.1.15 2.5
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 565 to 565 <<<<<<<<<<<<<<
GetBulkTimeoutOverrideRatio-.1.3.6.1.4.1.1872.1.15 2.5
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 576 to 576 >>>>>>>>>>>>>>>
#GetBulkRetriesOverrideRatio-.1.3.6.1.4.1.1872.1.15 1.5
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 576 to 576 <<<<<<<<<<<<<<
GetBulkRetriesOverrideRatio-.1.3.6.1.4.1.1872.1.15 1.5
<================ End Difference ================>
```

```
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 582 to 582 >>>>>>>>>>>>>>
maxOIDsPerPacketForASNMP 19
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 582 to 582 <<<<<<<<<<<<<<
maxOIDsPerPacketForASNMP 15
<=============== End Difference ===============>
<------------------------------------------------>
```

Running Configuration Scanner tool without server name

You can run the tool without specifying a running server in the command line. In this scenario, the tool only scans for changes you made to the configuration files. A sample output is provided:

```
C:\InCharge\IP\smarts\bin>sm_perl sm_getinfo -k
Executing sm_configscan ...
Deleting files:
   C:\InCharge\IP\smarts\local\logs\smgetinfo_files\*smgetinfo-version
   s.log*
Getting the Smarts server version ...
Getting the Executable versions ...
Getting the Local lib versions ...
Getting the lib versions ...
Getting the list of installed TTPs ...
No TTPs currently installed
No patches currently installed.
Archiving the files...
Writing to sm_getinfo28Aug2012-044639.tar.zip ...
... Done writing to Final_sm_getinfo28Aug2012-044639.tar.zip
Please send the file:
   C:\InCharge\IP\smarts\local\logs\Final_sm_getinfo28Aug2012-044639.t
   ar.zip to EMC Support
```

Report when server is not specified

The following is the sample of the report when the tool is run without specifying a running server in the command line:

```
Version: IP.9.1.0.0
These files have been modified in the installation:
====================================================
C:/InCharge/IP/smarts/local/conf/discovery/discovery.conf
C:/InCharge/IP/smarts/local/conf/discovery/name-resolver.conf
C:/InCharge/IP/smarts/local/conf/discovery/oid2type_Cisco.conf
C:/InCharge/IP/smarts/local/conf/discovery/oid2type_Misc.conf
C:/InCharge/IP/smarts/local/conf/discovery/tpmgr-param.conf
These files have been introduced in the installation:
====================================================
C:/InCharge/IP/smarts/local/repos/icf/INCHARGE-AMPM.rps
C:/InCharge/IP/smarts/local/repos/icf/INCHARGE-AMPM.rps.bak
The following changes were made to some special configuration files:
=================================================================
File: C:/InCharge/IP/smarts/local/conf/discovery/discovery.conf
  Attribute Name : MetroEthernetEnabled
    Current Value  : TRUE
    Default Value  : FALSE
    Comment        : Modified
  Attribute Name : defaultTimeout
    Current Value  : 2000
    Default Value  : 1000
    Comment        : Modified
  Attribute Name : defaultRetries
```

```
    Current Value  : 8
    Default Value  : 5
    Comment        : Modified
  Attribute Name : defaultSNMPAutoRetries
    Current Value  : 4
    Default Value  : 3
    Comment        : Modified
  Attribute Name : DiscoveryAddrPref
    Current Value  : "IPV4FIRST_IPV6NEXT"
    Default Value  : "IPV6FIRST_IPV4NEXT"
    Comment        : Modified
  Attribute Name : numberProbeThreads
    Current Value  : 15
    Default Value  : 10
    Comment        : Modified
  Attribute Name : LicenseThresholdPercentage
    Current Value  : 40
    Default Value  : 90
    Comment        : Modified
File: C:/InCharge/IP/smarts/local/conf/discovery/name-resolver.conf
  Attribute Name : NameFormat
    Current Value  : "TM_USESEEDNAME"
    Default Value  : "TM_USEAUTONAME"
    Comment        : Modified
  Attribute Name : TM_USEAGENTADDRESS
    Current Value  : 3
    Default Value  : 4
    Comment        : Modified
  Attribute Name : TM_USEPRIVATEIP
    Current Value  : 4
    Default Value  : 3
    Comment        : Modified

File: C:/InCharge/IP/smarts/local/conf/discovery/tpmgr-param.conf
  Attribute Name : maxOIDsPerPacketForASNMP
    Current Value  : 15
    Default Value  : 19
    Comment        : Modified
  Attribute Name : GetBulkPattern-.1.3.6.1.4.1.1872.1.15
    Current Value  : TRUE
    Default Value  :
    Comment        : Newly added
  Attribute Name : GetBulkRetriesOverrideRatio-.1.3.6.1.4.1.1872.1.15
    Current Value  : 1.5
    Default Value  :
    Comment        : Newly added
  Attribute Name : GetBulkTimeoutOverrideRatio-.1.3.6.1.4.1.1872.1.15
    Current Value  : 2.5
    Default Value  :
    Comment        : Newly added
  Attribute Name : IFTypePatternIFExt.1.3.6.1.4.1.119.1.3.13.4
    Current Value  :
    Default Value  : 39|53|1
    Comment        : Removed
  Attribute Name : IFTypePattern-SwitchPort.1.3.6.1.4.1.119.1.14.8
    Current Value  :
    Default Value  : 37
    Comment        : Removed
The following are two way text differences:
==========================================
<--- C:/InCharge/IP/smarts/conf/discovery/discovery.conf --->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 54 to 54 >>>>>>>>>>>>>>
defaultRetries = 5
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
```

```
<<<<<<<<<<<<<< From line: 54 to 54 <<<<<<<<<<<<<<
defaultRetries = 8
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 61 to 61 >>>>>>>>>>>>>>>
defaultTimeout = 1000
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 61 to 61 <<<<<<<<<<<<<<
defaultTimeout = 2000
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 82 to 82 >>>>>>>>>>>>>>>
defaultSNMPAutoRetries = 3
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 82 to 82 <<<<<<<<<<<<<<
defaultSNMPAutoRetries = 4
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 97 to 97 >>>>>>>>>>>>>>>
numberProbeThreads = 10
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 97 to 97 <<<<<<<<<<<<<<
numberProbeThreads = 15
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 280 to 280 >>>>>>>>>>>>>>>
DiscoveryAddrPref =  "IPV6FIRST_IPV4NEXT"
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 280 to 280 <<<<<<<<<<<<<<
DiscoveryAddrPref =  "IPV4FIRST_IPV6NEXT"
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 287 to 287 >>>>>>>>>>>>>>>
MetroEthernetEnabled = FALSE
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 287 to 287 <<<<<<<<<<<<<<
MetroEthernetEnabled = TRUE
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 290 to 290 >>>>>>>>>>>>>>>
LicenseThresholdPercentage = 90
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 290 to 290 <<<<<<<<<<<<<<
LicenseThresholdPercentage = 40
<=============== End Difference ===============>
<------------------------------------------------>
<--C:/InCharge/IP/smarts/conf/discovery/name-resolver.conf -->
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 19 to 18 >>>>>>>>>>>>>>>
#NameFormat = "TM_USESEEDNAME"
NameFormat = "TM_USEAUTONAME"
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 18 to 19 <<<<<<<<<<<<<<
NameFormat = "TM_USESEEDNAME"
#NameFormat = "TM_USEAUTONAME"
<=============== End Difference ===============>
<============== Start Difference ==============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 30 to 29 >>>>>>>>>>>>>>>
```

```
AutoNameOrder 3 TM_USEPRIVATEIP
AutoNameOrder 4 TM_USEAGENTADDRESS
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 29 to 30 <<<<<<<<<<<<<<
AutoNameOrder 3 TM_USEAGENTADDRESS
AutoNameOrder 4 TM_USEPRIVATEIP
<=============== End Difference ===============>
<------------------------------------------------>

<--C:/InCharge/IP/smarts/conf/discovery/oid2type_Cisco.conf-->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 12369 to 12370 >>>>>>>>>>>>>>
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 12370 to 12384 <<<<<<<<<<<<<<

.1.3.6.1.4.1.9.1.916 {
TYPE = Firewall
VENDOR = Cisco
MODEL = ciscoASA5580sc
CERTIFICATION = CERTIFIED
CONT = Cisco-Entity
HEALTH = Cisco-Entity

INSTRUMENTATION:
CPU/Memory = CiscoRouter:DeviceID
Interface-Fault = MIB2
Interface-Performance = MIB2
}
<=============== End Difference ===============>
<------------------------------------------------>
<--C:/InCharge/IP/smarts/conf/discovery/oid2type_Misc.conf -->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 8816 to 8806 >>>>>>>>>>>>>>
.1.3.6.1.4.1.10734.1.3.8 {
TYPE = Firewall
VENDOR = TippingPoint
MODEL = TippingPointIPS
CERTIFICATION = CERTIFIED
CONT = MIB2-IfStack

INSTRUMENTATION:
Interface-Fault           = MIB2
Interface-Performance     = MIB2
}
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 8806 to 8816 <<<<<<<<<<<<<<
#.1.3.6.1.4.1.10734.1.3.8 {
# TYPE = Firewall
# VENDOR = TippingPoint
# MODEL = TippingPointIPS
# CERTIFICATION = CERTIFIED
# CONT = MIB2-IfStack
#
#INSTRUMENTATION:
# Interface-Fault           = MIB2
# Interface-Performance     = MIB2
#}
<=============== End Difference ===============>
<------------------------------------------------>

<--C:/InCharge/IP/smarts/conf/discovery/tpmgr-param.conf --->
<============== Start Difference ==============>
>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>
>>>>>>>>>>>>>> From line: 40 to 40 >>>>>>>>>>>>>>
```

```
IFTypePatternIFExt.1.3.6.1.4.1.119.1.3.13.4 39|53|1
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 40 to 40 <<<<<<<<<<<<<<
#IFTypePatternIFExt.1.3.6.1.4.1.119.1.3.13.4 39|53|1
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 125 to 125 >>>>>>>>>>>>>>>
IFTypePattern-SwitchPort.1.3.6.1.4.1.119.1.14.8 37
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 125 to 125 <<<<<<<<<<<<<<
#IFTypePattern-SwitchPort.1.3.6.1.4.1.119.1.14.8 37
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 554 to 554 >>>>>>>>>>>>>>>
#GetBulkPattern-.1.3.6.1.4.1.1872.1.15 TRUE
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 554 to 554 <<<<<<<<<<<<<<
GetBulkPattern-.1.3.6.1.4.1.1872.1.15 TRUE
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 565 to 565 >>>>>>>>>>>>>>>
#GetBulkTimeoutOverrideRatio-.1.3.6.1.4.1.1872.1.15 2.5
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 565 to 565 <<<<<<<<<<<<<<
GetBulkTimeoutOverrideRatio-.1.3.6.1.4.1.1872.1.15 2.5
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 576 to 576 >>>>>>>>>>>>>>>
#GetBulkRetriesOverrideRatio-.1.3.6.1.4.1.1872.1.15 1.5
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 576 to 576 <<<<<<<<<<<<<<
GetBulkRetriesOverrideRatio-.1.3.6.1.4.1.1872.1.15 1.5
<================ End Difference ================>
<=============== Start Difference ===============>
>>>>>>>>>>>>>>> Base File Contents >>>>>>>>>>>>>>>
>>>>>>>>>>>>>>> From line: 582 to 582 >>>>>>>>>>>>>>>
maxOIDsPerPacketForASNMP 19
<<<<<<<<<<<<<< Local File Contents <<<<<<<<<<<<<<
<<<<<<<<<<<<<< From line: 582 to 582 <<<<<<<<<<<<<<
maxOIDsPerPacketForASNMP 15
<================ End Difference ================>
<------------------------------------------------>
```